

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP				PSE	NNU / NERC
BAL-001-0a	0.	Real Power Balancing Control Performance				X															CCR / RCCR		Adopted by NERC: 2005-02-08
BAL-001-0a	01.	Each Balancing Authority shall operate such that, on a rolling 12-month basis, the average of the clock-minute averages of the Balancing Authority's Area Control Error (ACE) divided by 10B (B is the clock-minute average of the Balancing Authority Area's Frequency Bias) times the corresponding clock-minute averages of the Interconnection's Frequency Error is less than a specific limit. This limit ϵ_1^2 is a constant derived from a targeted frequency bound (separately calculated for each Interconnection) that is reviewed and set as necessary by the NERC Operating Committee. The equation for ACE is: ACE = (NIA - NIS) - 10B (FA - FS) - IME (this section continues with other formula and data specs)				X															CCR / RCCR	NPCC C-08 NPCC B-02	BA
BAL-001-0a	02.	Each Balancing Authority shall operate such that its average ACE for at least 90% of clock ten-minute periods (6 non-overlapping periods per hour) during a calendar month is within a specific limit, referred to as L10. It is the targeted root-mean-square (RMS) value of ten-minute average Frequency Error based on frequency performance over a given year. The bound, ϵ_{10} , is the same for every Balancing Authority Area within an Interconnection, and Bs is the sum of the Frequency Bias Settings of the Balancing Authority Areas in the respective Interconnection. For Balancing Authority Areas with variable bias, this is equal to the sum of the minimum Frequency Bias Settings. (this section continues with other formulae and data specs)				X															CCR / RCCR	NPCC C-08	BA
BAL-001-0a	03.	Each BA providing Overlap Regulation Service shall evaluate Requirement R1 (CPS1) and Requirement R2 (CPS2) using the characteristics of the combined ACE and combined Frequency Bias Settings.				X															CCR / RCCR	NPCC A-06 NPCC C-08	Not applicable : this service is not available in Québec.
BAL-001-0a	04.	Any Balancing Authority receiving Overlap Regulation Service shall not have its control performance evaluated (i.e. from a control performance perspective, the Balancing Authority has shifted all control requirements to the Balancing Authority providing Overlap Regulation Service).				X															CCR / RCCR		Not applicable : this service is not available in Québec.
BAL-002-0	0.	Disturbance Control Performance	X			X		X													Main Transmission System		Adopted by NERC: 2005-02-08
BAL-002-0	01.	Each Balancing Authority shall have access to and/or operate Contingency Reserve to respond to Disturbances. Contingency Reserve may be supplied from generation, controllable load resources, or coordinated adjustments to Interchange Schedules.				X															Main Transmission System	NPCC A-06	BA
BAL-002-0	01.1	A Balancing Authority may elect to fulfill its Contingency Reserve obligations by participating as a member of a Reserve Sharing Group. In such cases, the Reserve Sharing Group shall have the same responsibilities and obligations as each Balancing Authority with respect to monitoring and meeting the requirements of Standard BAL-002.				X		X													Main Transmission System	NPCC A-06 NPCC C-12	Not applicable: no "RSG" in Québec.
BAL-002-0	02.	Each RRO, sub-Regional Reliability Organization or Reserve Sharing Group shall specify its Contingency Reserve policies, including:	X					X													Main Transmission System	NPCC A-06	Not applicable: no "RSG" in Québec.
BAL-002-0	02.1	The minimum reserve requirement for the group.	X					X													Main Transmission System	NPCC A-06	Not applicable: no "RSG" in Québec.
BAL-002-0	02.2	Its allocation among members	X					X													Main Transmission System	NPCC A-06	Not applicable: no "RSG" in Québec.
BAL-002-0	02.3	The permissible mix of Operating Reserve – Spinning and Operating Reserve – Supplemental that may be included in Contingency Reserve.	X					X													Main Transmission System	NPCC A-06	Not applicable: no "RSG" in Québec.
BAL-002-0	02.4	The procedure for applying Contingency Reserve in practice.	X					X													Main Transmission System	NPCC A-06	Not applicable: no "RSG" in Québec.
BAL-002-0	02.5	The limitations, if any, upon the amount of interruptible load that may be included.	X					X													Main Transmission System		Not applicable: no "RSG" in Québec.
BAL-002-0	02.6	The same portion of resource capacity (e.g. reserves from jointly owned generation) shall not be counted more than once as Contingency Reserve by multiple Balancing Authorities.	X					X													Main Transmission System	NPCC A-06	Not applicable: no "RSG" in Québec.
BAL-002-0	03.	Each Balancing Authority or Reserve Sharing Group shall activate sufficient Contingency Reserve to comply with the DCS.				X		X													Main Transmission System	NPCC C-09	BA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
BAL-002-0	03.1	As a minimum, the Balancing Authority or Reserve Sharing Group shall carry at least enough Contingency Reserve to cover the most severe single contingency. All Balancing Authorities and Reserve Sharing Groups shall review, no less frequently than annually, their probable contingencies to determine their prospective most severe single contingencies.				X		X														Main Transmission System	NPCC A-06	BA
BAL-002-0	04.	A Balancing Authority or Reserve Sharing Group shall meet the Disturbance Recovery Criterion within the Disturbance Recovery Period (DCS) for 100% of Reportable Disturbances. The Disturbance Recovery Criterion is:				X		X														Main Transmission System	NPCC A-06	BA
BAL-002-0	04.1	A Balancing Authority shall return its ACE to zero if its ACE just prior to the Reportable Disturbance was positive or equal to zero. For negative initial ACE values just prior to the Disturbance, the Balancing Authority shall return ACE to its pre-Disturbance value.				X																Main Transmission System	NPCC A-06	BA
BAL-002-0	05.	Each Reserve Sharing Group shall comply with the DCS. A Reserve Sharing Group shall be considered in a Reportable Disturbance condition whenever a group member has experienced a Reportable Disturbance and calls for the activation of Contingency Reserves from one or more other group members. (If a group member has experienced a Reportable Disturbance but does not call for reserve activation from other members of the Reserve Sharing Group, then that member shall report as a single Balancing Authority.) Compliance may be demonstrated by either of the following two methods:				X		X														Main Transmission System	NPCC A-06 NPCC C-12	<i>Not applicable: no "RSG" in Québec.</i>
BAL-002-0	05.1	The Reserve Sharing Group reviews group ACE (or equivalent) and demonstrates compliance to the DCS. To be in compliance, the group ACE (or its equivalent) must meet the Disturbance Recovery Criterion after the schedule change(s) related to reserve sharing have been fully implemented, and within the Disturbance Recovery Period, or						X														Main Transmission System	NPCC A-06 NPCC C-12	<i>Not applicable: no "RSG" in Québec</i>
BAL-002-0	05.2	The Reserve Sharing Group reviews each member's ACE in response to the activation of reserves. To be in compliance, a member's ACE (or its equivalent) must meet the Disturbance Recovery Criterion after the schedule change(s) related to reserve sharing have been fully implemented, and within the Disturbance Recovery Period.						X														Main Transmission System	NPCC A-06 NPCC C-12	<i>Not applicable: no "RSG" in Québec.</i>
BAL-002-0	06.	A Balancing Authority or Reserve Sharing Group shall fully restore its Contingency Reserves within the Contingency Reserve Restoration Period for its Interconnection.				X		X														Main Transmission System	NPCC A-06	BA
BAL-002-0	06.1	The Contingency Reserve Restoration Period begins at the end of the Disturbance Recovery Period.				X		X														Main Transmission System	NPCC A-06 NPCC C-09	BA
BAL-002-0	06.2	The default Contingency Reserve Restoration Period is 90 minutes. This period may be adjusted to better suit the reliability targets of the Interconnection based on analysis approved by the NERC Operating Committee.				X		X														Main Transmission System	NPCC A-06	BA
BAL-003-0a	0.	Frequency Response and Bias				X																CCR / RCCR		Adopted by NERC: 2005-02-08
BAL-003-0a	01.	Each Balancing Authority shall review its Frequency Bias Settings by January 1 of each year and recalculate its setting to reflect any change in the Frequency Response of the Balancing Authority Area.				X																CCR / RCCR		BA
BAL-003-0a	01.1	The Balancing Authority may change its Frequency Bias Setting, and the method used to determine the setting, whenever any of the factors used to determine the current bias value change.				X																CCR / RCCR		BA
BAL-003-0a	01.2	Each Balancing Authority shall report its Frequency Bias Setting, and method for determining that setting, to the NERC Operating Committee.				X																CCR / RCCR		BA
BAL-003-0a	02.	Each Balancing Authority shall establish and maintain a Frequency Bias Setting that is as close as practical to, or greater than, the Balancing Authority's Frequency Response. Frequency Bias may be calculated several ways:				X																CCR / RCCR		BA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities					
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC				
BAL-003-0a	02.1	The Balancing Authority may use a fixed Frequency Bias value which is based on a fixed, straight-line function of Tie Line deviation versus Frequency Deviation. The Balancing Authority shall determine the fixed value by observing and averaging the Frequency Response for several Disturbances during on-peak hours.				X																		CCR / RCCR		BA	
BAL-003-0a	02.2	The Balancing Authority may use a variable (linear or non-linear) bias value, which is based on a variable function of Tie Line deviation to Frequency Deviation. The Balancing Authority shall determine the variable frequency bias value by analyzing Frequency Response as it varies with factors such as load, generation, governor characteristics, and frequency.				X																			CCR / RCCR		BA
BAL-003-0a	03.	Each Balancing Authority shall operate its Automatic Generation Control (AGC) on Tie Line Frequency Bias, unless such operation is adverse to system or Interconnection reliability.				X																			CCR / RCCR		BA <i>Québec specific: System operated asynchronously and ACE calculated only with frequency components.</i>
BAL-003-0a	04.	Balancing Authorities that use Dynamic Scheduling or Pseudo-ties for jointly owned units shall reflect their respective share of the unit governor droop response in their respective Frequency Bias Setting.				X																			CCR / RCCR		<i>Not applicable: there is no "JOU" nor Dynamic schedule in Québec.</i>
BAL-003-0a	04.1	Fixed schedules for Jointly Owned Units mandate that Balancing Authority (A) that contains the Jointly Owned Unit must incorporate the respective share of the unit governor droop response for any Balancing Authorities that have fixed schedules (B and C). See the diagram below.				X																			CCR / RCCR		<i>Not applicable: there is no "JOU" in Québec.</i>
BAL-003-0a	04.2	The Balancing Authorities that have a fixed schedule (B and C) but do not contain the Jointly Owned Unit shall not include their share of the governor droop response in their Frequency Bias Setting.				X																			CCR / RCCR		<i>Not applicable: there is no "JOU" nor Dynamic schedule in Québec.</i>
BAL-003-0a	05.	Balancing Authorities that serve native load shall have a monthly average Frequency Bias Setting that is at least 1% of the Balancing Authority's estimated yearly peak demand per 0.1 Hz change.				X																			CCR / RCCR		BA
BAL-003-0a	05.1	Balancing Authorities that do not serve native load shall have a monthly average Frequency Bias Setting that is at least 1% of its estimated maximum generation level in the coming year per 0.1 Hz change.				X																			CCR / RCCR		BA <i>Note: the Québec BA serves native load.</i>
BAL-003-0a	06.	A Balancing Authority that is performing Overlap Regulation Service shall increase its Frequency Bias Setting to match the frequency response of the entire area being controlled. A Balancing Authority shall not change its Frequency Bias Setting when performing Supplemental Regulation Service.				X																			CCR / RCCR		<i>Not applicable: This service is not available in Québec.</i>
BAL-004-0	0.	Time Error Correction		X		X																			CCR / RCCR		Adopted by NERC: 2005-02-08
BAL-004-0	01.	Only a Reliability Coordinator shall be eligible to act as Interconnection Time Monitor. A single Reliability Coordinator in each Interconnection shall be designated by the NERC Operating Committee to serve as Interconnection Time Monitor.		X																					CCR / RCCR		RC
BAL-004-0	02.	The Interconnection Time Monitor shall monitor Time Error and shall initiate or terminate corrective action orders in accordance with the NAESB Time Error Correction Procedure.		X																					CCR / RCCR		RC
BAL-004-0	03.	Each Balancing Authority, when requested, shall participate in a Time Error Correction by one of the following methods:				X																			CCR / RCCR	NPCC RRP	BA
BAL-004-0	03.1	The Balancing Authority shall offset its frequency schedule by 0.02 Hertz, leaving the Frequency Bias Setting normal; or				X																			CCR / RCCR		BA
BAL-004-0	03.2	The Balancing Authority shall offset its Net Interchange Schedule (MW) by an amount equal to the computed bias contribution during a 0.02 Hertz Frequency Deviation (i.e. 20% of the Frequency Bias Setting).				X																			CCR / RCCR		BA
BAL-004-0	04.	Any Reliability Coordinator in an Interconnection shall have the authority to request the Interconnection Time Monitor to terminate a Time Error Correction in progress, or a scheduled Time Error Correction that has not begun, for reliability considerations.		X																					CCR / RCCR	NPCC RRP	RC

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
BAL-004-0	04.1	Balancing Authorities that have reliability concerns with the execution of a Time Error Correction shall notify their Reliability Coordinator and request the termination of a Time Error Correction in progress.		X		X															CCR / RCCR	NPCC C-03	BA, RC
BAL-005-0b	0.	Automatic Generation Control			X	X						X				X					All Québec Interconnection Facilities		Adopted by NERC: 2005-02-08
BAL-005-0b	01.	All generation, transmission, and load operating within an Interconnection must be included within the metered boundaries of a Balancing Authority Area.			X	X						X				X					All Québec Interconnection Facilities Any facilities directly connected to HQT System or through non public Regional System meet this requirement.	NPCC A-03	BA, TOP GOP-1, GOP-2, GOP-3 LSE-1, LSE-2
BAL-005-0b	01.1	Each Generator Operator with generation facilities operating in an Interconnection shall ensure that those generation facilities are included within the metered boundaries of a Balancing Authority Area.										X									All Québec Interconnection Facilities Any facilities directly connected to HQT System or through non public Regional System meet this requirement.	NPCC A-03	GOP-1, GOP-2, GOP-3
BAL-005-0b	01.2	Each Transmission Operator with transmission facilities operating in an Interconnection shall ensure that those transmission facilities are included within the metered boundaries of a Balancing Authority Area.			X																All Québec Interconnection Facilities Any facilities directly connected to HQT System or through non public Regional System meet this requirement.	NPCC A-03	TOP
BAL-005-0b	01.3	Each Load-Serving Entity with load operating in an Interconnection shall ensure that those loads are included within the metered boundaries of a Balancing Authority Area.														X					All Québec Interconnection Facilities Any facilities directly connected to HQT System or through non public Regional System meet this requirement.	NPCC A-03	LSE-1, LSE-2
BAL-005-0b	02.	Each Balancing Authority shall maintain Regulating Reserve that can be controlled by AGC to meet the Control Performance Standard.				X															All Québec Interconnection Facilities	NPCC A-06	BA
BAL-005-0b	03.	A Balancing Authority providing Regulation Service shall ensure that adequate metering, communications, and control equipment are employed to prevent such service from becoming a Burden on the Interconnection or other Balancing Authority Areas.				X															All Québec Interconnection Facilities	NPCC A-03	BA
BAL-005-0b	04.	A Balancing Authority providing Regulation Service shall notify the Host Balancing Authority for whom it is controlling if it is unable to provide the service, as well as any Intermediate Balancing Authorities.				X															All Québec Interconnection Facilities	NPCC A-03	BA
BAL-005-0b	05.	A Balancing Authority receiving Regulation Service shall ensure that backup plans are in place to provide replacement Regulation Service should the supplying Balancing Authority no longer be able to provide this service.				X															All Québec Interconnection Facilities	NPCC RRP	BA
BAL-005-0b	06.	The Balancing Authority's AGC shall compare total Net Actual Interchange to total Net Scheduled Interchange plus Frequency Bias obligation to determine the Balancing Authority's ACE. Single Balancing Authorities operating asynchronously may employ alternative ACE calculations such as (but not limited to) flat frequency control. If a Balancing Authority is unable to calculate ACE for more than 30 minutes it shall notify its Reliability Coordinator.				X															All Québec Interconnection Facilities		BA
BAL-005-0b	07.	The Balancing Authority shall operate AGC continuously unless such operation adversely impacts the reliability of the Interconnection. If AGC has become inoperative, the Balancing Authority shall use manual control to adjust generation to maintain the Net Scheduled Interchange.				X															All Québec Interconnection Facilities	NPCC A-03	BA
BAL-005-0b	08.	The Balancing Authority shall ensure that data acquisition for and calculation of ACE occur at least every six seconds.				X															All Québec Interconnection Facilities		BA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities			
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC		
BAL-005-0b	08.1	Each Balancing Authority shall provide redundant and independent frequency metering equipment that shall automatically activate upon detection of failure of the primary source. This overall installation shall provide a minimum availability of 99.95%.				X																All Québec Interconnection Facilities		BA	
BAL-005-0b	09.	The Balancing Authority shall include all Interchange Schedules with Adjacent Balancing Authorities in the calculation of Net Scheduled Interchange for the ACE equation.				X																	All Québec Interconnection Facilities		BA <i>Québec specific: System operated asynchronously and ACE calculated only with frequency components.</i>
BAL-005-0b	09.1	Balancing Authorities with a high voltage direct current (HVDC) link to another Balancing Authority connected asynchronously to their Interconnection may choose to omit the Interchange Schedule related to the HVDC link from the ACE equation if it is modeled as internal generation or load.				X																	All Québec Interconnection Facilities		BA
BAL-005-0b	10.	The Balancing Authority shall include all Dynamic Schedules in the calculation of Net Scheduled Interchange for the ACE equation.				X																	All Québec Interconnection Facilities		<i>Not applicable: this service is not available in Québec.</i>
BAL-005-0b	11.	Balancing Authorities shall include the effect of ramp rates, which shall be identical and agreed to between affected Balancing Authorities, in the Scheduled Interchange values to calculate ACE.				X																	All Québec Interconnection Facilities		BA
BAL-005-0b	12.	Each Balancing Authority shall include all Tie Line flows with Adjacent Balancing Authority Areas in the ACE calculation.				X																	All Québec Interconnection Facilities		BA
BAL-005-0b	12.1	Balancing Authorities that share a tie shall ensure Tie Line MW metering is telemetered to both control centers, and emanates from a common, agreed-upon source using common primary metering equipment. Balancing Authorities shall ensure that megawatt-hour data is telemetered or reported at the end of each hour.				X																	All Québec Interconnection Facilities		BA
BAL-005-0b	12.2	Balancing Authorities shall ensure the power flow and ACE signals that are utilized for calculating Balancing Authority performance or that are transmitted for Regulation Service are not filtered prior to transmission, except for the Anti-aliasing Filters of Tie Lines.				X																	All Québec Interconnection Facilities		BA
BAL-005-0b	12.3	Balancing Authorities shall install common metering equipment where Dynamic Schedules or Pseudo-Ties are implemented between two or more Balancing Authorities to deliver the output of Jointly Owned Units or to serve remote load.				X																	All Québec Interconnection Facilities		<i>Not applicable: there is no "JOU" nor Dynamic schedule in Québec.</i>
BAL-005-0b	13.	Each Balancing Authority shall perform hourly error checks using Tie Line megawatt-hour meters with common time synchronization to determine the accuracy of its control equipment. The Balancing Authority shall adjust the component (e.g., Tie Line meter) of ACE that is in error (if known) or use the interchange meter error (IME) term of the ACE equation to compensate for any equipment error until repairs can be made.				X																	All Québec Interconnection Facilities		BA
BAL-005-0b	14.	The Balancing Authority shall provide its operating personnel with sufficient instrumentation and data recording equipment to facilitate monitoring of control performance, generation response, and after-the-fact analysis of area performance. As a minimum, the Balancing Authority shall provide its operating personnel with real-time values for ACE, Interconnection frequency and Net Actual Interchange with each Adjacent Balancing Authority Area.				X																	All Québec Interconnection Facilities	NPCC A-03 NPCC C-25	BA
BAL-005-0b	15.	The Balancing Authority shall provide adequate and reliable backup power supplies and shall periodically test these supplies at the Balancing Authority's control center and other critical locations to ensure continuous operation of AGC and vital data recording equipment during loss of the normal power supply.				X																	Load-Frequency Controller (LFC) and Generating station under the control of LFC	NPCC RRP	BA
BAL-005-0b	16.	The Balancing Authority shall sample data at least at the same periodicity with which ACE is calculated. The Balancing Authority shall flag missing or bad data for operator display and archival purposes. The Balancing Authority shall collect coincident data to the greatest practical extent, i.e., ACE, Interconnection frequency, Net Actual Interchange, and other data shall all be sampled at the same time.				X																	All Québec Interconnection Facilities		BA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
BAL-005-0b	17.	Each Balancing Authority shall at least annually check and calibrate its time error and frequency devices against a common reference. The Balancing Authority shall adhere to the minimum values for measuring devices as listed below: (see the standard for devices and required accuracy)				X																All Québec Interconnection Facilities		BA
BAL-006-1	0.	Inadvertent Interchange				X																Main Transmission System		Adopted by NERC: 2006-05-02
BAL-006-1	01.	Each Balancing Authority shall calculate and record hourly Inadvertent Interchange.				X																Main Transmission System		BA
BAL-006-1	02.	Each Balancing Authority shall include all AC tie lines that connect to its Adjacent Balancing Authority Areas in its Inadvertent Interchange account. The Balancing Authority shall take into account interchange served by jointly owned generators.				X																Main Transmission System		BA
BAL-006-1	03.	Each Balancing Authority shall ensure all of its Balancing Authority Area interconnection points are equipped with common megawatt-hour meters, with readings provided hourly to the control centers of Adjacent Balancing Authorities.				X																Main Transmission System		BA
BAL-006-1	04.	Adjacent Balancing Authority Areas shall operate to a common Net Interchange Schedule and Actual Net Interchange value and shall record these hourly quantities, with like values but opposite sign. Each Balancing Authority shall compute its Inadvertent Interchange based on the following:				X																Main Transmission System		BA
BAL-006-1	04.1	Each Balancing Authority, by the end of the next business day, shall agree with its Adjacent Balancing Authorities to:				X																Main Transmission System		BA
BAL-006-1	04.1.1	The hourly values of Net Interchange Schedule.				X																Main Transmission System		BA
BAL-006-1	04.1.2	The hourly integrated megawatt-hour values of Net Actual Interchange.				X																Main Transmission System		BA
BAL-006-1	04.2	Each Balancing Authority shall use the agreed-to daily and monthly accounting data to compile its monthly accumulated Inadvertent Interchange for the On-Peak and Off- Peak hours of the month.				X																Main Transmission System		BA
BAL-006-1	04.3	A BA shall make after-the-fact corrections to the agreed-to daily and monthly accounting data only as needed to reflect actual operating conditions (e.g. a meter being used for control was sending bad data). Changes or corrections based on non-reliability considerations shall not be reflected in the BA's Inadvertent Interchange. After-the-fact corrections to scheduled or actual values will not be accepted without agreement of the Adjacent BA(s).				X																Main Transmission System		BA
BAL-006-1	05.	Adjacent BAs that cannot mutually agree upon their respective Net Actual Interchange or Net Scheduled Interchange quantities by the 15th calendar day of the following month shall, for the purposes of dispute resolution, submit a report to their respective RRO Survey Contact. The report shall describe the nature and the cause of the dispute as well as a process for correcting the discrepancy.				X																Main Transmission System		BA
CIP-001-1	0.	Sabotage Reporting		X	X	X							X					X				Main Transmission System		Adopted by NERC: 2006-11-01
CIP-001-0	01.	Each Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator, and Load Serving Entity shall have procedures for the recognition of and for making their operating personnel aware of sabotage events on its facilities and multi-site sabotage affecting larger portions of the Interconnection.		X	X	X							X					X				Main Transmission System	NPCC RRP	BA, RC, TOP GOP-1, GOP-2, GOP-3 LSE-1, LSE-2
CIP-001-0	02.	Each Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator, and Load Serving Entity shall have procedures for the communication of information concerning sabotage events to appropriate parties in the Interconnection.		X	X	X							X					X				Main Transmission System	NPCC RRP	BA, RC, TOP GOP-1, GOP-2, GOP-3 LSE-1, LSE-2
CIP-001-0	03.	Each Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator, and Load Serving Entity shall provide its operating personnel with sabotage response guidelines, including personnel to contact, for reporting disturbances due to sabotage events.		X	X	X							X					X				Main Transmission System	NPCC RRP	BA, RC, TOP GOP-1, GOP-2, GOP-3 LSE-1, LSE-2
CIP-001-0	04.	Each Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator, and Load Serving Entity shall establish communications contacts, as applicable, with local Federal Bureau of Investigation (FBI) or Royal Canadian Mounted Police (RCMP) officials and develop reporting procedures as appropriate to their circumstances. (* In Québec, this communication is made to the Sûreté du Québec.		X	X	X							X					X				Main Transmission System	NPCC RRP	BA, RC, TOP GOP-1, GOP-2, GOP-3 LSE-1, LSE-2

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-002-1	0.	Cyber Security — Critical Cyber Asset Identification	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02
CIP-002-1	01.	Critical Asset Identification Method — The Responsible Entity shall identify and document a risk-based assessment methodology to use to identify its Critical Assets.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.1	The Responsible Entity shall maintain documentation describing its risk-based assessment methodology that includes procedures and evaluation criteria.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2	The risk-based assessment shall consider the following assets:	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2.1	Control centers and backup control centers performing the functions of the entities listed in the Applicability section of this standard.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2.2	Transmission substations that support the reliable operation of the Bulk Electric System.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2.3	Generation resources that support the reliable operation of the Bulk Electric System.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2.4	Systems and facilities critical to system restoration, including blackstart generators and substations in the electrical path of transmission lines used for initial system restoration.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2.5	Systems and facilities critical to automatic load shedding under a common control system capable of shedding 300 MW or more.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2.6	Special Protection Systems that support the reliable operation of the Bulk Electric System.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	01.2.7	Any additional assets that support the reliable operation of the Bulk Electric System that the Responsible Entity deems appropriate to include in its assessment.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	02.	Critical Asset Identification — The Responsible Entity shall develop a list of its identified Critical Assets determined through an annual application of the risk-based assessment methodology required in R1. The Responsible Entity shall review this list at least annually, and update it as necessary.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	03.	Critical Cyber Asset Identification — Using the list of Critical Assets developed pursuant to Requirement R2, the Responsible Entity shall develop a list of associated Critical Cyber Assets essential to the operation of the Critical Asset. Examples at control centers and backup control centers include systems and facilities at master and remote sites that provide monitoring and control, automatic generation control, real-time power system modeling, and real-time interutility data exchange. The Responsible Entity shall review this list at least annually, and update it as necessary. For the purpose of Standard CIP-002, Critical Cyber Assets are further qualified to be those having at least one of the following characteristics:	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	03.1	The Cyber Asset uses a routable protocol to communicate outside the Electronic Security Perimeter; or,	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	03.2	The Cyber Asset uses a routable protocol within a control center; or,	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-002-1	03.3	The Cyber Asset is dial-up accessible.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-002-1	04.	Annual Approval — A senior manager or delegate(s) shall approve annually the list of Critical Assets and the list of Critical Cyber Assets. Based on Requirements R1, R2, and R3 the Responsible Entity may determine that it has no Critical Assets or Critical Cyber Assets. The Responsible Entity shall keep a signed and dated record of the senior manager or delegate(s)'s approval of the list of Critical Assets and the list of Critical Cyber Assets (even if such lists are null.)	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	0.	Cyber Security — Security Management Controls	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02
CIP-003-1	01.	Cyber Security Policy — The Responsible Entity shall document and implement a cyber security policy that represents management's commitment and ability to secure its Critical Cyber Assets. The Responsible Entity shall, at minimum, ensure the following:	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	01.1	The cyber security policy addresses the requirements in Standards CIP-002 through CIP-009, including provision for emergency situations.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	01.2	The cyber security policy is readily available to all personnel who have access to, or are responsible for, Critical Cyber Assets.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	01.3	Annual review and approval of the cyber security policy by the senior manager assigned pursuant to R2.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	02.	Leadership — The Responsible Entity shall assign a senior manager with overall responsibility for leading and managing the entity's implementation of, and adherence to, Standards CIP-002 through CIP-009.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	02.1	The senior manager shall be identified by name, title, business phone, business address, and date of designation.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	02.2	Changes to the senior manager must be documented within thirty calendar days of the effective date.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	02.3	The senior manager or delegate(s), shall authorize and document any exception from the requirements of the cyber security policy.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	03.	Exceptions — Instances where the Responsible Entity cannot conform to its cyber security policy must be documented as exceptions and authorized by the senior manager or delegate(s).	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	03.1	Exceptions to the Responsible Entity's cyber security policy must be documented within thirty days of being approved by the senior manager or delegate(s).	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	03.2	Documented exceptions to the cyber security policy must include an explanation as to why the exception is necessary and any compensating measures, or a statement accepting risk.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	03.3	Authorized exceptions to the cyber security policy must be reviewed and approved annually by the senior manager or delegate(s) to ensure the exceptions are still required and valid. Such review and approval shall be documented.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	04.	Information Protection — The Responsible Entity shall implement and document a program to identify, classify, and protect information associated with Critical Cyber Assets.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	04.1	The Critical Cyber Asset information to be protected shall include, at a minimum and regardless of media type, operational procedures, lists as required in Standard CIP- 002, network topology or similar diagrams, floor plans of computing centers that contain Critical Cyber Assets, equipment layouts of Critical Cyber Assets, disaster recovery plans, incident response plans, and security configuration information.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	04.2	The Responsible Entity shall classify information to be protected under this program based on the sensitivity of the Critical Cyber Asset information.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
CIP-003-1	04.3	The Responsible Entity shall, at least annually, assess adherence to its Critical Cyber Asset information protection program, document the assessment results, and implement an action plan to remediate deficiencies identified during the assessment.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	05.	Access Control — The Responsible Entity shall document and implement a program for managing access to protected Critical Cyber Asset information.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	05.1	The Responsible Entity shall maintain a list of designated personnel who are responsible for authorizing logical or physical access to protected information.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	05.1.1	Personnel shall be identified by name, title, business phone and the information for which they are responsible for authorizing access.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	05.1.2	The list of personnel responsible for authorizing access to protected information shall be verified at least annually.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	05.2	The Responsible Entity shall review at least annually the access privileges to protected information to confirm that access privileges are correct and that they correspond with the Responsible Entity's needs and appropriate personnel roles and responsibilities.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	05.3	The Responsible Entity shall assess and document at least annually the processes for controlling access privileges to protected information.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-003-1	06.	Change Control and Configuration Management — The Responsible Entity shall establish and document a process of change control and configuration management for adding, modifying, replacing, or removing Critical Cyber Asset hardware or software, and implement supporting configuration management activities to identify, control and document all entity or vendor-related changes to hardware and software components of Critical Cyber Assets pursuant to the change control process.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	0.	Cyber Security — Personnel & Training	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02
CIP-004-1	01.	Awareness — The Responsible Entity shall establish, maintain, and document a security awareness program to ensure personnel having authorized cyber or authorized unescorted physical access receive on-going reinforcement in sound security practices. The program shall include security awareness reinforcement on at least a quarterly basis using mechanisms such as: • Direct communications (e.g., emails, memos, computer based training, etc.); • Indirect communications (e.g., posters, intranet, brochures, etc.); • Management support and reinforcement (e.g., presentations, meetings, etc.).	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	02.	Training — The Responsible Entity shall establish, maintain, and document an annual cyber security training program for personnel having authorized cyber or authorized unescorted physical access to Critical Cyber Assets, and review the program annually and update as necessary.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	02.1	This program will ensure that all personnel having such access to Critical Cyber Assets, including contractors and service vendors, are trained within ninety calendar days of such authorization.	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	02.2	Training shall cover the policies, access controls, and procedures as developed for the Critical Cyber Assets covered by CIP-004, and include, at a minimum, the following required items appropriate to personnel roles and responsibilities:	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	02.2.1	The proper use of Critical Cyber Assets;	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	02.2.2	Physical and electronic access controls to Critical Cyber Assets;	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	02.2.3	The proper handling of Critical Cyber Asset information; and,	X	X	X	X	X			X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-004-1	02.2.4	Action plans and procedures to recover or re-establish Critical Cyber Assets and access thereto following a Cyber Security Incident.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	02.3	The Responsible Entity shall maintain documentation that training is conducted at least annually, including the date the training was completed and attendance records.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	03.	Personnel Risk Assessment —The Responsible Entity shall have a documented personnel risk assessment program, in accordance with federal, state, provincial, and local laws, and subject to existing collective bargaining unit agreements, for personnel having authorized cyber or authorized unescorted physical access. A personnel risk assessment shall be conducted pursuant to that program within thirty days of such personnel being granted such access. Such program shall at a minimum include:	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	03.1	The Responsible Entity shall ensure that each assessment conducted include, at least, identity verification (e.g., Social Security Number verification in the U.S.) and sevenyear criminal check. The Responsible Entity may conduct more detailed reviews, as permitted by law and subject to existing collective bargaining unit agreements, depending upon the criticality of the position.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	03.2	The Responsible Entity shall update each personnel risk assessment at least every seven years after the initial personnel risk assessment or for cause.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	03.3	The Responsible Entity shall document the results of personnel risk assessments of its personnel having authorized cyber or authorized unescorted physical access to Critical Cyber Assets, and that personnel risk assessments of contractor and service vendor personnel with such access are conducted pursuant to Standard CIP-004.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	04.	Access — The Responsible Entity shall maintain list(s) of personnel with authorized cyber or authorized unescorted physical access to Critical Cyber Assets, including their specific electronic and physical access rights to Critical Cyber Assets.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	04.1	The Responsible Entity shall review the list(s) of its personnel who have such access to Critical Cyber Assets quarterly, and update the list(s) within seven calendar days of any change of personnel with such access to Critical Cyber Assets, or any change in the access rights of such personnel. The Responsible Entity shall ensure access list(s) for contractors and service vendors are properly maintained.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-004-1	04.2	The Responsible Entity shall revoke such access to Critical Cyber Assets within 24 hours for personnel terminated for cause and within seven calendar days for personnel who no longer require such access to Critical Cyber Assets.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	0.	Cyber Security — Electronic Security Perimeter(s)	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02
CIP-005-1	01.	Electronic Security Perimeter — The Responsible Entity shall ensure that every Critical Cyber Asset resides within an Electronic Security Perimeter. The Responsible Entity shall identify and document the Electronic Security Perimeter(s) and all access points to the perimeter(s).	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	01.1	Access points to the Electronic Security Perimeter(s) shall include any externally connected communication end point (for example, dial-up modems) terminating at any device within the Electronic Security Perimeter(s).	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	01.2	For a dial-up accessible Critical Cyber Asset that uses a non-routable protocol, the Responsible Entity shall define an Electronic Security Perimeter for that single access point at the dial-up device.	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	01.3	Communication links connecting discrete Electronic Security Perimeters shall not be considered part of the Electronic Security Perimeter. However, end points of these communication links within the Electronic Security Perimeter(s) shall be considered access points to the Electronic Security Perimeter(s).	X	X	X	X	X			X			X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE			
CIP-005-1	01.4	Any non-critical Cyber Asset within a defined Electronic Security Perimeter shall be identified and protected pursuant to the requirements of Standard CIP-005.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	01.5	Cyber Assets used in the access control and monitoring of the Electronic Security Perimeter(s) shall be afforded the protective measures as a specified in Standard CIP-003, Standard CIP-004 Requirement R3, Standard CIP-005 Requirements R2 and R3, Standard CIP-006 Requirements R2 and R3, Standard CIP-007, Requirements R1 and R3 through R9, Standard CIP-008, and Standard CIP-009.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	01.6	The Responsible Entity shall maintain documentation of Electronic Security Perimeter(s), all interconnected Critical and non-critical Cyber Assets within the Electronic Security Perimeter(s), all electronic access points to the Electronic Security Perimeter(s) and the Cyber Assets deployed for the access control and monitoring of these access points.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.	Electronic Access Controls — The Responsible Entity shall implement and document the organizational processes and technical and procedural mechanisms for control of electronic access at all electronic access points to the Electronic Security Perimeter(s).	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.1	These processes and mechanisms shall use an access control model that denies access by default, such that explicit access permissions must be specified.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.2	At all access points to the Electronic Security Perimeter(s), the Responsible Entity shall enable only ports and services required for operations and for monitoring Cyber Assets within the Electronic Security Perimeter, and shall document, individually or by specified grouping, the configuration of those ports and services.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.3	The Responsible Entity shall maintain a procedure for securing dial-up access to the Electronic Security Perimeter(s).	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.4	Where external interactive access into the Electronic Security Perimeter has been enabled, the Responsible Entity shall implement strong procedural or technical controls at the access points to ensure authenticity of the accessing party, where technically feasible.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.5	The required documentation shall, at least, identify and describe:	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.5.1	The processes for access request and authorization.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.5.2	The authentication methods.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.5.3	The review process for authorization rights, in accordance with Standard CIP-004 Requirement R4.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.5.4	The controls used to secure dial-up accessible connections.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	02.6	Appropriate Use Banner — Where technically feasible, electronic access control devices shall display an appropriate use banner on the user screen upon all interactive access attempts. The Responsible Entity shall maintain a document identifying the content of the banner.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	03.	Monitoring Electronic Access — The Responsible Entity shall implement and document an electronic or manual process(es) for monitoring and logging access at access points to the Electronic Security Perimeter(s) twenty-four hours a day, seven days a week.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	03.1	For dial-up accessible Critical Cyber Assets that use non-routable protocols, the Responsible Entity shall implement and document monitoring process(es) at each access point to the dial-up device, where technically feasible.	X	X	X	X	X			X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-005-1	03.2	Where technically feasible, the security monitoring process(es) shall detect and alert for attempts at or actual unauthorized accesses. These alerts shall provide for appropriate notification to designated response personnel. Where alerting is not technically feasible, the Responsible Entity shall review or otherwise assess access logs for attempts at or actual unauthorized accesses at least every ninety calendar days.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	04.	Cyber Vulnerability Assessment — The Responsible Entity shall perform a cyber vulnerability assessment of the electronic access points to the Electronic Security Perimeter(s) at least annually. The vulnerability assessment shall include, at a minimum, the following:	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	04.1	A document identifying the vulnerability assessment process;	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	04.2	A review to verify that only ports and services required for operations at these access points are enabled;	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	04.3	The discovery of all access points to the Electronic Security Perimeter;	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	04.4	A review of controls for default accounts, passwords, and network management community strings; and,	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	04.5	Documentation of the results of the assessment, the action plan to remediate or mitigate vulnerabilities identified in the assessment, and the execution status of that action plan.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	05.	Documentation Review and Maintenance — The Responsible Entity shall review, update, and maintain all documentation to support compliance with the requirements of Standard CIP-005.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	05.1	The Responsible Entity shall ensure that all documentation required by Standard CIP-005 reflect current configurations and processes and shall review the documents and procedures referenced in Standard CIP-005 at least annually.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	05.2	The Responsible Entity shall update the documentation to reflect the modification of the network or controls within ninety calendar days of the change.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-005-1	05.3	The Responsible Entity shall retain electronic access logs for at least ninety calendar days. Logs related to reportable incidents shall be kept in accordance with the requirements of Standard CIP-008.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	0.	Cyber Security — Physical Security of Critical Cyber Assets	X	X	X	X	X			X		X				X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02	
CIP-006-1	01.	Physical Security Plan — The Responsible Entity shall create and maintain a physical security plan, approved by a senior manager or delegate(s) that shall address, at a minimum, the following:	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.1	Processes to ensure and document that all Cyber Assets within an Electronic Security Perimeter also reside within an identified Physical Security Perimeter. Where a completely enclosed ("six-wall") border cannot be established, the Responsible Entity shall deploy and document alternative measures to control physical access to the Critical Cyber Assets.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.2	Processes to identify all access points through each Physical Security Perimeter and measures to control entry at those access points.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.3	Processes, tools, and procedures to monitor physical access to the perimeter(s).	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.4	Procedures for the appropriate use of physical access controls as described in Requirement R3 including visitor pass management, response to loss, and prohibition of inappropriate use of physical access controls.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities			
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC		
CIP-006-1	01.5	Procedures for reviewing access authorization requests and revocation of access authorization, in accordance with CIP-004 Requirement R4.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.6	Procedures for escorted access within the physical security perimeter of personnel not authorized for unescorted access.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.7	Process for updating the physical security plan within ninety calendar days of any physical security system redesign or reconfiguration, including, but not limited to, addition or removal of access points through the physical security perimeter, physical access controls, monitoring controls, or logging controls.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.8	Cyber Assets used in the access control and monitoring of the Physical Security Perimeter(s) shall be afforded the protective measures specified in Standard CIP-003, Standard CIP-004 Requirement R3, Standard CIP-005 Requirements R2 and R3, Standard CIP-006 Requirement R2 and R3, Standard CIP-007, Standard CIP-008 and Standard CIP-009.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	01.9	Process for ensuring that the physical security plan is reviewed at least annually.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	02.	Physical Access Controls — The Responsible Entity shall document and implement the operational and procedural controls to manage physical access at all access points to the Physical Security Perimeter(s) twenty-four hours a day, seven days a week. The Responsible Entity shall implement one or more of the following physical access methods:	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	02.1	Card Key: A means of electronic access where the access rights of the card holder are predefined in a computer database. Access rights may differ from one perimeter to another.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	02.2	Special Locks: These include, but are not limited to, locks with "restricted key" systems, magnetic locks that can be operated remotely, and "man-trap" systems.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	02.3	Security Personnel: Personnel responsible for controlling physical access who may reside on-site or at a monitoring station.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	02.4	Other Authentication Devices: Biometric, keypad, token, or other equivalent devices that control physical access to the Critical Cyber Assets.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	03.	Monitoring Physical Access — The Responsible Entity shall document and implement the technical and procedural controls for monitoring physical access at all access points to the Physical Security Perimeter(s) twenty-four hours a day, seven days a week. Unauthorized access attempts shall be reviewed immediately and handled in accordance with the procedures specified in Requirement CIP-008. One or more of the following monitoring methods shall be used:	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	03.1	Alarm Systems: Systems that alarm to indicate a door, gate or window has been opened without authorization. These alarms must provide for immediate notification to personnel responsible for response.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	03.2	Human Observation of Access Points: Monitoring of physical access points by authorized personnel as specified in Requirement R2.3.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	04.	Logging Physical Access — Logging shall record sufficient information to uniquely identify individuals and the time of access twenty-four hours a day, seven days a week. The Responsible Entity shall implement and document the technical and procedural mechanisms for logging physical entry at all access points to the Physical Security Perimeter(s) using one or more of the following logging methods or their equivalent:	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	04.1	Computerized Logging: Electronic logs produced by the Responsible Entity's selected access control and monitoring method.	X	X	X	X	X			X		X							X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-006-1	04.2	Video Recording: Electronic capture of video images of sufficient quality to determine identity.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	04.3	Manual Logging: A log book or sign-in sheet, or other record of physical access maintained by security or other personnel authorized to control and monitor physical access as specified in Requirement R2.3.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	05.	Access Log Retention — The responsible entity shall retain physical access logs for at least ninety calendar days. Logs related to reportable incidents shall be kept in accordance with the requirements of Standard CIP-008.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	06.	Maintenance and Testing — The Responsible Entity shall implement a maintenance and testing program to ensure that all physical security systems under Requirements R2, R3, and R4 function properly. The program must include, at a minimum, the following:	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	06.1	Testing and maintenance of all physical security mechanisms on a cycle no longer than three years.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	06.2	Retention of testing and maintenance records for the cycle determined by the Responsible Entity in Requirement R6.1.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-006-1	06.3	Retention of outage records regarding access controls, logging, and monitoring for a minimum of one calendar year.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	0.	Cyber Security — Systems Security Management	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02
CIP-007-1	01.	Test Procedures — The Responsible Entity shall ensure that new Cyber Assets and significant changes to existing Cyber Assets within the Electronic Security Perimeter do not adversely affect existing cyber security controls. For purposes of Standard CIP-007, a significant change shall, at a minimum, include implementation of security patches, cumulative service packs, vendor releases, and version upgrades of operating systems, applications, database platforms, or other third-party software or firmware.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	01.1	The Responsible Entity shall create, implement, and maintain cyber security test procedures in a manner that minimizes adverse effects on the production system or its operation.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	01.2	The Responsible Entity shall document that testing is performed in a manner that reflects the production environment.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	01.3	The Responsible Entity shall document test results.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	02.	Ports and Services — The Responsible Entity shall establish and document a process to ensure that only those ports and services required for normal and emergency operations are enabled.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	02.1	The Responsible Entity shall enable only those ports and services required for normal and emergency operations.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	02.2	The Responsible Entity shall disable other ports and services, including those used for testing purposes, prior to production use of all Cyber Assets inside the Electronic Security Perimeter(s).	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	02.3	In the case where unused ports and services cannot be disabled due to technical limitations, the Responsible Entity shall document compensating measure(s) applied to mitigate risk exposure or an acceptance of risk.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-007-1	03.	Security Patch Management — The Responsible Entity, either separately or as a component of the documented configuration management process specified in CIP-003 Requirement R6, shall establish and document a security patch management program for tracking, evaluating, testing, and installing applicable cyber security software patches for all Cyber Assets within the Electronic Security Perimeter(s).	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	03.1	The Responsible Entity shall document the assessment of security patches and security upgrades for applicability within thirty calendar days of availability of the patches or upgrades.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	03.2	The Responsible Entity shall document the implementation of security patches. In any case where the patch is not installed, the Responsible Entity shall document compensating measure(s) applied to mitigate risk exposure or an acceptance of risk.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	04.	Malicious Software Prevention — The Responsible Entity shall use anti-virus software and other malicious software ("malware") prevention tools, where technically feasible, to detect, prevent, deter, and mitigate the introduction, exposure, and propagation of malware on all Cyber Assets within the Electronic Security Perimeter(s).	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	04.1	The Responsible Entity shall document and implement anti-virus and malware prevention tools. In the case where anti-virus software and malware prevention tools are not installed, the Responsible Entity shall document compensating measure(s) applied to mitigate risk exposure or an acceptance of risk.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	04.2	The Responsible Entity shall document and implement a process for the update of anti-virus and malware prevention "signatures." The process must address testing and installing the signatures.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.	Account Management — The Responsible Entity shall establish, implement, and document technical and procedural controls that enforce access authentication of, and accountability for, all user activity, and that minimize the risk of unauthorized system access.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.1	The Responsible Entity shall ensure that individual and shared system accounts and authorized access permissions are consistent with the concept of "need to know" with respect to work functions performed.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.1.1	The Responsible Entity shall ensure that user accounts are implemented as approved by designated personnel. Refer to Standard CIP-003 Requirement R5.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.1.2	The Responsible Entity shall establish methods, processes, and procedures that generate logs of sufficient detail to create historical audit trails of individual user account access activity for a minimum of ninety days.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.1.3	The Responsible Entity shall review, at least annually, user accounts to verify access privileges are in accordance with Standard CIP-003 Requirement R5 and Standard CIP-004 Requirement R4.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.2	The Responsible Entity shall implement a policy to minimize and manage the scope and acceptable use of administrator, shared, and other generic account privileges including factory default accounts.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.2.1	The policy shall include the removal, disabling, or renaming of such accounts where possible. For such accounts that must remain enabled, passwords shall be changed prior to putting any system into service.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.2.2	The Responsible Entity shall identify those individuals with access to shared accounts.	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.2.3	Where such accounts must be shared, the Responsible Entity shall have a policy for managing the use of such accounts that limits access to only those with authorization, an audit trail of the account use (automated or manual), and steps for securing the account in the event of personnel changes (for example, change in assignment or termination).	X	X	X	X	X			X		X	X				X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-007-1	05.3	At a minimum, the Responsible Entity shall require and use passwords, subject to the following, as technically feasible:	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.3.1	Each password shall be a minimum of six characters.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.3.2	Each password shall consist of a combination of alpha, numeric, and "special" characters.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	05.3.3	Each password shall be changed at least annually, or more frequently based on risk.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	06.	Security Status Monitoring — The Responsible Entity shall ensure that all Cyber Assets within the Electronic Security Perimeter, as technically feasible, implement automated tools or organizational process controls to monitor system events that are related to cyber security.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	06.1	The Responsible Entity shall implement and document the organizational processes and technical and procedural mechanisms for monitoring for security events on all Cyber Assets within the Electronic Security Perimeter.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	06.2	The security monitoring controls shall issue automated or manual alerts for detected Cyber Security Incidents.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	06.3	The Responsible Entity shall maintain logs of system events related to cyber security, where technically feasible, to support incident response as required in Standard CIP- 008.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	06.4	The Responsible Entity shall retain all logs specified in Requirement R6 for ninety calendar days.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	06.5	The Responsible Entity shall review logs of system events related to cyber security and maintain records documenting review of logs.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	07.	Disposal or Redeployment — The Responsible Entity shall establish formal methods, processes, and procedures for disposal or redeployment of Cyber Assets within the Electronic Security Perimeter(s) as identified and documented in Standard CIP-005.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	07.1	Prior to the disposal of such assets, the Responsible Entity shall destroy or erase the data storage media to prevent unauthorized retrieval of sensitive cyber security or reliability data.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	07.2	Prior to redeployment of such assets, the Responsible Entity shall, at a minimum, erase the data storage media to prevent unauthorized retrieval of sensitive cyber security or reliability data.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	07.3	The Responsible Entity shall maintain records that such assets were disposed of or redeployed in accordance with documented procedures.	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	08.	Cyber Vulnerability Assessment — The Responsible Entity shall perform a cyber vulnerability assessment of all Cyber Assets within the Electronic Security Perimeter at least annually. The vulnerability assessment shall include, at a minimum, the following:	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	08.1	A document identifying the vulnerability assessment process;	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	08.2	A review to verify that only ports and services required for operation of the Cyber Assets within the Electronic Security Perimeter are enabled;	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	08.3	A review of controls for default accounts; and,	X	X	X	X	X			X		X					X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-007-1	08.4	Documentation of the results of the assessment, the action plan to remediate or mitigate vulnerabilities identified in the assessment, and the execution status of that action plan.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-007-1	09.	Documentation Review and Maintenance — The Responsible Entity shall review and update the documentation specified in Standard CIP-007 at least annually. Changes resulting from modifications to the systems or controls shall be documented within ninety calendar days of the change.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	0.	Cyber Security — Incident Reporting and Response Planning	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02
CIP-008-1	01.	Cyber Security Incident Response Plan — The Responsible Entity shall develop and maintain a Cyber Security Incident response plan. The Cyber Security Incident Response plan shall address, at a minimum, the following:	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	01.1	Procedures to characterize and classify events as reportable Cyber Security Incidents.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	01.2	Response actions, including roles and responsibilities of incident response teams, incident handling procedures, and communication plans.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	01.3	Process for reporting Cyber Security Incidents to the Electricity Sector Information Sharing and Analysis Center (ES ISAC). The Responsible Entity must ensure that all reportable Cyber Security Incidents are reported to the ES ISAC either directly or through an intermediary.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	01.4	Process for updating the Cyber Security Incident response plan within ninety calendar days of any changes.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	01.5	Process for ensuring that the Cyber Security Incident response plan is reviewed at least annually.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	01.6	Process for ensuring the Cyber Security Incident response plan is tested at least annually. A test of the incident response plan can range from a paper drill, to a full operational exercise, to the response to an actual incident.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-008-1	02.	Cyber Security Incident Documentation — The Responsible Entity shall keep relevant documentation related to Cyber Security Incidents reportable per Requirement R1.1 for three calendar years.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-009-1	0.	Cyber Security — Recovery Plans for Critical Cyber Assets	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02
CIP-009-1	01.	Recovery Plans — The Responsible Entity shall create and annually review recovery plan(s) for Critical Cyber Assets. The recovery plan(s) shall address at a minimum the following:	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-009-1	01.1	Specify the required actions in response to events or conditions of varying duration and severity that would activate the recovery plan(s).	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-009-1	01.2	Define the roles and responsibilities of responders.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-009-1	02.	Exercises — The recovery plan(s) shall be exercised at least annually. An exercise of the recovery plan(s) can range from a paper drill, to a full operational exercise, to recovery from an actual incident.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-009-1	03.	Change Control — Recovery plan(s) shall be updated to reflect any changes or lessons learned as a result of an exercise or the recovery from an actual incident. Updates shall be communicated to personnel responsible for the activation and implementation of the recovery plan(s) within ninety calendar days of the change.	X	X	X	X	X		X		X		X	X			X			X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
CIP-009-1	04.	Backup and Restore — The recovery plan(s) shall include processes and procedures for the backup and storage of information required to successfully restore Critical Cyber Assets. For example, backups may include spare electronic components or equipment, written documentation of configuration settings, tape backup, etc.	X	X	X	X	X			X			X	X						X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
CIP-009-1	05.	Testing Backup Media — Information essential to recovery that is stored on backup media shall be tested at least annually to ensure that the information is available. Testing can be completed off site.	X	X	X	X	X			X			X	X						X	Facilities and Control Centers identified in the Registry		BA, IA, RC, TOP GO-1, GOP-1 TO-1, TSP-1
COM-001-1	0.	Telecommunications		X	X	X													X	Main Transmission System		Adopted by NERC: 2006-11-01	
COM-001-1	01.	Each Reliability Coordinator, TOP and BA shall provide adequate and reliable telecommunications facilities for the exchange of Interconnection and operating information:		X	X	X															Main Transmission System	NPCC RRP	BA, IA, RC, TOP
COM-001-1	01.1	Internally		X	X	X															Main Transmission System	NPCC A-03	BA, IA, RC, TOP
COM-001-1	01.2	Between the Reliability Coordinator and its Transmission Operators and Balancing Authorities.		X	X	X															Main Transmission System	NPCC RRP	BA, IA, RC, TOP
COM-001-1	01.3	With other Reliability Coordinators, Transmission Operators, and Balancing Authorities as necessary to maintain reliability.		X	X	X															Main Transmission System	NPCC RRP	BA, IA, RC, TOP
COM-001-1	01.4	Where applicable, these facilities shall be redundant and diversely routed.		X	X	X															Main Transmission System	NPCC RRP	BA, IA, RC, TOP
COM-001-1	02.	Each RC, TOP and BA shall manage, alarm, test and/or actively monitor vital telecommunications facilities. Special attention shall be given to emergency telecoms facilities and equipment not used for routine communications.		X	X	X															Main Transmission System	NPCC RRP	BA, IA, RC, TOP
COM-001-1	03.	Each RC, TOP and BA shall provide a means to coordinate telecommunications among their respective areas. This coordination shall include the ability to investigate and recommend solutions to telecommunications problems within the area and with other areas.		X	X	X															Main Transmission System		BA, IA, RC, TOP
COM-001-1	04.	Unless agreed to otherwise, each RC, TOP and BA shall use English as the language for all communications between and among operating personnel responsible for the real-time generation control and operation of the interconnected BES. TOP and BA may use an alternate language for internal operations. (*) It is agreed that communication with entities located in the Province of Québec will be in French.		X	X	X															Main Transmission System		BA, IA, RC, TOP
COM-001-1	05.	Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall have written operating instructions and procedures to enable continued operation of the system during the loss of telecommunications facilities.		X	X	X															Main Transmission System	NPCC A-03	BA, IA, RC, TOP
COM-001-1	06.	Each NERCNet User Organization shall adhere to the requirements in Attachment 1-COM-001-0, "NERCNet Security Policy."																	X		Main Transmission System		BA, IA, RC, TOP Note: NERCNet Users
COM-002-2	0.	Communication and Coordination		X	X	X							X								Main Transmission System		Adopted by NERC: 2006-11-01
COM-002-2	01.	Each Transmission Operator, Balancing Authority, and Generator Operator shall have communications (voice and data links) with appropriate Reliability Coordinators, Balancing Authorities, and Transmission Operators. Such communications shall be staffed and available for addressing a real-time emergency condition.		X	X	X							X								Main Transmission System	NPCC C-20	BA, RC, TOP GOP-1, GOP-2, GOP-3 LSE-1, LSE-2
COM-002-2	01.1	Each Balancing Authority and Transmission Operator shall notify its Reliability Coordinator, and all other potentially affected Balancing Authorities and Transmission Operators through predetermined communication paths of any condition that could threaten the reliability of its area or when firm load shedding is anticipated.		X	X	X															Main Transmission System	NPCC C-36	BA, RC, TOP
COM-002-2	02.	Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall issue directives in a clear, concise, and definitive manner; shall ensure the recipient of the directive repeats the information back correctly; and shall acknowledge the response as correct or repeat the original statement to resolve any misunderstandings.		X	X	X															Main Transmission System	NPCC RRP	BA, RC, TOP
EOP-001-0	0.	Emergency Operations Planning			X	X															Main Transmission System		Adopted by NERC: 2006-05-02

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
EOP-001-0	01.	Balancing Authorities shall have operating agreements with adjacent Balancing Authorities that shall, at a minimum, contain provisions for emergency assistance, including provisions to obtain emergency assistance from remote Balancing Authorities.				X																Main Transmission System	NPCC A-03	BA
EOP-001-0	02.	The TOP shall have an emergency load reduction plan for all identified IROLs. The plan shall include the details on how the TOP will implement load reduction in sufficient amount and time to mitigate the IROL violation before system separation or collapse would occur. The load reduction plan must be capable of being implemented within 30 minutes.			X																	Main Transmission System	NPCC A-03	TOP
EOP-001-0	03.	Each Transmission Operator and Balancing Authority shall (see following sections):			X	X																Main Transmission System	NPCC RRP	BA, TOP
EOP-001-0	03.1	Develop, maintain, and implement a set of plans to mitigate operating emergencies for insufficient generating capacity.			X	X																Main Transmission System	NPCC C-20	BA, TOP
EOP-001-0	03.2	Develop, maintain, and implement a set of plans to mitigate operating emergencies on the transmission system.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-001-0	03.3	Develop, maintain, and implement a set of plans for load shedding.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-001-0	03.4	Develop, maintain, and implement a set of plans for system restoration.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-001-0	04.	Each Transmission Operator and Balancing Authority shall have emergency plans that will enable it to mitigate operating emergencies. At a minimum, Transmission Operator and Balancing Authority emergency plans shall include (see following sections):			X	X																Main Transmission System	NPCC RRP	BA, TOP
EOP-001-0	04.1	Communications protocols to be used during emergencies.			X	X																Main Transmission System	NPCC C-01	BA, TOP
EOP-001-0	04.2	A list of controlling actions to resolve the emergency. Load reduction, in sufficient quantity to resolve the emergency within NERC-established timelines, shall be one of the controlling actions.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-001-0	04.3	The tasks to be coordinated with and among adjacent Transmission Operators and Balancing Authorities.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-001-0	04.4	Staffing levels for the emergency.			X	X																Main Transmission System	NPCC RRP	BA, TOP
EOP-001-0	05.	Each Transmission Operator and Balancing Authority shall include the applicable elements in Attachment 1-EOP-001-0 when developing an emergency plan.			X	X																Main Transmission System		BA, TOP
EOP-001-0	06.	The Transmission Operator and Balancing Authority shall annually review and update each emergency plan. The Transmission Operator and Balancing Authority shall provide a copy of its updated emergency plans to its Reliability Coordinator and to neighboring Transmission Operators and Balancing Authorities.			X	X																Main Transmission System		BA, TOP
EOP-001-0	07.	The Transmission Operator and Balancing Authority shall coordinate its emergency plans with other Transmission Operators and Balancing Authorities as appropriate. This coordination includes the following steps, as applicable:			X	X																Main Transmission System	NPCC RRP	BA, TOP
EOP-001-0	07.1	The Transmission Operator and Balancing Authority shall establish and maintain reliable communications between interconnected systems.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-001-0	07.2	The Transmission Operator and Balancing Authority shall arrange new interchange agreements to provide for emergency capacity or energy transfers if existing agreements cannot be used.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-001-0	07.3	The Transmission Operator and Balancing Authority shall coordinate transmission and generator maintenance schedules to maximize capacity or conserve the fuel in short supply. (This includes water for hydro generators.)			X	X																Main Transmission System	NPCC C-01	BA, TOP
EOP-001-0	07.4	The Transmission Operator and Balancing Authority shall arrange deliveries of electrical energy or fuel from remote systems through normal operating channels.			X	X																Main Transmission System	NPCC A-03	BA, TOP
EOP-002-2	0.	Capacity and Energy Emergencies		X		X																Main Transmission System + interruptible and sheddable load		Adopted by NERC: 2006-11-01
EOP-002-2	01.	Each Balancing Authority and Reliability Coordinator shall have the responsibility and clear decision-making authority to take whatever actions are needed to ensure the reliability of its respective area and shall exercise specific authority to alleviate capacity and energy emergencies.		X		X																Main Transmission System + interruptible and sheddable load	NPCC RRP	BA, RC

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
EOP-002-2	02.	Each Balancing Authority shall implement its capacity and energy emergency plan, when required and as appropriate, to reduce risks to the interconnected system.				X																Main Transmission System + interruptible and sheddable load	NPCC RRP	BA
EOP-002-2	03.	A Balancing Authority that is experiencing an operating capacity or energy emergency shall communicate its current and future system conditions to its Reliability Coordinator and neighboring Balancing Authorities.				X																Main Transmission System + interruptible and sheddable load	NPCC C-20	BA
EOP-002-2	04.	A Balancing Authority anticipating an operating capacity or energy emergency shall perform all actions necessary including bringing on all available generation, postponing equipment maintenance, scheduling interchange purchases in advance, and being prepared to reduce firm load.				X																Main Transmission System + interruptible and sheddable load	NPCC RRP NPCC C-20	BA
EOP-002-2	05.	A deficient Balancing Authority shall only use the assistance provided by the Interconnection's frequency bias for the time needed to implement corrective actions. The Balancing Authority shall not unilaterally adjust generation in an attempt to return Interconnection frequency to normal beyond that supplied through frequency bias action and Interchange Schedule changes. Such unilateral adjustment may overload transmission facilities.				X																Main Transmission System + interruptible and sheddable load	NPCC RRP	BA
EOP-002-2	06.	If the Balancing Authority cannot comply with the Control Performance and Disturbance Control Standards, then it shall immediately implement remedies to do so. These remedies include, but are not limited to:				X																Main Transmission System + interruptible and sheddable load	NPCC RRP	BA
EOP-002-2	06.1	Loading all available generating capacity.				X																Main Transmission System + interruptible and sheddable load	NPCC C-20	BA
EOP-002-2	06.2	Deploying all available operating reserve.				X																Main Transmission System + interruptible and sheddable load	NPCC C-20	BA
EOP-002-2	06.3	Interrupting interruptible load and exports.				X																Main Transmission System + interruptible and sheddable load	NPCC C-20	BA
EOP-002-2	06.4	Requesting emergency assistance from other Balancing Authorities.				X																Main Transmission System + interruptible and sheddable load	NPCC RRP	BA
EOP-002-2	06.5	Declaring an Energy Emergency through its Reliability Coordinator; and				X																Main Transmission System + interruptible and sheddable load	NPCC RRP	BA
EOP-002-2	06.6	Reducing load, through procedures such as public appeals, voltage reductions, curtailing interruptible loads and firm loads.				X																Main Transmission System + interruptible and sheddable load	NPCC RRP	BA
EOP-002-2	07.	Once the Balancing Authority has exhausted the steps listed in Requirement 7, or if these steps cannot be completed in sufficient time to resolve the emergency condition, the Balancing Authority shall:				X																Main Transmission System + interruptible and sheddable load	NPCC C-20	BA
EOP-002-2	07.1	Manually shed firm load without delay to return its ACE to zero; and				X																Main Transmission System + interruptible and sheddable load	NPCC RRP NPCC C-20	BA
EOP-002-2	07.2	Request the Reliability Coordinator to declare an Energy Emergency Alert in accordance with Attachment 1-EOP-002-0 "Energy Emergency Alert Levels."				X																Main Transmission System + interruptible and sheddable load	NPCC C-20	BA
EOP-002-2	08.	A Reliability Coordinator that has any Balancing Authority within its Reliability Coordinator area experiencing a potential or actual Energy Emergency shall initiate an Energy Emergency Alert as detailed in Attachment 1-EOP-002-0 "Energy Emergency Alert Levels." The Reliability Coordinator shall act to mitigate the emergency condition, including a request for emergency assistance if required.		X																		Main Transmission System + interruptible and sheddable load	NPCC RRP	RC
EOP-002-2	09.	When a Transmission Service Provider expects to elevate the transmission service priority of an Interchange Transaction from Priority 6 (Network Integration Transmission Service from Non-designated Resources) to Priority 7 (Network Integration Transmission Service from designated Network Resources) as permitted in its transmission tariff (See Attachment 1-IRO-006-0 "Transmission Loading Relief Procedure" for explanation of Transmission Service Priorities):																				Main Transmission System + interruptible and sheddable load		TSP-1, TSP-2

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP				PSE	NNU / NERC
EOP-002-2	09.1	The deficient Load-Serving Entity shall request its Reliability Coordinator to initiate an Energy Emergency Alert in accordance with Attachment 1-EOP-002-0.		X																	Main Transmission System + interruptible and sheddable load		RC LSE-1
EOP-002-2	09.2	The Reliability Coordinator shall submit the report to NERC for posting on the NERC Website, noting the expected total MW that may have its transmission service priority changed.		X																	Main Transmission System + interruptible and sheddable load		RC
EOP-002-2	09.3	The Reliability Coordinator shall use EEA 1 to forecast the change of the priority of transmission service of an Interchange Transaction on the system from Priority 6 to Priority 7.		X																	Main Transmission System + interruptible and sheddable load		RC
EOP-002-2	09.4	The Reliability Coordinator shall use EEA 2 to announce the change of the priority of transmission service of an Interchange Transaction on the system from Priority 6 to Priority 7.		X																	Main Transmission System + interruptible and sheddable load		RC
EOP-002-2	att. 1	This Attachment to EOP-002-0 provides the procedures by which a LSE can obtain capacity and energy when it has exhausted all other options and can no longer provide its customers' expected energy requirements. NERC defines this situation as an "Energy Emergency". NERC assumes that a capacity deficiency will manifest itself as an energy emergency. The EEA Procedure is initiated by the LSE's Reliability Coordinator, who declares various EEA levels as defined in Section B to provide assistance to the LSE.		X		X															Main Transmission System + interruptible and sheddable load	NPCC RRP	BA, RC LSE-1
EOP-003-1	0.	Load Shedding Plans			X	X															Main Transmission System + interruptible and sheddable load		Adopted by NERC: 2006-11-01
EOP-003-1	01.	After taking all other remedial steps, a Transmission Operator or Balancing Authority operating with insufficient generation or transmission capacity shall shed customer load rather than risk an uncontrolled failure of components or cascading outages of the Interconnection.			X	X															Main Transmission System + interruptible and sheddable load	NPCC RRP	BA, TOP
EOP-003-1	02.	Each Transmission Operator and Balancing Authority shall establish plans for automatic load shedding for underfrequency or undervoltage conditions.			X	X															Main Transmission System + interruptible and sheddable load	NPCC A-03	BA, TOP
EOP-003-1	03.	Each Transmission Operator and Balancing Authority shall coordinate load shedding plans among other interconnected Transmission Operators and Balancing Authorities.			X	X															Main Transmission System + interruptible and sheddable load	NPCC A-03	BA, TOP
EOP-003-1	04.	A Transmission Operator or Balancing Authority shall consider one or more of these factors in designing an automatic load shedding scheme: frequency, rate of frequency decay, voltage level, rate of voltage decay, or power flow levels.			X	X															Main Transmission System + interruptible and sheddable load	NPCC B-07	BA, TOP
EOP-003-1	05.	A Transmission Operator or Balancing Authority shall implement load shedding in steps established to minimize the risk of further uncontrolled separation, loss of generation, or system shutdown.			X	X															Main Transmission System + interruptible and sheddable load	NPCC A-03	BA, TOP
EOP-003-1	06.	After a Transmission Operator or Balancing Authority Area separates from the Interconnection, if there is insufficient generating capacity to restore system frequency following automatic underfrequency load shedding, the Transmission Operator or Balancing Authority shall shed additional load.			X	X															Main Transmission System + interruptible and sheddable load	NPCC A-03	BA, TOP
EOP-003-1	07.	The Transmission Operator and Balancing Authority shall coordinate automatic load shedding throughout their areas with underfrequency isolation of generating units, tripping of shunt capacitors, and other automatic actions that will occur under abnormal frequency, voltage, or power flow conditions.			X	X															Main Transmission System + interruptible and sheddable load	NPCC A-03	BA, TOP
EOP-003-1	08.	Each Transmission Operator or Balancing Authority shall have plans for operator-controlled manual load shedding to respond to real-time emergencies. The Transmission Operator or Balancing Authority shall be capable of implementing the load shedding in a timeframe adequate for responding to the emergency.			X	X															Main Transmission System + interruptible and sheddable load	NPCC A-03	BA, TOP
EOP-004-1	0.	Disturbance Reporting	X	X	X	X							X								Main Transmission System		Adopted by NERC: 2006-11-01
EOP-004-1	01.	Each Regional Reliability Organization shall establish and maintain a Regional reporting procedure to facilitate preparation of preliminary and final disturbance reports.	X																		Not applicable in Québec	NPCC B-13	Not applicable in Québec (NPCC only)

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP				PSE	NNU / NERC
EOP-004-1	02.	A Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator or Load Serving Entity shall promptly analyze Bulk Electric System disturbances on its system or facilities.		X	X	X								X							Main Transmission System or load affected by the Main Transmission System	NPCC B-13	BA, RC, TOP LSE-1 GOP-1, GOP-2
EOP-004-1	03.	A Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator or Load Serving Entity experiencing a reportable incident shall provide a preliminary written report to its Regional Reliability Organization and NERC.		X	X	X								X							Main Transmission System or load affected by the Main Transmission System	NPCC B-13	BA, RC, TOP LSE-1 GOP-1, GOP-2
EOP-004-1	03.1	The affected Reliability Coordinator, BA, TOP, GOP or LSE shall submit within 24 hours of the disturbance or unusual occurrence either a copy of the report submitted to DOE, or, if no DOE report is required, a copy of the NERC IROL and Preliminary Disturbance Report form. Events that are not identified until some time after they occur shall be reported within 24 hours of being recognized.		X	X	X								X							Main Transmission System or load affected by the Main Transmission System	NPCC B-13	BA, RC, TOP LSE-1 GOP-1, GOP-2 <i>Note : DOE report not required in Québec</i>
EOP-004-1	03.2	Applicable reporting forms are provided in Attachments 1-EOP-004-0 and 2-EOP-004-0.		X	X	X								X							Main Transmission System ou charges affectées par le Main Transmission System	NPCC B-13	BA, RC, TOP LSE-1 GOP-1, GOP-2
EOP-004-1	03.3	Under certain adverse conditions, e.g., severe weather, it may not be possible to assess the damage caused by a disturbance and issue a written IROL and Preliminary Disturbance Report within 24 hours. In such cases, the affected Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator, or Load Serving Entity shall promptly notify its Regional Reliability Organization(s) and NERC, and verbally provide as much information as is available at that time. The affected RC, Balancing Authority, Transmission Operator, Generator Operator, or Load Serving Entity shall then provide timely, periodic verbal updates until adequate information is available to issue a written Preliminary Disturbance Report.		X	X	X								X							Main Transmission System or load affected by the Main Transmission System		BA, RC, TOP LSE-1 GOP-1, GOP-2
EOP-004-1	03.4	If, in the judgment of the Regional Reliability Organization, after consultation with the Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator, or Load Serving Entity in which a disturbance occurred, a final report is required, the affected Reliability Coordinator, Balancing Authority, Transmission Operator, Generator Operator, or Load Serving Entity shall prepare this report within 60 days. As a minimum, the final report shall have a discussion of the events and its cause, the conclusions reached, and recommendations to prevent recurrence of this type of event. The report shall be subject to Regional Reliability Organization approval.	X	X	X	X								X							Main Transmission System or load affected by the Main Transmission System	NPCC B-13	BA, RC, TOP LSE-1 GOP-1, GOP-2
EOP-004-1	04.	When a BES disturbance occurs, the RRO shall make its representatives on the NERC Operating Committee and Disturbance Analysis Working Group available to the affected RC, BA, TOP, Generator Operator, or LSE immediately affected by the disturbance for the purpose of providing any needed assistance in the investigation and to assist in the preparation of a final report.	X																		Not applicable in Québec	NPCC B-13	<i>Not applicable in Québec (only applicable to NPCC in the Northeast).</i>
EOP-004-1	05.	The RRO shall track and review the status of all final report recommendations at least twice each year to ensure they are being acted upon in a timely manner. If any recommendation has not been acted on within two years, or if RRO tracking and review indicates at any time that any recommendation is not being acted on with sufficient diligence, the RRO shall notify the NERC PC and OC of the status of the recommendation(s) and the steps the RRO has taken to accelerate implementation.	X																		Not applicable in Québec	NPCC B-13 NPCC C-30	<i>Not applicable in Québec (only applicable to NPCC in the Northeast).</i>
EOP-004-1	att. 1	Attachment 1-EOP-004-0 NERC Disturbance Report Form		X	X	X								X							Main Transmission System or load affected by the Main Transmission System	NPCC B-13	BA, RC, TOP LSE-1 GOP-1, GOP-2
EOP-005-1	0.	System Restoration Plans			X	X															Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-05-02

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
EOP-005-1	01.	Each Transmission Operator shall have a restoration plan to reestablish its electric system in a stable and orderly manner in the event of a partial or total shutdown of its system, including necessary operating instructions and procedures to cover emergency conditions, and the loss of vital telecommunications channels. Each Transmission Operator shall include the applicable elements listed in Attachment 1-EOP-005 in developing a restoration plan.			X																	Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-005-1	02.	Each Transmission Operator shall review and update its restoration plan at least annually and whenever it makes changes in the power system network, and shall correct deficiencies found during the simulated restoration exercises.			X																	Facilities and Control Centers identified in the Registry	NPCC A-03	TOP
EOP-005-1	03.	Each Transmission Operator shall develop restoration plans with a priority of restoring the integrity of the Interconnection.			X																	Facilities and Control Centers identified in the Registry	NPCC A-03	TOP
EOP-005-1	04.	Each Transmission Operator shall coordinate its restoration plans with the Generator Owners and Balancing Authorities within its area, its Reliability Coordinator, and neighboring Transmission Operators and Balancing Authorities.			X																	Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-005-1	05.	Each Transmission Operator and Balancing Authority shall periodically test its telecommunication facilities needed to implement the restoration plan.			X																	Facilities and Control Centers identified in the Registry	NPCC A-03	TOP
EOP-005-1	06.	Each Transmission Operator and Balancing Authority shall train its operating personnel in the implementation of the restoration plan. Such training shall include simulated exercises, if practicable.			X	X																Facilities and Control Centers identified in the Registry	NPCC A-03	BA, TOP
EOP-005-1	07.	Each Transmission Operator and Balancing Authority shall verify the restoration procedure by actual testing or by simulation.			X	X																Facilities and Control Centers identified in the Registry	NPCC A-03	BA, TOP
EOP-005-1	08.	Each Transmission Operator shall verify that the number, size, availability, and location of system blackstart generating units are sufficient to meet Regional Reliability Organization restoration plan requirements for the Transmission Operator's area.			X																	Facilities and Control Centers identified in the Registry	NPCC A-03	TOP
EOP-005-1	09.	The Transmission Operator shall document the Cranking Paths, including initial switching requirements, between each blackstart generating unit and the unit(s) to be started and shall provide this documentation for review by the Regional Reliability Organization upon request. Such documentation may include Cranking Path diagrams.			X																	Facilities and Control Centers identified in the Registry		TOP
EOP-005-1	10.	The Transmission Operator shall demonstrate, through simulation or testing, that the blackstart generating units in its restoration plan can perform their intended functions as required in the regional restoration plan.			X																	Facilities and Control Centers identified in the Registry	NPCC A-03	TOP
EOP-005-1	10.1	The Transmission Operator shall perform this simulation or testing at least once every five years.			X																	Facilities and Control Centers identified in the Registry	NPCC A-03	TOP
EOP-005-1	11.	Following a disturbance in which one or more areas of the Bulk Electric System become isolated or blacked out, the affected Transmission Operators and Balancing Authorities shall begin immediately to return the Bulk Electric System to normal.			X	X																Facilities and Control Centers identified in the Registry	NPCC RRP	BA, TOP
EOP-005-1	11.1	The affected Transmission Operators and Balancing Authorities shall work in conjunction with their Reliability Coordinator(s) to determine the extent and condition of the isolated area(s).			X	X																Facilities and Control Centers identified in the Registry	NPCC RRP	BA, TOP
EOP-005-1	11.2	The affected Transmission Operators and Balancing Authorities shall take the necessary actions to restore Bulk Electric System frequency to normal, including adjusting generation, placing additional generators on line, or load shedding.			X	X																Facilities and Control Centers identified in the Registry	NPCC RRP	BA, TOP
EOP-005-1	11.3	The affected Balancing Authorities, working with their Reliability Coordinator(s), shall immediately review the Interchange Schedules between those Balancing Authority Areas or fragments of those Balancing Authority Areas within the separated area and make adjustments as needed to facilitate the restoration. The affected Balancing Authorities shall make all attempts to maintain the adjusted Interchange Schedules, whether generation control is manual or automatic.				X																Facilities and Control Centers identified in the Registry	NPCC RRP	BA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
EOP-005-1	11.4	The affected Transmission Operators shall give high priority to restoration of offsite power to nuclear stations.			X																Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-005-1	11.5	The affected Transmission Operators may resynchronize the isolated area(s) with the surrounding area(s) when the following conditions are met:			X																Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-005-1	11.5.1	Voltage, frequency, and phase angle permit.			X																Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-005-1	11.5.2	The size of the area being reconnected and the capacity of the transmission lines effecting the reconnection and the number of synchronizing points across the system are considered.			X																Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-005-1	11.5.3	Reliability Coordinator(s) and adjacent areas are notified and Reliability Coordinator approval is given.			X																Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-005-1	11.5.4	Load is shed in neighboring areas, if required, to permit successful interconnected system restoration.			X																Facilities and Control Centers identified in the Registry	NPCC RRP	TOP
EOP-006-1	0.	Reliability Coordination – System Restoration		X																	Facilities and Control Centers identified in the Registry		Adopted by NERC: 2006-11-01
EOP-006-1	01.	Each Reliability Coordinator shall be aware of the restoration plan of each Transmission Operator in its Reliability Coordinator Area in accordance with NERC and regional requirements.		X																	Facilities and Control Centers identified in the Registry	NPCC RRP	RC
EOP-006-1	02.	The Reliability Coordinator shall monitor restoration progress and coordinate any needed assistance.		X																	Facilities and Control Centers identified in the Registry	NPCC RRP	RC
EOP-006-1	03.	The Reliability Coordinator shall have a Reliability Coordinator Area restoration plan that provides coordination between individual Transmission Operator restoration plans and that ensures reliability is maintained during system restoration events.		X																	Facilities and Control Centers identified in the Registry	NPCC RRP	RC
EOP-006-1	04.	The Reliability Coordinator shall serve as the primary contact for disseminating information regarding restoration to neighboring Reliability Coordinators and Transmission Operators or Balancing Authorities not immediately involved in restoration.		X																	Facilities and Control Centers identified in the Registry	NPCC RRP	RC
EOP-006-1	05.	Reliability Coordinators shall approve, communicate, and coordinate the re-synchronizing of major system islands or synchronizing points so as not to cause a Burden on adjacent Transmission Operator, Balancing Authority, or Reliability Coordinator Areas.		X																	Facilities and Control Centers identified in the Registry	NPCC RRP	RC
EOP-006-1	06.	The Reliability Coordinator shall take actions to restore normal operations once an operating emergency has been mitigated in accordance with its restoration plan.		X																	Facilities and Control Centers identified in the Registry	NPCC RRP	RC
EOP-008-0	0.	Plans for Loss of Control Center Functionality		X	X	X															CCR / RCCR		Adopted by NERC: 2006-05-02
EOP-008-0	01.	Each Reliability Coordinator, Transmission Operator and Balancing Authority shall have a plan to continue reliability operations in the event its control center becomes inoperable. The contingency plan must meet the following requirements (see R1.1, etc. below):		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-008-0	01.1	The contingency plan shall not rely on data or voice communication from the primary control facility to be viable.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-008-0	01.2	The plan shall include procedures and responsibilities for providing basic tie line control and procedures and for maintaining the status of all inter-area schedules, such that there is an hourly accounting of all schedules.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-008-0	01.3	The contingency plan must address monitoring and control of critical transmission facilities, generation control, voltage control, time and frequency control, control of critical substation devices, and logging of significant power system events. The plan shall list the critical facilities.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-008-0	01.4	The plan shall include procedures and responsibilities for maintaining basic voice communication capabilities with other areas.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
EOP-008-0	01.5	The plan shall include procedures and responsibilities for conducting periodic tests, at least annually, to ensure viability of the plan.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-008-0	01.6	The plan shall include procedures and responsibilities for providing annual training to ensure that operating personnel are able to implement the contingency plans.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-008-0	01.7	The plan shall be reviewed and updated annually.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-008-0	01.8	Interim provisions must be included if it is expected to take more than one hour to implement the contingency plan for loss of primary control facility.		X	X	X															CCR / RCCR	NPCC RRP	BA, RC, TOP
EOP-009-0	0.	Documentation of Blackstart Generating Unit Test Results											X	X							Blackstart Generating Station identified in the Registry		Adopted by NERC: 2006-05-02
EOP-009-0	01.	The Generator Operator of each blackstart generating unit shall test the startup and operation of each system blackstart generating unit identified in the BCP as required in the Regional BCP (Reliability Standard EOP-007-0_R1). Testing records shall include the dates of the tests, the duration of the tests, and an indication of whether the tests met Regional BCP requirements.											X								Blackstart Generating Station identified in the Registry	NPCC A-03	GO-1, GOP-1
EOP-009-0	02.	The Generator Owner or Generator Operator shall provide documentation of the test results of the startup and operation of each blackstart generating unit to the Regional Reliability Organizations and upon request to NERC.											X	X							Blackstart Generating Station identified in the Registry	NPCC A-03	GO-1, GOP-1
FAC-001-0	0.	Facility Connection Requirements							X												Main Transmission System		Adopted by NERC: 2006-05-02
FAC-001-0	01.	The Transmission Owner shall document, maintain, and publish facility connection requirements to ensure compliance with NERC Reliability Standards and applicable Regional Reliability Organization, subregional, Power Pool, and individual Transmission Owner planning Criteria and facility connection requirements. The Transmission Owner's facility connection requirements shall address connection requirements for (refer to R1.1, etc. below):									X										Main Transmission System	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	01.1	Generation facilities								X											Main Transmission System	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	01.2	Transmission facilities								X											Main Transmission System connection tap	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	01.3	End User facilities								X											Main Transmission System connection tap	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.	The Transmission Owner's facility connection requirements shall address, but are not limited to, the following items:								X											Main Transmission System	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1	Provide a written summary of its plans to achieve the required system performance as described above throughout the planning horizon:								X											Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.1	Procedures for coordinated joint studies of new facilities and their impacts on the interconnected transmission systems.								X											Main Transmission System	HQT Facility Connection Requirements NPCC B-04	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.10	Power quality impacts								X											Main Transmission System		TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.11	Equipment ratings								X											Main Transmission System	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.12	Synchronizing of facilities								X											Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
FAC-001-0	02.1.13	Maintenance coordination							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.14	Operational issues (abnormal frequency and voltages)							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.15	Inspection requirements for existing or new facilities							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.16	Communications and procedures during normal and emergency operating conditions.							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.2	Procedures for notification of new or modified facilities to others (those responsible for the reliability of the interconnected transmission systems) as soon as feasible.							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.3	Voltage level and MW and MVAR capacity or demand at point of connection.							X													Main Transmission System	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.4	Breaker duty and surge protection							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.5	System protection and coordination							X													Main Transmission System	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.6	Metering and telecommunications							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.7	Grounding and safety issues							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.8	Insulation and insulation coordination							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	02.1.9	Voltage, Reactive Power, and power factor control.							X													Main Transmission System	HQT Facility Connection Requirements	TO-1, TO-2, TO-3, TO-4
FAC-001-0	03.	The Transmission Owner shall maintain and update its facility connection requirements as required. The Transmission Owner shall make documentation of these requirements available to the users of the transmission system, the Regional Reliability Organization, and NERC on request (five business days).							X													Main Transmission System	HQT Facility Connection Requirements NPCC C-29	TO-1, TO-2, TO-3, TO-4
FAC-002-0	0.	Coordination of Plans For New Generation, Transmission, and End-User							X	X		X		X		X	X					Main Transmission System and Distribution Systems		Adopted by NERC: 2006-05-02
FAC-002-0	01.	The Generator Owner, Transmission Owner, Distribution Provider, and Load-Serving Entity seeking to integrate generation facilities, transmission facilities, and electricity end-user facilities shall each coordinate and cooperate on its assessments with its Transmission Planner and Planning Authority. The assessment shall include (see R1.1, R1.2, etc. below):							X					X		X	X					Main Transmission System and Distribution Systems	HQT Facility Connection Requirements Common Operating Instruction Connection Agreement Contract(s) NPCC C-29	DP GO-1, GO-2, GO-3, GO-4* LSE-1, LSE-2 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-002-0	01.1	Evaluation of the reliability impact of the new facilities and their connections on the interconnected transmission systems.							X					X		X	X					Main Transmission System and Distribution Systems		DP GO-1, GO-2, GO-3, GO-4* LSE-1, LSE-2 TO-1, TO-2, TO-3, TO-4, TO-5

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities				
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC			
FAC-003-1	01.1	The TVMP shall define a schedule for and the type (aerial, ground) of ROW vegetation inspections. This schedule should be flexible enough to adjust for changing conditions. The inspection schedule shall be based on the anticipated growth of vegetation and any other environmental or operational factors that could impact the relationship of vegetation to the Transmission Owner's transmission lines.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	01.2	The Transmission Owner, in the TVMP, shall identify and document clearances between vegetation and any overhead, ungrounded supply conductors, taking into consideration transmission line voltage, the effects of ambient temperature on conductor sag under maximum design loading, and the effects of wind velocities on conductor sway. Specifically, the Transmission Owner shall establish clearances to be achieved at the time of vegetation management work identified herein as Clearance 1, and shall also establish and maintain a set of clearances identified herein as Clearance 2 to prevent flashover between vegetation and overhead ungrounded supply conductors.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	01.2.1	Clearance 1 — The Transmission Owner shall determine and document appropriate clearance distances to be achieved at the time of transmission vegetation management work based upon local conditions and the expected time frame in which the Transmission Owner plans to return for future vegetation management work. Local conditions may include, but are not limited to: operating voltage, appropriate vegetation management techniques, fire risk, reasonably anticipated tree and conductor movement, species types and growth rates, species failure characteristics, local climate and rainfall patterns, line terrain and elevation, location of the vegetation within the span, and worker approach distance requirements. Clearance 1 distances shall be greater than those defined by Clearance 2 below.								X														All transmission lines operated at 200 kV and above	NPCC RRP	TO-1, TO-3
FAC-003-1	01.2.2	Clearance 2 — The Transmission Owner shall determine and document specific radial clearances to be maintained between vegetation and conductors under all rated electrical operating conditions. These minimum clearance distances are necessary to prevent flashover between vegetation and conductors and will vary due to such factors as altitude and operating voltage. These Transmission Owner-specific minimum clearance distances shall be no less than those set forth in the Institute of Electrical and Electronics Engineers (IEEE) Standard 516-2003 (Guide for Maintenance Methods on Energized Power Lines) and as specified in its Section 4.2.2.3, Minimum Air Insulation Distances without Tools in the Air Gap.								X														All transmission lines operated at 200 kV and above	NPCC RRP	TO-1, TO-3
FAC-003-1	01.2.2.1	Where transmission system transient overvoltage factors are not known, clearances shall be derived from Table 5, IEEE 516-2003, phase-to-ground distances, with appropriate altitude correction factors applied.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	01.2.2.2	Where transmission system transient overvoltage factors are known, clearances shall be derived from Table 7, IEEE 516-2003, phase-to-phase voltages, with appropriate altitude correction factors applied.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	01.3	All personnel directly involved in the design and implementation of the TVMP shall hold appropriate qualifications and training, as defined by the Transmission Owner, to perform their duties.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	01.4	Each Transmission Owner shall develop mitigation measures to achieve sufficient clearances for the protection of the transmission facilities when it identifies locations on the ROW where the Transmission Owner is restricted from attaining the clearances specified in Requirement 1.2.1.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	01.5	Each Transmission Owner shall establish and document a process for the immediate communication of vegetation conditions that present an imminent threat of a transmission line outage. This is so that action (temporary reduction in line rating, switching line out of service, etc.) may be taken until the threat is relieved.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities				
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC			
FAC-003-1	02.	The Transmission Owner shall create and implement an annual plan for vegetation management work to ensure the reliability of the system. The plan shall describe the methods used, such as manual clearing, mechanical clearing, herbicide treatment, or other actions. The plan should be flexible enough to adjust to changing conditions, taking into consideration anticipated growth of vegetation and all other environmental factors that may have an impact on the reliability of the transmission systems. Adjustments to the plan shall be documented as they occur. The plan should take into consideration the time required to obtain permissions or permits from landowners or regulatory authorities. Each Transmission Owner shall have systems and procedures for documenting and tracking the planned vegetation management work and ensuring that the vegetation management work was completed according to work specifications.								X													All transmission lines operated at 200 kV and above		TO-1, TO-3	
FAC-003-1	03.	The Transmission Owner shall report quarterly to its RRO, or the RRO's designee, sustained transmission line outages determined by the Transmission Owner to have been caused by vegetation.								X														All transmission lines operated at 200 kV and above	NPCC RRP	TO-1, TO-3
FAC-003-1	03.1	Multiple sustained outages on an individual line, if caused by the same vegetation, shall be reported as one outage regardless of the actual number of outages within a 24-hour period.								X														All transmission lines operated at 200 kV and above	NPCC RRP	TO-1, TO-3
FAC-003-1	03.2	The Transmission Owner is not required to report to the RRO, or the RRO's designee, certain sustained transmission line outages caused by vegetation: (1) Vegetation related outages that result from vegetation falling into lines from outside the ROW that result from natural disasters shall not be considered reportable (examples of disasters that could create non-reportable outages include, but are not limited to, earthquakes, fires, tornados, hurricanes, landslides, wind shear, major storms as defined either by the Transmission Owner or an applicable regulatory body, ice storms, and floods), and (2) Vegetation-related outages due to human or animal activity shall not be considered reportable (examples of human or animal activity that could cause a non-reportable outage include, but are not limited to, logging, animal severing tree, vehicle contact with tree, arboricultural activities or horticultural or agricultural activities, or removal or digging of vegetation).								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	03.3	The outage information provided by the Transmission Owner to the RRO, or the RRO's designee, shall include at a minimum: the name of the circuit(s) outaged, the date, time and duration of the outage; a description of the cause of the outage; other pertinent comments; and any countermeasures taken by the Transmission Owner.								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	03.4	An outage shall be categorized as one of the following:								X														All transmission lines operated at 200 kV and above		TO-1, TO-3
FAC-003-1	03.4.1	Category 1 — Grow-ins: Outages caused by vegetation growing into lines from vegetation inside and/or outside of the ROW;								X														All transmission lines operated at 200 kV and above	NPCC RRP	TO-1, TO-3
FAC-003-1	03.4.2	Category 2 — Fall-ins: Outages caused by vegetation falling into lines from inside the ROW;								X														All transmission lines operated at 200 kV and above	NPCC RRP	TO-1, TO-3
FAC-003-1	03.4.3	Category 3 — Fall-ins: Outages caused by vegetation falling into lines from outside the ROW.								X														All transmission lines operated at 200 kV and above	NPCC RRP	TO-1, TO-3
FAC-003-1	04.	The RRO shall report the outage information provided to it by Transmission Owner's, as required by Requirement 3, quarterly to NERC, as well as any actions taken by the RRO as a result of any of the reported outages.	X																					All transmission lines operated at 200 kV and above		<i>Not applicable in Québec (NPCC only)</i>
FAC-008-1	0.	Facility Ratings Methodology								X					X									Main Transmission System		Adopted by NERC: 2006-02-07
FAC-008-1	01.	The Transmission Owner and Generator Owner shall each document its current methodology used for developing Facility Ratings (Facility Ratings Methodology) of its solely and jointly owned Facilities. The methodology shall include all of the following:								X						X								Main Transmission System	NPCC C-29	GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.1	A statement that a Facility Rating shall equal the most limiting applicable Equipment Rating of the individual equipment that comprises that Facility.								X						X								Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities			
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC		
FAC-008-1	01.2	The method by which the Rating (of major BES equipment that comprises a Facility) is determined.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.2.1	The scope of equipment addressed shall include, but not be limited to, generators, transmission conductors, transformers, relay protective devices, terminal equipment, and series and shunt compensation devices.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.2.2	The scope of Ratings addressed shall include, as a minimum, both Normal and Emergency Ratings.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.3	Consideration of the following:								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.3.1	Ratings provided by equipment manufacturers.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.3.2	Design Criteria (e.g., including applicable references to industry Rating practices such as manufacturer's warranty, IEEE, ANSI or other Standards).								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.3.3	Ambient conditions								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.3.4	Operating limitations.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	01.3.5	Other assumptions.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	02.	The Transmission Owner and Generator Owner shall each make its Facility Ratings Methodology available for inspection and technical review by those Reliability Coordinators, Transmission Operators, Transmission Planners, and Planning Authorities that have responsibility for the area in which the associated Facilities are located, within 15 business days of receipt of a request.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-008-1	03.	If a Reliability Coordinator, Transmission Operator, Transmission Planner, or Planning Authority provides written comments on its technical review of a Transmission Owner's or Generator Owner's Facility Ratings Methodology, the Transmission Owner or Generator Owner shall provide a written response to that commenting entity within 45 calendar days of receipt of those comments. The response shall indicate whether a change will be made to the Facility Ratings Methodology and, if no change will be made to that Facility Ratings Methodology, the reason why.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-009-1	0.	Establish and Communicate Facility Ratings								X													Main Transmission System		Adopted by NERC: 2006-02-07
FAC-009-1	01.	The Transmission Owner and Generator Owner shall each establish Facility Ratings for its solely and jointly owned Facilities that are consistent with the associated Facility Ratings Methodology.								X													Main Transmission System	NPCC C-29	GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-009-1	02.	The Transmission Owner and Generator Owner shall each provide Facility Ratings for its solely and jointly owned Facilities that are existing Facilities, new Facilities, modifications to existing Facilities and re-ratings of existing Facilities to its associated Reliability Coordinator(s), Planning Authority(ies), Transmission Planner(s), and Transmission Operator(s) as scheduled by such requesting entities.								X													Main Transmission System		GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4, TO-5
FAC-010-1	0.	System Operating Limits Methodology for the Planning Horizon																					Main Transmission System		Adopted by NERC: 2006-11-01
FAC-010-1	01.	The Planning Authority shall have a documented SOL Methodology for use in developing SOLs within its Planning Authority Area. This SOL Methodology shall:																					Main Transmission System		PA
FAC-010-1	01.1	Be applicable for developing SOLs used in the planning horizon.																					Main Transmission System		PA
FAC-010-1	01.2	State that SOLs shall not exceed associated Facility Ratings.																					Main Transmission System		PA
FAC-010-1	01.3	Include a description of how to identify the subset of SOLs that qualify as IROLs.																					Main Transmission System		PA
FAC-010-1	02.	The Planning Authority's SOL Methodology shall include a requirement that SOLs provide BES performance consistent with the following:																					Main Transmission System	NPCC A-02	PA
FAC-010-1	02.1	In the pre-contingency state and with all Facilities in service, the BES shall demonstrate transient, dynamic and voltage stability; all Facilities shall be within their Facility Ratings and within their thermal, voltage and stability limits. In the determination of SOLs, the BES condition used shall reflect expected system conditions and shall reflect changes to system topology such as Facility outages.																					Main Transmission System	NPCC A-02	PA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities				
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC			
FAC-010-1	02.2	Following the single Contingencies (*) identified in Requirement 2.2.1 through Requirement 2.2.3, the system shall demonstrate transient, dynamic and voltage stability; all Facilities shall be operating within their Facility Ratings and within their thermal, voltage and stability limits; and Cascading Outages or uncontrolled separation shall not occur. (*) The Contingencies identified in R2.2.1 through R2.2.3 are the minimum contingencies that must be studied but are not necessarily the only Contingencies that should be studied.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.2.1	Single line to ground or three-phase Fault (whichever is more severe), with Normal Clearing, on any Faulted generator, line, transformer, or shunt device.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.2.2	Loss of any generator, line, transformer, or shunt device without a Fault.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.2.3	Single pole block, with Normal Clearing, in a monopolar or bipolar high voltage direct current system.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.3	Starting with all Facilities in service, the system's response to a single Contingency, may include any of the following:											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.3.1	Planned or controlled interruption of electric supply to radial customers or some local network customers connected to or supplied by the Faulted Facility or by the affected area.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.3.2	System reconfiguration through manual or automatic control or protection actions.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.3.3	To prepare for the next Contingency, system adjustments may be made, including changes to generation, uses of the transmission system, and the transmission system topology.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.4	Starting with all facilities in service and following any of the multiple Contingencies identified in Reliability Standard TPL-003 the system shall demonstrate transient, dynamic and voltage stability; all Facilities shall be operating within their Facility Ratings and within their thermal, voltage and stability limits; and Cascading Outages or uncontrolled separation shall not occur.											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.5	In determining the system's response to any of the multiple Contingencies, identified in Reliability Standard TPL-003, in addition to the actions identified in R2.3.1 and R2.3.2, the following shall be acceptable:											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	02.5.1	Planned or controlled interruption of electric supply to customers (load shedding), the planned removal from service of certain generators, and/or the curtailment of contracted Firm (non-recallable reserved) electric power Transfers											X											Main Transmission System	NPCC A-02	PA
FAC-010-1	03.	The Planning Authority's methodology for determining SOLs, shall include, as a minimum, a description of the following, along with any reliability margins applied for each:											X											Main Transmission System		PA
FAC-010-1	03.1	Study model (must include at least the entire Planning Authority Area as well as the critical modeling details from other Planning Authority Areas that would impact the Facility or Facilities under study).											X											Main Transmission System		PA
FAC-010-1	03.2	Selection of applicable Contingencies.											X											Main Transmission System		PA
FAC-010-1	03.3	Level of detail of system models used to determine SOLs.											X											Main Transmission System		PA
FAC-010-1	03.4	Allowed uses of Special Protection Systems or Remedial Action Plans.											X											Main Transmission System		PA
FAC-010-1	03.5	Anticipated transmission system configuration, generation dispatch and Load level.											X											Main Transmission System		PA
FAC-010-1	03.6	Criteria for determining when violating a SOL qualifies as an Interconnection Reliability Operating Limit (IROL) and criteria for developing any associated IROL T _v .											X											Main Transmission System		PA
FAC-010-1	04.	The Planning Authority shall issue its SOL Methodology, and any change to that methodology, to all of the following prior to the effectiveness of the change:											X											Main Transmission System		PA
FAC-010-1	04.1	Each adjacent Planning Authority and each Planning Authority that indicated it has a reliability-related need for the methodology.											X											Main Transmission System		PA
FAC-010-1	04.2	Each Reliability Coordinator and Transmission Operator that operates any portion of the Planning Authority's Planning Authority Area.											X											Main Transmission System		PA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities			
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC		
FAC-010-1	04.3	Each Transmission Planner that works in the Planning Authority's Planning Authority Area.											X									Main Transmission System		PA	
FAC-010-1	05.	If a recipient of the SOL Methodology provides documented technical comments on the methodology, the Planning Authority shall provide a documented response to that recipient within 45 calendar days of receipt of those comments. The response shall indicate whether a change will be made to the SOL Methodology and, if no change will be made to that SOL Methodology, the reason why.											X										Main Transmission System		PA
FAC-011-1	0.	System Operating Limits Methodology for the Operations Horizon		X																			Main Transmission System		Adopted by NERC: 2006-11-01
FAC-011-1	01.	The Reliability Coordinator shall have a documented methodology for use in developing SOLs (SOL Methodology) within its Reliability Coordinator Area. This SOL Methodology shall:		X																			Main Transmission System		RC
FAC-011-1	01.1	Be applicable for developing SOLs used in the operations horizon.		X																			Main Transmission System		RC
FAC-011-1	01.2	State that SOLs shall not exceed associated Facility Ratings.		X																			Main Transmission System		RC
FAC-011-1	01.3	Include a description of how to identify the subset of SOLs that qualify as IROLs.		X																			Main Transmission System		RC
FAC-011-1	02.	The Reliability Coordinator's SOL Methodology shall include a requirement that SOLs provide BES performance consistent with the following:		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.1	In the pre-contingency state, the BES shall demonstrate transient, dynamic and voltage stability; all Facilities shall be within their Facility Ratings and within their thermal, voltage and stability limits. In the determination of SOLs, the BES condition used shall reflect current or expected system conditions and shall reflect changes to system topology such as Facility outages.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.2	Following the single Contingencies (*) identified in Requirement 2.2.1 through Requirement 2.2.3, the system shall demonstrate transient, dynamic and voltage stability; all Facilities shall be operating within their Facility Ratings and within their thermal, voltage and stability limits; and Cascading Outages or uncontrolled separation shall not occur. (*) The Contingencies identified in R2.2.1 through R2.2.3 are the minimum contingencies that must be studied but are not necessarily the only Contingencies that should be studied.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.2.1	Single line to ground or 3-phase Fault (whichever is more severe), with Normal Clearing, on any Faulted generator, line, transformer, or shunt device.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.2.2	Loss of any generator, line, transformer, or shunt device without a Fault.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.2.3	Single pole block, with Normal Clearing, in a monopolar or bipolar high voltage direct current system.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.3	In determining the system's response to a single Contingency, the following shall be acceptable:		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.3.1	Planned or controlled interruption of electric supply to radial customers or some local network customers connected to or supplied by the Faulted Facility or by the affected area.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.3.2	Interruption of other network customers, only if the system has already been adjusted, or is being adjusted, following at least one prior outage, or, if the real-time operating conditions are more adverse than anticipated in the corresponding studies, e.g., load greater than studied.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.3.3	System reconfiguration through manual or automatic control or protection actions.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	02.4	To prepare for the next Contingency, system adjustments may be made, including changes to generation, uses of the transmission system, and the transmission system topology.		X																			Main Transmission System	NPCC A-02	RC
FAC-011-1	03.	The Reliability Coordinator's methodology for determining SOLs, shall include, as a minimum, a description of the following, along with any reliability margins applied for each:		X																			Main Transmission System		RC

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
FAC-011-1	03.1	Study model (must include at least the entire Reliability Coordinator Area as well as the critical modeling details from other Reliability Coordinator Areas that would impact the Facility or Facilities under study.)		X																	Main Transmission System		RC
FAC-011-1	03.2	Selection of applicable Contingencies		X																	Main Transmission System		RC
FAC-011-1	03.3	A process for determining which of the stability limits associated with the list of multiple contingencies (provided by the Planning Authority in accordance with FAC-014 Requirement 6) are applicable for use in the operating horizon given the actual or expected system conditions.		X																	Main Transmission System		RC
FAC-011-1	03.3.1	This process shall address the need to modify these limits, to modify the list of limits, and to modify the list of associated multiple contingencies.		X																	Main Transmission System		RC
FAC-011-1	03.4	Level of detail of system models used to determine SOLs.		X																	Main Transmission System		RC
FAC-011-1	03.5	Allowed uses of Special Protection Systems or Remedial Action Plans.		X																	Main Transmission System		RC
FAC-011-1	03.6	Anticipated transmission system configuration, generation dispatch and Load level		X																	Main Transmission System		RC
FAC-011-1	03.7	Criteria for determining when violating a SOL qualifies as an Interconnection Reliability Operating Limit (IROL) and criteria for developing any associated IROL T _v .		X																	Main Transmission System		RC
FAC-011-1	04.	The Reliability Coordinator shall issue its SOL Methodology and any changes to that methodology, prior to the effectiveness of the Methodology or of a change to the Methodology, to all of the following:		X																	Main Transmission System		RC
FAC-011-1	04.1	Each adjacent Reliability Coordinator and each Reliability Coordinator that indicated it has a reliability-related need for the methodology.		X																	Main Transmission System		RC
FAC-011-1	04.2	Each Planning Authority and Transmission Planner that models any portion of the Reliability Coordinator's Reliability Coordinator Area.		X																	Main Transmission System		RC
FAC-011-1	04.3	Each Transmission Operator that operates in the Reliability Coordinator Area.		X																	Main Transmission System		RC
FAC-011-1	05.	If a recipient of the SOL Methodology provides documented technical comments on the methodology, the Reliability Coordinator shall provide a documented response to that recipient within 45 calendar days of receipt of those comments. The response shall indicate whether a change will be made to the SOL Methodology and, if no change will be made to that SOL Methodology, the reason why.		X																	Main Transmission System		RC
FAC-013-1	0.	Establish and Communicate Transfer Capabilities	(X)	X									X								Interconnection's paths of Main Transmission System		Adopted by NERC: 2006-02-07
FAC-013-1	01.	The Reliability Coordinator and Planning Authority shall each establish a set of inter-regional and intra-regional Transfer Capabilities that is consistent with its current Transfer Capability Methodology.		X									X								Interconnection's paths of Main Transmission System		RC PA
FAC-013-1	02.	The Reliability Coordinator and Planning Authority shall each provide its inter-regional and intra-regional Transfer Capabilities to those entities that have a reliability-related need for such Transfer Capabilities and make a written request that includes a schedule for delivery of such Transfer Capabilities as follows:		X																	Interconnection's paths of Main Transmission System		RC
FAC-013-1	02.1	The Reliability Coordinator shall provide its Transfer Capabilities to its associated Regional Reliability Organization(s), to its adjacent Reliability Coordinators, and to the Transmission Operators, Transmission Service Providers and Planning Authorities that work in its Reliability Coordinator Area.		X																	Interconnection's paths of Main Transmission System		RC
FAC-013-1	02.2	The Planning Authority shall provide its Transfer Capabilities to its associated Reliability Coordinator(s) and Regional Reliability Organization(s), and to the Transmission Planners and Transmission Service Provider(s) that work in its Planning Authority Area.											X								Interconnection's paths of Main Transmission System		PA
FAC-014-1	0.	Establish and Communicate System Operating Limits		X	X								X								Main Transmission System		Adopted by NERC: 2006-11-01
FAC-014-1	01.	The Reliability Coordinator shall ensure that SOLs, including Interconnection Reliability Operating Limits (IROLs), for its Reliability Coordinator Area are established and that the SOLs (including Interconnection Reliability Operating Limits) are consistent with its SOL Methodology.		X																	Main Transmission System		RC

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
FAC-014-1	02.	The Transmission Operator shall establish SOLs (as directed by its Reliability Coordinator) for its portion of the Reliability Coordinator Area that are consistent with its Reliability Coordinator's SOL Methodology.			X																Main Transmission System		TOP
FAC-014-1	03.	The Planning Authority shall establish SOLs, including IROLs, for its Planning Authority Area that are consistent with its SOL Methodology.										X									Main Transmission System		PA
FAC-014-1	04.	The Transmission Planner shall establish SOLs, including IROLs, for its Transmission Planning Area that are consistent with its Planning Authority's SOL Methodology.									X										Main Transmission System		TP
FAC-014-1	05.	The Reliability Coordinator, Planning Authority and Transmission Planner shall each provide its SOLs and IROLs to those entities that have a reliability-related need for those limits and provide a written request that includes a schedule for delivery of those limits as follows:		X							X	X									Main Transmission System		PA TP
FAC-014-1	05.1	The Reliability Coordinator shall provide its SOLs (including the subset of SOLs that are IROLs) to adjacent Reliability Coordinators and Reliability Coordinators who indicate a reliability-related need for those limits, and to the Transmission Operators, Transmission Planners, Transmission Service Providers and Planning Authorities within its Reliability Coordinator Area. For each IROL, the Reliability Coordinator shall provide the following supporting information:		X																	Main Transmission System		RC
FAC-014-1	05.1.1	Identification and status of the associated Facility (or group of Facilities) that is (are) critical to the derivation of the IROL.		X																	Main Transmission System		RC
FAC-014-1	05.1.2	The value of the IROL and its associated T _r .		X																	Main Transmission System		RC
FAC-014-1	05.1.3	The associated Contingency(ies).		X																	Main Transmission System		RC
FAC-014-1	05.1.4	The type of limitation represented by the IROL (e.g., voltage collapse, angular stability).		X																	Main Transmission System		RC
FAC-014-1	05.2	The Transmission Operator shall provide any SOLs it developed to its Reliability Coordinator and to the Transmission Service Providers that share its portion of the Reliability Coordinator Area.			X																Main Transmission System		TOP
FAC-014-1	05.3	The Planning Authority shall provide its SOLs (including the subset of SOLs that are IROLs) to adjacent Planning Authorities, and to Transmission Planners, Transmission Service Providers, Transmission Operators and Reliability Coordinators that work within its Planning Authority Area.										X									Main Transmission System		PA
FAC-014-1	05.4	The Transmission Planner shall provide its SOLs (including the subset of SOLs that are IROLs) to its Planning Authority, Reliability Coordinators, Transmission Operators, and Transmission Service Providers that work within its Transmission Planning Area and to adjacent Transmission Planners.									X										Main Transmission System		TP
FAC-014-1	06.	The Planning Authority shall identify the subset of multiple contingencies (if any), from Reliability Standard TPL-003 which result in stability limits.										X									Main Transmission System		PA
FAC-014-1	06.1	The Planning Authority shall provide this list of multiple contingencies and the associated stability limits to the Reliability Coordinators that monitor the facilities associated with these contingencies and limits.										X									Main Transmission System		PA
FAC-014-1	06.2	If the Planning Authority does not identify any stability-related multiple contingencies, the Planning Authority shall so notify the Reliability Coordinator.										X									Main Transmission System		PA
INT-001-3	0.	Interchange Information				X												X			Main Transmission System		Adopted by NERC: 2006-11-01
INT-001-3	01.	The Load-Serving, Purchasing-Selling Entity shall ensure that Arranged Interchange is submitted to the Interchange Authority for:																X			Main Transmission System		PSE
INT-001-3	01.1	All Dynamic Schedules at the expected average MW profile for each hour.																X			Main Transmission System		PSE
INT-001-3	02.	The Sink Balancing Authority shall ensure that Arranged Interchange is submitted to the Interchange Authority:				X															Main Transmission System		BA
INT-001-3	02.1	If a Purchasing-Selling Entity is not involved in the Interchange, such as delivery from a jointly owned generator.				X															Main Transmission System		BA
INT-001-3	02.2	For each bilateral Inadvertent Interchange payback.				X															Main Transmission System		BA
INT-003-2	0.	Interchange Transaction Implementation				X															Main Transmission System		Adopted by NERC: 2006-11-01

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities			
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC		
INT-003-2	01.	Each Receiving Balancing Authority shall confirm Interchange Schedules with the Sending Balancing Authority prior to implementation in the Balancing Authority's ACE equation.				X																Main Transmission System		BA	
INT-003-2	01.1	The Sending Balancing Authority and Receiving Balancing Authority shall agree on Interchange as received from the Interchange Authority, including:				X																	Main Transmission System		BA
INT-003-2	01.1.1	Interchange Schedule start and end time.				X																	Main Transmission System		BA
INT-003-2	01.1.2	Energy profile.				X																	Main Transmission System		BA
INT-003-2	01.2	If a high voltage direct current (HVDC) tie is on the Scheduling Path, then the Sending Balancing Authorities and Receiving Balancing Authorities shall coordinate the Interchange Schedule with the Transmission Operator of the HVDC tie.				X																	Main Transmission System		BA
INT-004-2	0.	Dynamic Interchange Transaction Modifications		X	X	X													X				Not actually applicable in Québec		Adopted by NERC: 2007-10-09
INT-004-2	01.	At such time as the reliability event allows for the reloading of the transaction, the entity that initiated the curtailment shall release the limit on the Interchange Transaction tag to allow reloading the transaction and shall communicate the release of the limit to the Sink Balancing Authority.		X	X	X																	Not actually applicable in Québec		BA, RC, TOP
INT-004-2	02.	The Purchasing-Selling Entity responsible for tagging a Dynamic Interchange Schedule shall ensure the tag is updated for the next available scheduling hour and future hours when any one of the following occurs:																	X				Not actually applicable in Québec		PSE
INT-004-2	02.1	The average energy profile in an hour is greater than 250 MW and in that hour the actual hourly integrated energy deviates from the hourly average energy profile indicated on the tag by more than +10%.																	X				Not actually applicable in Québec		PSE
INT-004-2	02.2	The average energy profile in an hour is less than or equal to 250 MW and in that hour the actual hourly integrated energy deviates from the hourly average energy profile indicated on the tag by more than +25 megawatt-hours.																	X				Not actually applicable in Québec		PSE
INT-004-2	02.3	A Reliability Coordinator or Transmission Operator determines the deviation, regardless of magnitude, to be a reliability concern and notifies the Purchasing-Selling Entity of that determination and the reasons.		X	X																		Not actually applicable in Québec		RC, TOP
INT-005-2	0.	Interchange Authority Distributes Arranged Interchange					X																Main Transmission System		Adopted by NERC: 2006-05-02
INT-005-2	01.	Prior to the expiration of the time period defined in the Timing Table, Column A, the Interchange Authority shall distribute the Arranged Interchange information for reliability assessment to all reliability entities involved in the Interchange.					X																Main Transmission System		IA
INT-005-2	01.1	When a Balancing Authority or Reliability Coordinator initiates a Curtailment to Confirmed or Implemented Interchange for reliability, the Interchange Authority shall distribute the Arranged Interchange information for reliability assessment only to the Source Balancing Authority and the Sink Balancing Authority.					X																Main Transmission System		IA
INT-006-2	0.	Response to Interchange Authority				X					X												Main Transmission System		Adopted by NERC: 2006-05-02
INT-006-2	01.	Prior to the expiration of the reliability assessment period defined in the Timing Table, Column B, the Balancing Authority and Transmission Service Provider shall respond to a request from an Interchange Authority to transition an Arranged Interchange to a Confirmed Interchange.				X					X												Main Transmission System		BA TSP-1, TSP-2
INT-006-2	01.1	Each involved Balancing Authority shall evaluate the Arranged Interchange with respect to:				X																	Main Transmission System		BA
INT-006-2	01.1.1	Energy profile (ability to support the magnitude of the Interchange).				X																	Main Transmission System		BA
INT-006-2	01.1.2	Ramp (ability of generation maneuverability to accommodate).				X																	Main Transmission System		BA
INT-006-2	01.1.3	Scheduling path (proper connectivity of Adjacent Balancing Authorities).				X																	Main Transmission System		BA
INT-006-2	01.2	Each involved Transmission Service Provider shall confirm that the transmission service arrangements associated with the Arranged Interchange have adjacent Transmission Service Provider connectivity, are valid and prevailing transmission system limits will not be violated.									X												Main Transmission System		TSP-1, TSP-2
INT-007-1	0.	Interchange Confirmation					X																Main Transmission System		Adopted by NERC: 2006-05-02

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
INT-007-1	01.	The Interchange Authority shall verify that Arranged Interchange is balanced and valid prior to transitioning Arranged Interchange to Confirmed Interchange by verifying the following:					X															Main Transmission System		IA
INT-007-1	01.1	Source Balancing Authority megawatts equal sink Balancing Authority megawatts (adjusted for losses, if appropriate).					X															Main Transmission System		IA
INT-007-1	01.2	All reliability entities involved in the Arranged Interchange are currently in the NERC registry.					X															Main Transmission System		IA
INT-007-1	01.3	The following are defined:					X															Main Transmission System		IA
INT-007-1	01.3.1	Generation source and load sink.					X															Main Transmission System		IA
INT-007-1	01.3.2	Megawatt profile.					X															Main Transmission System		IA
INT-007-1	01.3.3	Ramp start and stop times.					X															Main Transmission System		IA
INT-007-1	01.3.4	Interchange duration.					X															Main Transmission System		IA
INT-007-1	01.4	Each Balancing Authority and Transmission Service Provider that received the Arranged Interchange information from the Interchange Authority for reliability assessment has provided approval.					X															Main Transmission System		IA
INT-008-2	0.	Interchange Authority Distributes Status					X															Main Transmission System		Adopted by NERC: 2006-05-02
INT-008-2	01.	Prior to the expiration of the time period defined in the Timing Table, Column C, the Interchange Authority shall distribute to all Balancing Authorities (including Balancing Authorities on both sides of a direct current tie), Transmission Service Providers and Purchasing-Selling Entities involved in the Arranged Interchange whether or not the Arranged Interchange has transitioned to a Confirmed Interchange.					X															Main Transmission System		IA
INT-008-2	01.1	For Confirmed Interchange, the Interchange Authority shall also communicate:					X															Main Transmission System		IA
INT-008-2	01.1.1	Start and stop times, ramps, and megawatt profile to Balancing Authorities.					X															Main Transmission System		IA
INT-008-2	01.1.2	Necessary Interchange information to NERC-identified reliability analysis services.					X															Main Transmission System		IA
INT-009-1	0.	Implementation of Interchange					X															Main Transmission System		Adopted by NERC: 2006-05-02
INT-009-1	01.	The Balancing Authority shall implement Confirmed Interchange as received from the Interchange Authority.					X															Main Transmission System		BA
INT-010-1	0.	Interchange Coordination Exemptions		X			X															Main Transmission System		Adopted by NERC: 2006-05-02
INT-010-1	01.	The Balancing Authority that experiences a loss of resources covered by an energy sharing agreement shall ensure that a request for an Arranged Interchange is submitted with a start time no more than 60 minutes beyond the resource loss. If the use of the energy sharing agreement does not exceed 60 minutes from the time of the resource loss, no request for Arranged Interchange is required.					X															Main Transmission System		BA
INT-010-1	02.	For a modification to an existing Interchange schedule that is directed by a Reliability Coordinator for current or imminent reliability-related reasons, the Reliability Coordinator shall direct a Balancing Authority to submit the modified Arranged Interchange reflecting that modification within 60 minutes of the initiation of the event.		X																		Main Transmission System		RC
INT-010-1	03.	For a new Interchange schedule that is directed by a Reliability Coordinator for current or imminent reliability-related reasons, the Reliability Coordinator shall direct a Balancing Authority to submit an Arranged Interchange reflecting that Interchange schedule within 60 minutes of the initiation of the event.		X																		Main Transmission System		RC
IRO-001-1	0.	Reliability Coordination – Responsibilities and Authorities	X	X	X	X					X		X				X		X			See each requirements		Adopted by NERC: 2006-11-01
IRO-001-1	01.	Each Regional Reliability Organization, subregion, or interregional coordinating group shall establish one or more Reliability Coordinators to continuously assess transmission reliability and coordinate emergency operations among the operating entities within the region and across the regional boundaries.	X																			Québec Interconnection	The Act respecting the Régie de l'énergie	Régie de l'énergie
IRO-001-1	02.	The Reliability Coordinator shall comply with a regional reliability plan approved by the NERC Operating Committee.		X																		Applicable only to Rc	NPCC RRP	RC

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
IRO-001-1	03.	The Reliability Coordinator shall have clear decision-making authority to act and to direct actions to be taken by Transmission Operators, Balancing Authorities, Generator Operators, Transmission Service Providers, Load-Serving Entities, and Purchasing-Selling Entities within its Reliability Coordinator Area to preserve the integrity and reliability of the Bulk Electric System. These actions shall be taken without delay, but no longer than 30 minutes.		X																	Applicable only to Rc	NPCC RRP	RC
IRO-001-1	04.	Reliability Coordinators that delegate tasks to other entities shall have formal operating agreements with each entity to which tasks are delegated. The Reliability Coordinator shall verify that all delegated tasks are understood, communicated, and addressed within its Reliability Coordinator Area. All responsibilities for complying with NERC and regional Standards applicable to Reliability Coordinators shall remain with the Reliability Coordinator.		X																	Applicable only to Rc	NPCC RRP	RC
IRO-001-1	05.	The Reliability Coordinator shall list within its reliability plan all entities to which the Reliability Coordinator has delegated required tasks.		X																	Applicable only to Rc		RC
IRO-001-1	06.	The Reliability Coordinator shall verify that all delegated tasks are carried out by NERC certified Reliability Coordinator operating personnel.		X																	Applicable only to Rc	NPCC RRP	RC
IRO-001-1	07.	The Reliability Coordinator shall have clear, comprehensive coordination agreements with adjacent Reliability Coordinators to ensure that System Operating Limit or Interconnection Reliability Operating Limit violation mitigation requiring actions in adjacent Reliability Coordinator Areas are coordinated.		X																	Main Transmission System	NPCC RRP	RC
IRO-001-1	08.	Transmission Operators, Balancing Authorities, Generator Operators, Transmission Service Providers, Load-Serving Entities, and Purchasing-Selling Entities shall comply with Reliability Coordinator directives unless such actions would violate safety, equipment, or regulatory or statutory requirements. Under these circumstances, the Transmission Operator, Balancing Authority, Generator Operator, Transmission Service Provider, Load-Serving Entity, or Purchasing-Selling Entity shall immediately inform the Reliability Coordinator of the inability to perform the directive so that the Reliability Coordinator may implement alternate remedial actions.			X	X											X		X		Main Transmission System	NPCC RRP	BA, TOP GOP-1, GOP-2, GOP-3 LSE-1 PSE TSP-1, TSP-2, TSP-3
IRO-001-1	09.	The Reliability Coordinator shall act in the interests of reliability for the overall Reliability Coordinator Area and the Interconnection before the interests of any other entity.		X																	Québec Interconnection	NPCC RRP	RC
IRO-002-1	0.	Reliability Coordination - Facilities		X																CCR / RCCR (Main Transmission System)		Adopted by NERC: 2006-11-01	
IRO-002-1	01.	Each Reliability Coordinator shall have adequate communications facilities (voice and data links) to appropriate entities within its Reliability Coordinator Area. These communications facilities shall be staffed and available to act in addressing a real-time emergency condition.		X																	CCR / RCCR	NPCC RRP	RC
IRO-002-1	02.	Each Reliability Coordinator shall determine the data requirements to support its reliability coordination tasks and shall request such data from its Transmission Operators, Balancing Authorities, Transmission Owners, Generation Owners, Generation Operators, and Load-Serving Entities, or adjacent Reliability Coordinators.		X																	CCR / RCCR	NPCC RRP	RC
IRO-002-1	03.	Each Reliability Coordinator – or its Transmission Operators and Balancing Authorities – shall provide, or arrange provisions for, data exchange to other Reliability Coordinators or Transmission Operators and Balancing Authorities via a secure network.		X																	CCR / RCCR	NPCC RRP	RC
IRO-002-1	04.	Each Reliability Coordinator shall have multi-directional communications capabilities with its Transmission Operators and Balancing Authorities, and with neighboring Reliability Coordinators, for both voice and data exchange as required to meet reliability needs of the Interconnection.		X																	CCR / RCCR	NPCC RRP	RC

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
IRO-002-1	05.	Each Reliability Coordinator shall have detailed real-time monitoring capability of its RC Area and sufficient monitoring capability of its surrounding RC Areas to ensure that potential or actual SOL or IROL violations are identified. Each RC shall have monitoring systems that provide information that can be easily understood and interpreted by the RC operating personnel, giving particular emphasis to alarm management and awareness systems, automated data transfers, and synchronized information systems, over a redundant and highly reliable infrastructure.		X																	CCR / RCCR	NPCC RRP	RC
IRO-002-1	06.	Each Reliability Coordinator shall monitor Bulk Electric System elements (generators, transmission lines, buses, transformers, breakers, etc.) that could result in SOL or IROL violations within its Reliability Coordinator Area. Each Reliability Coordinator shall monitor both real and reactive power system flows, and operating reserves, and the status of Bulk Electric System elements that are or could be critical to SOLs and IROLs and system restoration requirements within its RC Area.		X																	CCR / RCCR (Main Transmission System)	NPCC RRP	RC
IRO-002-1	07.	Each Reliability Coordinator shall have adequate analysis tools such as state estimation, pre and post-contingency analysis capabilities (thermal, stability, and voltage), and wide-area overview displays.		X																	CCR / RCCR	NPCC RRP	RC
IRO-002-1	08.	Each Reliability Coordinator shall continuously monitor its RC Area. Each RC shall have provisions for backup facilities that shall be exercised if the main monitoring system is unavailable. Each RC shall ensure SOL and IROL monitoring and derivations continue if the main monitoring system is unavailable.		X																	CCR / RCCR	NPCC RRP	RC
IRO-002-1	09.	Each Reliability Coordinator shall control its Reliability Coordinator analysis tools, including approvals for planned maintenance. Each Reliability Coordinator shall have procedures in place to mitigate the effects of analysis tool outages.		X																	CCR / RCCR		RC
IRO-003-2	0.	Reliability Coordination – Wide-Area View		X																	CCR / RCCR		Adopted by NERC: 2006-11-01
IRO-003-2	01.	Each Reliability Coordinator shall monitor all Bulk Electric System facilities, which may include sub-transmission information, within its Reliability Coordinator Area and adjacent Reliability Coordinator Areas, as necessary to ensure that, at any time, regardless of prior planned or unplanned events, the Reliability Coordinator is able to determine any potential System Operating Limit and Interconnection Reliability Operating Limit violations within its Reliability Coordinator Area.		X																	CCR / RCCR	NPCC RRP	RC
IRO-003-2	02.	Each Reliability Coordinator shall know the current status of all critical facilities whose failure, degradation or disconnection could result in an SOL or IROL violation. Reliability Coordinators shall also know the status of any facilities that may be required to assist area restoration objectives.		X																	CCR / RCCR	NPCC RRP	RC
IRO-004-1	0.	Reliability Coordination – Operations Planning		X	X	X			X		X		X	X				X			Main Transmission System		Adopted by NERC: 2006-02-07
IRO-004-1	01.	Each Reliability Coordinator shall conduct next-day reliability analyses for its Reliability Coordinator Area to ensure that the Bulk Electric System can be operated reliably in anticipated normal and Contingency event conditions. The Reliability Coordinator shall conduct Contingency analysis studies to identify potential interface and other SOL and IROL violations, including overloaded transmission lines and transformers, voltage and stability limits, etc.		X																	Main Transmission System	NPCC RRP	RC
IRO-004-1	02.	Each Reliability Coordinator shall pay particular attention to parallel flows to ensure one Reliability Coordinator Area does not place an unacceptable or undue Burden on an adjacent Reliability Coordinator Area.		X																	Main Transmission System	NPCC RRP	RC
IRO-004-1	03.	Each Reliability Coordinator shall, in conjunction with its Transmission Operators and Balancing Authorities, develop action plans that may be required, including reconfiguration of the transmission system, re-dispatching of generation, reduction or curtailment of Interchange Transactions, or reducing load to return transmission loading to within acceptable SOLs or IROLs.		X	X	X															Main Transmission System	NPCC RRP	BA, RC, TOP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities				
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC			
IRO-004-1	04.	Each Transmission Operator, Balancing Authority, Transmission Owner, Generator Owner, Generator Operator, and Load-Serving Entity in the Reliability Coordinator Area shall provide information required for system studies, such as critical facility status, Load, generation, operating reserve projections, and known Interchange Transactions. This information shall be available by 1200 Central Standard Time for the Eastern Interconnection and 1200 Pacific Standard Time for the Western Interconnection.			X	X					X				X	X							Main Transmission System	NPCC RRP	BA, TOP LSE-1 TO-1, TO-2, TO-3, TO-4 GOP-1, GOP-2, GOP-3 GO-1, GO-2, GO-3, GO-4	
IRO-004-1	05.	Each Reliability Coordinator shall share the results of its system studies, when conditions warrant or upon request, with other Reliability Coordinators and with Transmission Operators, Balancing Authorities, and Transmission Service Providers within its Reliability Coordinator Area. The Reliability Coordinator shall make study results available no later than 1500 Central Standard Time for the Eastern Interconnection and 1500 Pacific Standard Time for the Western Interconnection, unless circumstances warrant otherwise		X																			Main Transmission System	NPCC RRP	RC	
IRO-004-1	06.	If the results of these studies indicate potential SOL or IROL violations, the Reliability Coordinator shall direct its Transmission Operators, Balancing Authorities and Transmission Service Providers to take any necessary action the Reliability Coordinator deems appropriate to address the potential SOL or IROL violation.		X																			Main Transmission System	NPCC RRP	RC	
IRO-004-1	07.	Each Transmission Operator, Balancing Authority, and Transmission Service Provider shall comply with the directives of its Reliability Coordinator based on the next day assessments in the same manner in which it would comply during real time operating events.		X	X	X																	Main Transmission System	NPCC RRP	BA, TOP, TSP-1, TSP-2, TSP-3	
IRO-005-1	0.	Reliability Coordination – Current Day Operations		X	X	X									X							X		Main Transmission System		Adopted by NERC: 2006-02-07
IRO-005-1	01.	Each Reliability Coordinator shall monitor its Reliability Coordinator Area parameters, including but not limited to the following:		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.1	Current status of Bulk Electric System elements (transmission or generation including critical auxiliaries such as Automatic Voltage Regulators and Special Protection Systems) and system loading.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.2	Current pre-contingency element conditions (voltage, thermal, or stability), including any applicable mitigation plans to alleviate SOL or IROL violations, including the plan's viability and scope.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.3	Current post-contingency element conditions (voltage, thermal, or stability), including any applicable mitigation plans to alleviate SOL or IROL violations, including the plan's viability and scope.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.4	System real and reactive reserves (actual versus required).		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.5	Capacity and energy adequacy conditions.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.6	Current ACE for all its Balancing Authorities.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.7	Current local or Transmission Loading Relief procedures in effect.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.8	Planned generation dispatches.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.9	Planned transmission or generation outages.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	01.10	Contingency events.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	02.	Each Reliability Coordinator shall be aware of all Interchange Transactions that wheel through, source, or sink in its Reliability Coordinator Area, and make that Interchange Transaction information available to all Reliability Coordinators in the Interconnection.		X																			Main Transmission System	NPCC RRP	RC	
IRO-005-1	03.	As portions of the transmission system approach or exceed SOLs or IROLs, the Reliability Coordinator shall work with its Transmission Operators and Balancing Authorities to evaluate and assess any additional Interchange Schedules that would violate those limits. If a potential or actual IROL violation cannot be avoided through proactive intervention, the Reliability Coordinator shall initiate control actions or emergency procedures to relieve the violation without delay, and no longer than 30 minutes. The Reliability Coordinator shall ensure all resources, including load shedding, are available to address a potential or actual IROL violation.		X	X	X																	Main Transmission System	NPCC RRP	BA, RC, TOP	

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
IRO-005-1	04.	Each Reliability Coordinator shall monitor its Balancing Authorities' parameters to ensure that the required amount of operating reserves is provided and available as required to meet the Control Performance Standard and Disturbance Control Standard requirements. If necessary, the Reliability Coordinator shall direct the Balancing Authorities in the Reliability Coordinator Area to arrange for assistance from neighboring Balancing Authorities. The Reliability Coordinator shall issue Energy Emergency Alerts as needed and at the request of its Balancing Authorities and Load-Serving Entities.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	05.	Each Reliability Coordinator shall identify the cause of any potential or actual SOL or IROL violations. The Reliability Coordinator shall initiate the control action or emergency procedure to relieve the potential or actual IROL violation without delay, and no longer than 30 minutes. The Reliability Coordinator shall be able to utilize all resources, including load shedding, to address an IROL violation.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	06.	Each Reliability Coordinator shall ensure its Transmission Operators and Balancing Authorities are aware of Geo-Magnetic Disturbance (GMD) forecast information and assist as needed in the development of any required response plans.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	07.	The Reliability Coordinator shall disseminate information within its Reliability Coordinator Area, as required.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	08.	Each Reliability Coordinator shall monitor system frequency and its Balancing Authorities' performance and direct any necessary rebalancing to return to CPS and DCS compliance. The Transmission Operators and Balancing Authorities shall utilize all resources, including firm load shedding, as directed by its Reliability Coordinator to relieve the emergent condition.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	09.	The Reliability Coordinator shall coordinate with Transmission Operators, Balancing Authorities, and Generator Operators as needed to develop and implement action plans to mitigate potential or actual SOL, IROL, CPS, or DCS violations. The Reliability Coordinator shall coordinate pending generation and transmission maintenance outages with Transmission Operators, Balancing Authorities, and Generator Operators as needed in both the real time and next-day reliability analysis timeframes.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	10.	As necessary, the Reliability Coordinator shall assist the Balancing Authorities in its Reliability Coordinator Area in arranging for assistance from neighboring Reliability Coordinator Areas or Balancing Authorities.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	11.	The Reliability Coordinator shall identify sources of large Area Control Errors that may be contributing to Frequency Error, Time Error, or Inadvertent Interchange and shall discuss corrective actions with the appropriate Balancing Authority. The Reliability Coordinator shall direct its Balancing Authority to comply with CPS and DCS.		X																	Main Transmission System	NPCC RRP	RC
IRO-005-1	12.	Whenever a Special Protection System that may have an inter-Balancing Authority, or inter-Transmission Operator impact (e.g., could potentially affect transmission flows resulting in a SOL or IROL violation) is armed, the Reliability Coordinators shall be aware of the impact of the operation of that Special Protection System on inter-area flows. The Transmission Operator shall immediately inform the Reliability Coordinator of the status of the Special Protection System including any degradation or potential failure to operate as expected.		X	X																Main Transmission System	NPCC RRP	RC, TOP
IRO-005-1	13.	Each Reliability Coordinator shall ensure that all Transmission Operators, Balancing Authorities, Generator Operators, Transmission Service Providers, Load-Serving Entities, and Purchasing-Selling Entities operate to prevent the likelihood that a disturbance, action, or nonaction in its Reliability Coordinator Area will result in a SOL or IROL violation in another area of the Interconnection. In instances where there is a difference in derived limits, the Reliability Coordinator and its Transmission Operators, Balancing Authorities, Generator Operators, Transmission Service Providers, Load-Serving Entities, and Purchasing-Selling Entities shall always operate the Bulk Electric System to the most limiting parameter.		X	X	X							X				X		X		Main Transmission System	NPCC RRP	BA, RC, TOP GOP-1, GOP-2, GOP-3 LSE-1 PSE

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
IRO-005-1	14.	Each Reliability Coordinator shall make known to Transmission Service Providers within its Reliability Coordinator Area, SOLs or IROLs within its wide-area view. The Transmission Service Providers shall respect these SOLs or IROLs in accordance with filed tariffs and regional Total Transfer Calculation and Available Transfer Calculation processes.		X																		Main Transmission System	NPCC RRP	RC TSP-1, TSP-2, TSP-3
IRO-005-1	15.	Each Reliability Coordinator who foresees a transmission problem (such as an SOL or IROL violation, loss of reactive reserves, etc.) within its Reliability Coordinator Area shall issue an alert to all impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area without delay. The receiving Reliability Coordinator shall disseminate this information to its impacted Transmission Operators and Balancing Authorities. The Reliability Coordinator shall notify all impacted Transmission Operators, Balancing Authorities, when the transmission problem has been mitigated.		X																		Main Transmission System	NPCC RRP	RC
IRO-005-1	16.	Each Reliability Coordinator shall confirm reliability assessment results and determine the effects within its own and adjacent Reliability Coordinator Areas. The Reliability Coordinator shall discuss options to mitigate potential or actual SOL or IROL violations and take actions as necessary to always act in the best interests of the Interconnection at all times.		X																		Main Transmission System	NPCC RRP	RC
IRO-005-1	17.	When an IROL or SOL is exceeded, the Reliability Coordinator shall evaluate the local and wide-area impacts, both real-time and post-contingency, and determine if the actions being taken are appropriate and sufficient to return the system to within IROL in thirty minutes. If the actions being taken are not appropriate or sufficient, the Reliability Coordinator shall direct the Transmission Operator, Balancing Authority, Generator Operator, or Load-Serving Entity to return the system to within IROL or SOL.		X																		Main Transmission System	NPCC RRP	RC
IRO-006-3	0.	Reliability Coordination — Transmission Loading Relief		X	X	X																Main Transmission System		Adopted by NERC: 2006-08-02
IRO-006-3	01.	A Reliability Coordinator shall take appropriate actions in accordance with established policies, procedures, authority, and expectations to relieve transmission loading.		X																		Main Transmission System	NPCC RRP	RC
IRO-006-3	02.	A Reliability Coordinator experiencing a potential or actual SOL or IROL violation within its Reliability Coordinator Area shall, at its discretion, select from either a "local" (Regional, Interregional, or subregional) transmission loading relief procedure or an Interconnection-wide procedure.		X																		Main Transmission System	NPCC RRP	RC
IRO-006-3	02.1	The Interconnection-wide Transmission Loading Relief (TLR) procedure for use in the Eastern Interconnection is provided in Attachment 1-IRO-006-0.		X																		Main Transmission System	NPCC RRP	RC
IRO-006-3	02.2	The equivalent Interconnection-wide transmission loading relief procedure for use in the Western Interconnection is the "WSCC Unscheduled Flow Mitigation Plan," provided at: http://www.wecc.biz/documents/library/UFAS/UFAS_mitigation_plan_rev_2001-clean_8-8-03.pdf .		X																		Main Transmission System	NPCC RRP	RC
IRO-006-3	02.3	The Interconnection-wide transmission loading relief procedure for use in ERCOT is provided as Section 7 of the ERCOT Protocols, posted at: http://www.ercot.com/tac/retailsoadhoccommittee/protocols/keydocs/draftercotprotocols.htm .		X																		Main Transmission System	NPCC RRP	RC
IRO-006-3	03.	The Reliability Coordinator may use local transmission loading relief or congestion management procedures, provided the Transmission Operator experiencing the potential or actual SOL or IROL violation is a party to those procedures.		X	X																	Main Transmission System	NPCC C-20	RC, TOP
IRO-006-3	04.	A Reliability Coordinator may implement a local transmission loading relief or congestion management procedure simultaneously with an Interconnection-wide procedure. However, the Reliability Coordinator shall follow the curtailments as directed by the Interconnection-wide procedure. A Reliability Coordinator desiring to use a local procedure as a substitute for curtailments as directed by the Interconnection-wide procedure shall have such use approved by the NERC Operating Committee.		X																		Main Transmission System	NPCC C-20	RC

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
IRO-006-3	05.	When implemented, all Reliability Coordinators shall comply with the provisions of the Interconnection-wide procedure including, for example, action by Reliability Coordinators in other Interconnections to curtail an Interchange Transaction that crosses an Interconnection boundary.		X																		Main Transmission System		RC
IRO-006-3	06.	During the implementation of relief procedures, and up to the point that emergency action is necessary, Reliability Coordinators and Balancing Authorities shall comply with interchange scheduling standards INT-001 through INT-004.		X		X																Main Transmission System		BA, RC
IRO-014-1	0.	Procedures, Processes, or Plans to Support Coordination Between Reliability Coordinators		X																		Main Transmission System		Adopted by NERC: 2006-02-07
IRO-014-1	01.	The Reliability Coordinator shall have Operating Procedures, Processes, or Plans in place for activities that require notification, exchange of information or coordination of actions with one or more other Reliability Coordinators to support Interconnection reliability. These Operating Procedures, Processes, or Plans shall address Scenarios that affect other Reliability Coordinator Areas as well as those developed in coordination with other Reliability Coordinators.		X																		Main Transmission System		RC
IRO-014-1	01.1	These Operating Procedures, Processes, or Plans shall collectively address, as a minimum, the following:		X																		Main Transmission System		RC
IRO-014-1	01.1.1	Communications and notifications, including the conditions ¹ under which one Reliability Coordinator notifies other Reliability Coordinators; the process to follow in making those notifications; and the data and information to be exchanged with other Reliability Coordinators. <small>1. Examples of conditions when one Reliability Coordinator may need to notify another Reliability Coordinator may include (but aren't limited to) sabotage events, Interconnection Reliability Operating Limit violations, voltage reductions, insufficient resources, arming of special protection systems, etc.</small>		X																		Main Transmission System		RC
IRO-014-1	01.1.2	Energy and capacity shortages.		X																		Main Transmission System		RC
IRO-014-1	01.1.3	Planned or unplanned outage information.		X																		Main Transmission System		RC
IRO-014-1	01.1.4	Voltage control, including the coordination of reactive resources for voltage control.		X																		Main Transmission System		RC
IRO-014-1	01.1.5	Coordination of information exchange to support reliability assessments.		X																		Main Transmission System		RC
IRO-014-1	01.1.6	Authority to act to prevent and mitigate instances of causing Adverse Reliability Impacts to other Reliability Coordinator Areas		X																		Main Transmission System		RC
IRO-014-1	02.	Each Reliability Coordinator's Operating Procedure, Process, or Plan that requires one or more other Reliability Coordinators to take action (e.g., make notifications, exchange information, or coordinate actions) shall be:		X																		Main Transmission System		RC
IRO-014-1	02.1	Agreed to by all the Reliability Coordinators required to take the indicated action(s).		X																		Main Transmission System		RC
IRO-014-1	02.2	Distributed to all Reliability Coordinators that are required to take the indicated action(s).		X																		Main Transmission System		RC
IRO-014-1	03.	A Reliability Coordinator's Operating Procedures, Processes, or Plans developed to support a Reliability Coordinator-to-Reliability Coordinator Operating Procedure, Process, or Plan shall include:		X																		Main Transmission System		RC
IRO-014-1	03.1	A reference to the associated Reliability Coordinator-to-Reliability Coordinator Operating Procedure, Process, or Plan.		X																		Main Transmission System		RC
IRO-014-1	03.2	The agreed-upon actions from the associated Reliability Coordinator-to-Reliability Coordinator Operating Procedure, Process, or Plan.		X																		Main Transmission System		RC
IRO-014-1	04.	Each of the Operating Procedures, Processes, and Plans addressed in Reliability Standard IRO-014 Requirement 1 and Requirement 3 shall:		X																		Main Transmission System		RC
IRO-014-1	04.1	Include version control number or date.		X																		Main Transmission System		RC
IRO-014-1	04.2	Include a distribution list.		X																		Main Transmission System		RC
IRO-014-1	04.3	Be reviewed, at least once every three years, and updated if needed.		X																		Main Transmission System		RC
IRO-015-1	0.	Notifications and Information Exchange Between Reliability Coordinators		X																		Main Transmission System		Adopted by NERC: 2006-02-07

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
IRO-015-1	01.	The Reliability Coordinator shall follow its Operating Procedures, Processes, or Plans for making notifications and exchanging reliability-related information with other Reliability Coordinators.		X																	Main Transmission System		RC
IRO-015-1	01.1	The Reliability Coordinator shall make notifications to other Reliability Coordinators of conditions in its Reliability Coordinator Area that may impact other Reliability Coordinator Areas.		X																	Main Transmission System		RC
IRO-015-1	02.	The Reliability Coordinator shall participate in agreed upon conference calls and other communication forums with adjacent Reliability Coordinators.		X																	Main Transmission System		RC
IRO-015-1	02.1	The frequency of these conference calls shall be agreed upon by all involved Reliability Coordinators and shall be at least weekly.		X																	Main Transmission System		RC
IRO-015-1	03.	The Reliability Coordinator shall provide reliability-related information as requested by other Reliability Coordinators.		X																	Main Transmission System		RC
IRO-016-1	0.	Coordination of Real-time Activities Between Reliability Coordinators		X																	Main Transmission System		Adopted by NERC: 2006-02-07
IRO-016-1	01.	The Reliability Coordinator that identifies a potential, expected, or actual problem that requires the actions of one or more other Reliability Coordinators shall contact the other Reliability Coordinator(s) to confirm that there is a problem and then discuss options and decide upon a solution to prevent or resolve the identified problem.		X																	Main Transmission System		RC
IRO-016-1	01.1	If the involved Reliability Coordinators agree on the problem and the actions to take to prevent or mitigate the system condition, each involved Reliability Coordinator shall implement the agreed-upon solution, and notify the involved Reliability Coordinators of the action(s) taken.		X																	Main Transmission System		RC
IRO-016-1	01.2	If the involved Reliability Coordinators cannot agree on the problem(s) each Reliability Coordinator shall re-evaluate the causes of the disagreement (bad data, status, study results, tools, etc.).		X																	Main Transmission System		RC
IRO-016-1	01.2.1	If time permits, this re-evaluation shall be done before taking corrective actions.		X																	Main Transmission System		RC
IRO-016-1	01.2.2	If time does not permit, then each Reliability Coordinator shall operate as though the problem(s) exist(s) until the conflicting system status is resolved.		X																	Main Transmission System		RC
IRO-016-1	01.3	If the involved Reliability Coordinators cannot agree on the solution, the more conservative solution shall be implemented.		X																	Main Transmission System		RC
IRO-016-1	02.	The Reliability Coordinator shall document (via operator logs or other data sources) its actions taken for either the event or for the disagreement on the problem(s) or for both.		X																	Main Transmission System		RC
MOD-006-0	0.	Procedure for the Use of Capacity Benefit Margin Values																			Interconnection's paths of Main Transmission System		Adopted by NERC: 2005-02-08
MOD-006-0	01.	Each Transmission Service Provider shall document its procedure on the use of Capacity Benefit Margin (CBM) (scheduling of energy against a CBM preservation). The procedure shall include the following three components:																			Interconnection's paths of Main Transmission System	NPCC CO-13 "Regional Methodology & Guidelines For Forecasting TTC & ATC" (RMGF T&A)	TSP-1, TSP-2
MOD-006-0	01.1	Require that CBM be used only after the following steps have been taken (as time permits): all non-firm sales have been terminated, Direct-Control Load Management has been implemented, and customer interruptible demands have been interrupted. CBM may be used to reestablish Operating Reserves.																			Interconnection's paths of Main Transmission System	NPCC RMGF T&A	TSP-1, TSP-2
MOD-006-0	01.2	Require that CBM shall only be used if the Load-Serving Entity calling for its use is experiencing a generation deficiency and its Transmission Service Provider is also experiencing Transmission Constraints relative to imports of energy on its transmission system.																			Interconnection's paths of Main Transmission System	NPCC RMGF T&A	TSP-1, TSP-2
MOD-006-0	01.3	Describe the conditions under which CBM may be available as Non-Firm Transmission Service.																			Interconnection's paths of Main Transmission System	NPCC RMGF T&A	TSP-1, TSP-2

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
MOD-006-0	02.	Each Transmission Service Provider shall make its CBM use procedure available on a web site accessible by the Regional Reliability Organizations, NERC, and transmission users.																				Interconnection's paths of Main Transmission System	NPCC RMGF T&A NPCC Web Site	TSP-1, TSP-2
MOD-007-0	0.	Documentation of the Use of Capacity Benefit Margin																				Interconnection's paths of Main Transmission System		Adopted by NERC: 2005-02-08
MOD-007-0	01.	Each Transmission Service Provider that uses CBM shall report (to the Regional Reliability Organization, NERC and the transmission users) the use of CBM by the Load-Serving Entities' Loads on its system, except for CBM sales as Non-Firm Transmission Service. (This use of CBM shall be consistent with the Transmission Service Provider's procedure for use of CBM.)																				Interconnection's paths of Main Transmission System		TSP-1, TSP-2
MOD-007-0	02.	The Transmission Service Provider shall post the following three items within 15 calendar days after the use of CBM for an Energy Emergency. This posting shall be on a web site accessible by the Regional Reliability Organizations, NERC, and transmission users.																				Interconnection's paths of Main Transmission System		TSP-1, TSP-2
MOD-007-0	02.1	Circumstances.																				Interconnection's paths of Main Transmission System		TSP-1, TSP-2
MOD-007-0	02.2	Duration.																				Interconnection's paths of Main Transmission System		TSP-1, TSP-2
MOD-007-0	02.3	Amount of CBM used.																				Interconnection's paths of Main Transmission System		TSP-1, TSP-2
MOD-010-0	0.	Steady-State Data for Modeling and Simulation of the Interconnected Transmission System								X	X					X	X					Main Transmission System		Adopted by NERC: 2005-02-08
MOD-010-0	01.	The Transmission Owners, Transmission Planners, Generator Owners, and Resource Planners (specified in the data requirements and reporting procedures of MOD-011-0_R1) shall provide appropriate equipment characteristics, system data, and existing and future Interchange Schedules in compliance with its respective Interconnection Regional steady-state modeling and simulation data requirements and reporting procedures as defined in Reliability Standard MOD-011-0_R1.								X	X					X	X					Main Transmission System	NPCC C-29	GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4 TP RP
MOD-010-0	02.	The Transmission Owners, Transmission Planners, Generator Owners, and Resource Planners (specified in the data requirements and reporting procedures of MOD-011-0_R1) shall provide this steady-state modeling and simulation data to the Regional Reliability Organizations, NERC, and those entities specified within Reliability Standard MOD-011-0_R1. If no schedule exists, then these entities shall provide the data on request (30 calendar days).								X	X					X	X					Main Transmission System	NPCC C-29	GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4 TP RP
MOD-012-0	0.	Dynamics Data for Modeling and Simulation of the Interconnected Transmission System								X	X					X	X					Main Transmission System		Adopted by NERC: 2005-02-08
MOD-012-0	01.	The Transmission Owners, Transmission Planners, Generator Owners, and Resource Planners (specified in the data requirements and reporting procedures of MOD-013-0_R1) shall provide appropriate equipment characteristics and system data in compliance with the respective Interconnection-wide Regional dynamics system modeling and simulation data requirements and reporting procedures as defined in Reliability Standard MOD-013-0_R1.								X	X					X	X					Main Transmission System	NPCC C-29 NPCC SS34 Data	GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4 TP RP
MOD-012-0	02.	The Transmission Owners, Transmission Planners, Generator Owners, and Resource Planners (specified in the data requirements and reporting procedures of MOD-013-0_R1) shall provide dynamics system modeling and simulation data to its Regional Reliability Organization(s), NERC, and those entities specified within the applicable reporting procedures identified in Reliability Standard MOD-013-0_R1. If no schedule exists, then these entities shall provide data on request (30 calendar days).								X	X					X	X					Main Transmission System	NPCC C-29 NPCC SS34 Data	GO-1, GO-2, GO-3, GO-4 TO-1, TO-2, TO-3, TO-4 TP RP
MOD-016-1	0.	Documentation of Data Reporting Requirements for Actual and Forecast Demands, Net Energy for Load, and Controllable Demand-Side Management	X																			Québec Interconnection		Adopted by NERC: 2006-05-02

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
MOD-016-1	01.	The Planning Authority and Regional Reliability Organization shall have documentation identifying the scope and details of the actual and forecast (a) Demand data, (b) Net Energy for Load data, and (c) controllable DSM data to be reported for system modeling and reliability analyses.	X																			Québec Interconnection		PA
MOD-016-1	01.1	The aggregated and dispersed data submittal requirements shall ensure that consistent data is supplied for Reliability Standards TPL-005, TPL-006, MOD-010, MOD-011, MOD-012, MOD-013, MOD-014, MOD-015, MOD-016, MOD-017, MOD-018, MOD-019, MOD-020, and MOD-021. The data submittal requirements shall stipulate that each Load-Serving Entity count its customer Demand once and only once, on an aggregated and dispersed basis, in developing its actual and forecast customer Demand values.	X																			Québec Interconnection		PA
MOD-016-1	02.	The Regional Reliability Organization shall distribute its documentation required in Requirement 1 and any changes to that documentation, to all Planning Authorities that work within its Region. The Regional Reliability Organization shall make this distribution within 30 calendar days of approval. The Planning Authority shall distribute its documentation required in R1 for reporting customer data and any changes to that documentation, to its Transmission Planners and Load-Serving Entities that work within its Planning Authority Area. The Planning Authority shall make this distribution within 30 calendar days of approval.	X																			Québec Interconnection		PA
MOD-017-0	0.	Aggregated Actual and Forecast Demands and Net Energy for Load										X				X	X					Québec Interconnection		Adopted by NERC: 2005-02-08
MOD-017-0	01.	The Load-Serving Entity, Planning Authority and Resource Planner shall each provide the following information annually on an aggregated Regional, subregional, Power Pool, individual system, or Load-Serving Entity basis to NERC, the Regional Reliability Organizations, and any other entities specified by the documentation in Standard MOD-016-0_R1.										X				X	X					Québec Interconnection		LSE-1 PA RP
MOD-017-0	01.1	Integrated hourly demands in megawatts (MW) for the prior year.										X				X	X					Québec Interconnection		LSE-1 PA RP
MOD-017-0	01.2	Monthly and annual peak hour actual demands in MW and Net Energy for Load in gigawatthours (GWh) for the prior year.										X				X	X					Québec Interconnection		LSE-1 PA RP
MOD-017-0	01.3	Monthly peak hour forecast demands in MW and Net Energy for Load in GWh for the next two years.										X				X	X					Québec Interconnection		LSE-1 PA RP
MOD-017-0	01.4	Annual Peak hour forecast demands (summer and winter) in MW and annual Net Energy for load in GWh for at least five years and up to ten years into the future, as requested.										X				X	X					Québec Interconnection		LSE-1 PA RP
MOD-018-0	0.	Treatment of Non-member Demand Data and How Uncertainties are Addressed in the Forecasts of Demand and Net Energy for Load										X	X			X	X					Québec Interconnection		Adopted by NERC: 2005-02-08
MOD-018-0	01.	The Load-Serving Entity, Planning Authority, Transmission Planner and Resource Planner's report of actual and forecast demand data (reported on either an aggregated or dispersed basis) shall:										X	X			X	X					Québec Interconnection		LSE-1 PA RP TP
MOD-018-0	01.1	Indicate whether the demand data of nonmember entities within an area or Regional Reliability Organization are included, and										X	X			X	X					Québec Interconnection		LSE-1 PA RP TP
MOD-018-0	01.2	Address assumptions, methods, and the manner in which uncertainties are treated in the forecasts of aggregated peak demands and Net Energy for Load.										X	X			X	X					Québec Interconnection		LSE-1 PA RP TP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities			
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC		
MOD-018-0	01.3	Items (MOD-018-0_R1.1) and (MOD-018-0_R1.2) shall be addressed as described in the reporting procedures developed for Standard MOD-016-0_R1.									X		X										Québec Interconnection		LSE-1 PA RP TP
MOD-018-0	02.	The Load-Serving Entity, Planning Authority, Transmission Planner and Resource Planner shall each report data associated with Reliability Standard MOD-018-0_R1 to NERC, the Regional Reliability Organization, Load-Serving Entity, Planning Authority, and Resource Planner on request (within 30 calendar days).									X		X										Québec Interconnection		LSE-1 PA RP TP
MOD-019-0	0.	Reporting of Interruptible Demands and Direct Control Load Management									X		X										Interruptible loads		Adopted by NERC: 2005-02-08
MOD-019-0	01.	The Load-Serving Entity, Planning Authority, Transmission Planner, and Resource Planner shall each provide annually its forecasts of interruptible demands and Direct Control Load Management (DCLM) data for at least five years and up to ten years into the future, as requested, for summer and winter peak system conditions to NERC, the Regional Reliability Organizations, and other entities (Load-Serving Entities, Planning Authorities, and Resource Planners) as specified by the documentation in Reliability Standard MOD-016-0_R1.									X		X										Shedable loads		LSE-1 PA RP TP
MOD-020-0	0.	Providing Interruptible Demands and Direct Control Load Management Data to System Operators and Reliability Coordinators									X												Interruptible loads		Adopted by NERC: 2005-02-08
MOD-020-0	01.	The Load-Serving Entity, Transmission Planner, and Resource Planner shall each make known its amount of interruptible demands and Direct Control Load Management (DCLM) to Transmission Operators, Balancing Authorities, and Reliability Coordinators on request within 30 calendar days.									X												Interruptible loads		LSE-1 RP TP
MOD-021-0	0.	Accounting Methodology for Effects of Controllable DSM in Forecasts									X												Québec Interconnection		Adopted by NERC: 2005-02-08
MOD-021-0	01.	The Load-Serving Entity Transmission Planner and Resource Planner's forecasts shall each clearly document how the Demand and energy effects of DSM programs (such as conservation, time-of-use rates, interruptible Demands, and Direct Control Load Management) are addressed.									X												Québec Interconnection		LSE-1 RP TP
MOD-021-0	02.	The Load-Serving Entity, Transmission Planner and Resource Planner shall each include information detailing how Demand-Side Management measures are addressed in the forecasts of its Peak Demand and annual Net Energy for Load in the data reporting procedures of Standard MOD-016-0_R1.									X												Québec Interconnection		LSE-1 RP TP
MOD-021-0	03.	The Load-Serving Entity, Transmission Planner and Resource Planner shall each make documentation on the treatment of its DSM programs available to NERC on request (within 30 calendar days).									X												Québec Interconnection		LSE-1 RP TP
PER-001-0	0.	Operating Personnel Responsibility and Authority			X	X																	Applicable only to TOP and BA		Adopted by NERC: 2005-02-08
PER-001-0	01.	Each Transmission Operator and Balancing Authority shall provide operating personnel with the responsibility and authority to implement real-time actions to ensure the stable and reliable operation of the Bulk Electric System.			X	X																	Applicable only to TOP and BA	NPCC A-03	BA, TOP
PER-002-0	0.	Operating Personnel Training			X	X																	Applicable only to TOP and BA		Adopted by NERC: 2005-02-08
PER-002-0	01.	Each Transmission Operator and Balancing Authority shall be staffed with adequately trained operating personnel.			X	X																	Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	02.	Each Transmission Operator and Balancing Authority shall have a training program for all operating personnel that are in:			X	X																	Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	02.1	Positions that have the primary responsibility, either directly or through communications with others, for the real-time operation of the interconnected Bulk Electric System.			X	X																	Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	02.2	Positions directly responsible for complying with NERC Standards.			X	X																	Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	03.	For personnel identified in Requirement R2, the Transmission Operator and Balancing Authority shall provide a training program meeting the following Criteria:			X	X																	Applicable only to TOP and BA	NPCC RRP	BA, TOP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
PER-002-0	03.1	A set of training program objectives must be defined, based on NERC and Regional Reliability Organization Standards, entity operating procedures, and applicable regulatory requirements. These objectives shall reference the knowledge and competencies needed to apply those Standards, procedures, and requirements to normal, emergency, and restoration conditions for the TOP and BA operating positions.			X	X															Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	03.2	The training program must include a plan for the initial and continuing training of Transmission Operator and Balancing Authority operating personnel. That plan shall address knowledge and competencies required for reliable system operations.			X	X															Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	03.3	The training program must include training time for all Transmission Operator and Balancing Authority operating personnel to ensure their operating proficiency.			X	X															Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	03.4	Training staff must be identified, and the staff must be competent in both knowledge of system operations and instructional capabilities.			X	X															Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-002-0	04.	For personnel identified in Requirement R2, each Transmission Operator and Balancing Authority shall provide its operating personnel at least five days per year of training and drills using realistic simulations of system emergencies, in addition to other training required to maintain qualified operating personnel.			X	X															Applicable only to TOP and BA	NPCC RRP	BA, TOP
PER-003-0	0.	Operating Personnel Credentials		X	X	X															Applicable only to BA, RC et TOP (Main Transmission System)		Adopted by NERC: 2005-02-08
PER-003-0	01.	Each Transmission Operator, Balancing Authority, and Reliability Coordinator shall staff all operating positions that meet both of the following Criteria with personnel that are NERC certified for the applicable functions:		X	X	X															Applicable only to BA, RC et TOP (Main Transmission System)	NPCC RRP	BA, RC, TOP
PER-003-0	01.1	Positions that have the primary responsibility, either directly or through communications with others, for the real-time operation of the interconnected Bulk Electric System.		X	X	X															Applicable only to BA, RC et TOP (Main Transmission System)	NPCC RRP	BA, RC, TOP
PER-003-0	01.2	Positions directly responsible for complying with NERC Standards.		X	X	X															Applicable only to BA, RC et TOP (Main Transmission System)	NPCC RRP	BA, RC, TOP
PER-004-1	0.	Reliability Coordination – Staffing		X																	Applicable to RC only		Adopted by NERC: 2006-11-01
PER-004-1	01.	Each Reliability Coordinator shall be staffed with adequately trained and NERC-certified Reliability Coordinator operators, 24 hours per day, seven days per week.		X																	Applicable to RC only	NPCC RRP	RC
PER-004-1	02.	All Reliability Coordinator operating personnel shall each complete a minimum of five days per year of training and drills using realistic simulations of system emergencies, in addition to other training required to maintain qualified operating personnel.		X																	Applicable to RC only	NPCC RRP	RC
PER-004-1	03.	Reliability Coordinator operating personnel shall have a comprehensive understanding of the Reliability Coordinator Area and interactions with neighboring Reliability Coordinator Areas.		X																	Applicable to RC only	NPCC RRP	RC
PER-004-1	04.	Reliability Coordinator operating personnel shall have an extensive understanding of the Balancing Authorities, Transmission Operators, and Generation Operators within the Reliability Coordinator Area, including the operating staff, operating practices and procedures, restoration priorities and objectives, outage plans, equipment capabilities, and operational restrictions.		X																	Applicable to RC only	NPCC RRP	RC
PER-004-1	05.	Reliability Coordinator operating personnel shall place particular attention on SOLs and IROLs and inter-tie facility limits. The Reliability Coordinator shall ensure protocols are in place to allow Reliability Coordinator operating personnel to have the best available information at all times.		X																	Applicable to RC only	NPCC RRP	RC
PRC-001-1	0.	System Protection Coordination			X	X							X								Main Transmission System		Adopted by NERC: 2006-11-01
PRC-001-1	01.	Each Transmission Operator, Balancing Authority, and Generator Operator shall be familiar with the purpose and limitations of protection system schemes applied in its area.			X	X							X								Main Transmission System		BA, TOP GOP-1, GOP-2, GOP-3
PRC-001-1	02.	Each Generator Operator and Transmission Operator shall notify reliability entities of relay or equipment failures as follows:			X								X								Main Transmission System		TOP GOP-1, GOP-2, GOP-3

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
PRC-005-1	02.	Each Transmission Owner and any Distribution Provider that owns a transmission Protection System and each Generator Owner that owns a generation Protection System shall provide documentation of its Protection System maintenance and testing program and the implementation of that program to its Regional Reliability Organization on request (within 30 calendar days). The documentation of the program implementation shall include:								X												BULK Power System	NPCC A-08	TO-1
PRC-005-1	02.1	Evidence Protection System devices were maintained and tested within the defined intervals.								X												BULK Power System	NPCC A-08	TO-1
PRC-005-1	02.2	Date each Protection System device was last tested/maintained.								X												BULK Power System	NPCC A-08	TO-1
PRC-007-0	0.	Assuring Consistency of Entity Underfrequency Load Shedding Programs with RRO Underfrequency Load Shedding Program Requirements			X					X								X	X			Underfrequency load shedding facilities and systems		Adopted by NERC: 2005-02-08
PRC-007-0	01.	The Transmission Owner and Distribution Provider, with a UFLS program (as required by its Regional Reliability Organization) shall ensure that its UFLS program is consistent with its Regional Reliability Organization's UFLS program requirements.								X									X			Underfrequency load shedding facilities and systems	NPCC A-03	TO-1, TO-2
PRC-007-0	02.	The Transmission Owner, TOP, Distribution Provider, and LSE that owns or operates a UFLS program (as required by its RRO) shall provide, and annually update, its underfrequency data as necessary for its RRO to maintain and update a UFLS program database.			X					X								X	X			Underfrequency load shedding facilities and systems	NPCC B-07	TOP TO-1, TO-2
PRC-007-0	03.	The Transmission Owner and Distribution Provider that owns a UFLS program (as required by its Regional Reliability Organization) shall provide its documentation of that UFLS program to its Regional Reliability Organization on request (30 calendar days).								X									X			Underfrequency load shedding facilities and systems	NPCC A-08	TO-1, TO-2
PRC-008-0	0.	Implementation and Documentation of Underfrequency Load Shedding Equipment Maintenance Program								X									X			Underfrequency load shedding facilities and systems		Adopted by NERC: 2005-02-08
PRC-008-0	01.	The Transmission Owner and Distribution Provider with a UFLS program (as required by its Regional Reliability Organization) shall have a UFLS equipment maintenance and testing program in place. This UFLS equipment maintenance and testing program shall include UFLS equipment identification, the schedule for UFLS equipment testing, and the schedule for UFLS equipment maintenance.								X										X		Underfrequency load shedding facilities and systems	NPCC A-04	TO-1, TO-2
PRC-008-0	02.	The Transmission Owner and Distribution Provider with a UFLS program (as required by its Regional Reliability Organization) shall implement its UFLS equipment maintenance and testing program and shall provide UFLS maintenance and testing program results to its Regional Reliability Organization and NERC on request (within 30 calendar days).								X										X		Underfrequency load shedding facilities and systems	NPCC B-07	TO-1, TO-2
PRC-009-0	0.	Analysis and Documentation of Underfrequency Load Shedding Performance Following an Underfrequency Event			X					X								X	X			Underfrequency load shedding facilities and systems		Adopted by NERC: 2005-02-08
PRC-009-0	01.	The Transmission Owner, TOP, LSE and Distribution Provider that owns or operates a UFLS program (as required by its RRO) shall analyze and document its UFLS program performance in accordance with its RRO's UFLS program. The analysis shall address the performance of UFLS equipment and program effectiveness following system events resulting in system frequency excursions below the initializing set points of the UFLS program. The analysis shall include, but not be limited to:			X					X								X	X			Underfrequency load shedding facilities and systems	NPCC B-13	TOP TO-1, TO-2
PRC-009-0	01.1	A description of the event including initiating conditions.			X					X								X	X			Underfrequency load shedding facilities and systems	NPCC B-13	TOP TO-1, TO-2
PRC-009-0	01.2	A review of the UFLS set points and tripping times			X					X								X	X			Underfrequency load shedding facilities and systems		TOP TO-1, TO-2
PRC-009-0	01.3	Simulation of the event			X					X								X	X			Underfrequency load shedding facilities and systems		TOP TO-1, TO-2

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
PRC-009-0	01.4	A summary of the findings			X					X							X	X			Underfrequency load shedding facilities and systems	NPCC B-13	TOP TO-1, TO-2
PRC-009-0	02.	The Transmission Owner, Transmission Operator, Load-Serving Entity, and Distribution Provider that owns or operates a UFLS program (as required by its Regional Reliability Organization) shall provide documentation of the analysis of the UFLS program to its Regional Reliability Organization and NERC on request 90 calendar days after the system event.			X					X							X	X			Underfrequency load shedding facilities and systems		TOP TO-1, TO-2
PRC-010-0	0.	Assessment of the Design and Effectiveness of Undervoltage Load Shedding Program			X					X							X	X			Undervoltage load shedding facilities and systems		Adopted by NERC: 2005-02-08
PRC-010-0	01.	The Load-Serving Entity, Transmission Owner, Transmission Operator, and Distribution Provider that owns or operates a UVLS program shall periodically (at least every five years or as required by changes in system conditions) conduct and document an assessment of the effectiveness of the UVLS program. This assessment shall be conducted with the associated Transmission Planner(s) and Planning Authority(ies).			X					X							X	X			Undervoltage load shedding facilities and systems	NPCC B-04	TOP TO-1
PRC-010-0	01.1	This assessment shall include, but is not limited to:			X					X							X	X			Undervoltage load shedding facilities and systems	See below	TOP TO-1
PRC-010-0	01.1.1	Coordination of the UVLS programs with other protection and control systems in the Region and with other Regional Reliability Organizations, as appropriate.			X					X							X	X			Undervoltage load shedding facilities and systems	NPCC A-03	TOP TO-1
PRC-010-0	01.1.2	Simulations that demonstrate that the UVLS programs performance is consistent with Reliability Standards TPL-001-0, TPL-002-0, TPL-003-0 and TPL-004-0.			X					X							X	X			Undervoltage load shedding facilities and systems		TOP TO-1
PRC-010-0	01.1.3	A review of the voltage set points and timing.			X					X							X	X			Undervoltage load shedding facilities and systems		TOP TO-1
PRC-010-0	02.	The Load-Serving Entity, Transmission Owner, Transmission Operator, and Distribution Provider that owns or operates a UVLS program shall provide documentation of its current UVLS program assessment to its Regional Reliability Organization and NERC on request (30 calendar days).			X					X							X	X			Undervoltage load shedding facilities and systems		TOP TO-1
PRC-011-0	0.	Undervoltage Load Shedding System Maintenance and Testing								X								X			Undervoltage load shedding facilities and systems		Adopted by NERC: 2005-02-08
PRC-011-0	01.	The Transmission Owner and Distribution Provider that owns a UVLS system shall have a UVLS equipment maintenance and testing program in place. This program shall include:								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.1	The UVLS system identification which shall include but is not limited to:								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.1.1	Relays								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.1.2	Instrument transformers								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.1.3	Communications systems, where appropriate								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.1.4	Batteries								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.2	Documentation of maintenance and testing intervals and their basis.								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.3	Summary of testing procedure.								X								X			Undervoltage load shedding facilities and systems	NPCC A-04	TO-1
PRC-011-0	01.4	Schedule for system testing.								X								X			Undervoltage load shedding facilities and systems		TO-1
PRC-011-0	01.5	Schedule for system maintenance.								X								X			Undervoltage load shedding facilities and systems		TO-1
PRC-011-0	01.6	Date last tested/maintained								X								X			Undervoltage load shedding facilities and systems		TO-1
PRC-011-0	02.	The Transmission Owner, Generator Owner, and Distribution Provider that owns a transmission protection system shall provide documentation of its transmission protection system program and its implementation to the appropriate Regional Reliability Organization and NERC on request (within 30 calendar days).								X								X			Undervoltage load shedding facilities and systems	NPCC A-08	TO-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
PRC-015-0	0.	Special Protection System Data and Documentation							X													Special Protection Systems (SPS)		Adopted by NERC: 2005-02-08
PRC-015-0	01.	The Transmission Owner, Generator Owner, and Distribution Provider that owns an SPS shall maintain a list of and provide data for existing and proposed SPSs as specified in Reliability Standard PRC-013-0_R1.							X													Special Protection Systems (SPS)	NPCC A-11 NPCC A-02	TO-1, TO-2
PRC-015-0	02.	The Transmission Owner, Generator Owner, and Distribution Provider that owns an SPS shall have evidence it reviewed new or functionally modified SPSs in accordance with the Regional Reliability Organization's procedures as defined in Reliability Standard PRC-012-0_R1 prior to being placed in service.							X													Special Protection Systems (SPS)	NPCC C-16	TO-1, TO-2
PRC-015-0	03.	The Transmission Owner, Generator Owner, and Distribution Provider that owns an SPS shall provide documentation of SPS data and the results of Studies that show compliance of new or functionally modified SPSs with NERC Reliability Standards and Regional Reliability Organization Criteria to affected Regional Reliability Organizations and NERC on request (within 30 calendar days).							X													Special Protection Systems (SPS)		TO-1, TO-2
PRC-016-0	0.	Special Protection System Misoperations							X													Special Protection Systems (SPS)		Adopted by NERC: 2005-02-08
PRC-016-0	01.	The Transmission Owner, Generator Owner, and Distribution Provider that owns an SPS shall analyze its SPS operations and maintain a record of all misoperations in accordance with the Regional SPS review procedure specified in Reliability Standard PRC-012-0_R1.							X													Special Protection Systems (SPS)	NPCC B-21	TO-1, TO-2
PRC-016-0	02.	The Transmission Owner, Generator Owner, and Distribution Provider that owns an SPS shall take corrective actions to avoid future misoperations.							X													Special Protection Systems (SPS)	NPCC B-21 NPCC B-04	TO-1, TO-2
PRC-016-0	03.	The Transmission Owner, Generator Owner, and Distribution Provider that owns an SPS shall provide documentation of the misoperation analyses and the corrective action plans to its Regional Reliability Organization and NERC on request (within 90 calendar days).							X													Special Protection Systems (SPS)	NPCC B-21	TO-1, TO-2
PRC-017-0	0.	Special Protection System Maintenance and Testing							X													Special Protection Systems (SPS)		Adopted by NERC: 2005-02-08
PRC-017-0	01.	The Transmission Owner, Generator Owner, and Distribution Provider that owns an SPS shall have a system maintenance and testing program(s) in place. The program(s) shall include:							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.1	SPS identification shall include but is not limited to:							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.1.1	Relays							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.1.2	Instrument transformers							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.1.3	Communications systems, where appropriate							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.1.4	Batteries							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.2	Documentation of maintenance and testing intervals and their basis.							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.3	Summary of testing procedure.							X													Special Protection Systems (SPS)	NPCC A-04	TO-1, TO-2
PRC-017-0	01.4	Schedule for system testing.							X													Special Protection Systems (SPS)		TO-1, TO-2
PRC-017-0	01.5	Schedule for system maintenance.							X													Special Protection Systems (SPS)		TO-1, TO-2
PRC-017-0	01.6	Date last tested/maintained							X													Special Protection Systems (SPS)		TO-1, TO-2
PRC-017-0	02.	The Transmission Owner, Generator Owner, and Distribution Provider that owns a transmission protection system shall provide documentation of its transmission protection system program and its implementation to the appropriate Regional Reliability Organization and NERC on request (within 30 calendar days).							X													Special Protection Systems (SPS)	NPCC A-08	TO-1, TO-2
PRC-018-1	0.	Disturbance Monitoring Equipment Installation and Data Reporting							X													Specific Application - see Registry		Adopted by NERC: 2006-08-02

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities				
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC			
PRC-018-1	01.	Each Transmission Owner and Generator Owner required to install DMEs by its Regional Reliability Organization (reliability standard PRC-002 Requirements 1-3) shall have DMEs installed that meet the following requirements:								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	01.1	Internal Clocks in DME devices shall be synchronized to within 2 milliseconds or less of Universal Coordinated Time scale (UTC)								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	01.2	Recorded data from each Disturbance shall be retrievable for ten calendar days.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	02.	The Transmission Owner and Generator Owner shall each install DMEs in accordance with its Regional Reliability Organization's installation requirements (reliability standard PRC-002 Requirements 1 through 3).								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.	The Transmission Owner and Generator Owner shall each maintain, and report to its Regional Reliability Organization on request, the following data on the DMEs installed to meet that region's installation requirements (reliability standard PRC-002 Requirements 1.1, 2.1 and 3.1):								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.1	Type of DME (sequence of event recorder, fault recorder, or dynamic disturbance recorder).								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.2	Make and model of equipment.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.3	Installation location.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.4	Operational status.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.5	Date last tested.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.6	Monitored elements, such as transmission circuit, bus section, etc.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.7	Monitored devices, such as circuit breaker, disconnect status, alarms, etc.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	03.8	Monitored electrical quantities, such as voltage, current, etc.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	04.	The Transmission Owner and Generator Owner shall each provide Disturbance data (recorded by DMEs) in accordance with its Regional Reliability Organization's requirements (reliability standard PRC-002 Requirement 4).								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	05.	The Transmission Owner and Generator Owner shall each archive all data recorded by DMEs for Regional Reliability Organization-identified events for at least three years.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	06.	Each Transmission Owner and Generator Owner that is required by its Regional Reliability Organization to have DMEs shall have a maintenance and testing program for those DMEs that includes:								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	06.1	Maintenance and testing intervals and their basis.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-018-1	06.2	Summary of maintenance and testing procedures.								X														Specific Application - see Registry	NPCC A-15 NPCC B-26	GO-1, GO-2 TO-1, TO-2, TO-3, TO-4
PRC-021-1	0.	Under-Voltage Load Shedding Program Data								X														Undervoltage load shedding facilities and systems		Adopted by NERC: 2006-02-07
PRC-021-1	01.	Each Transmission Owner and Distribution Provider that owns a UVLS program to mitigate the risk of voltage collapse or voltage instability in the BES shall annually update its UVLS data to support the Regional UVLS program database. The following data shall be provided to the Regional Reliability Organization for each installed UVLS system:								X														Undervoltage load shedding facilities and systems		TO-1
PRC-021-1	01.1	Size and location of customer load, or percent of connected load, to be interrupted.								X														Undervoltage load shedding facilities and systems		TO-1
PRC-021-1	01.2	Corresponding voltage set points and overall scheme clearing times.								X														Undervoltage load shedding facilities and systems		TO-1
PRC-021-1	01.3	Time delay from initiation to trip signal.								X														Undervoltage load shedding facilities and systems		TO-1
PRC-021-1	01.4	Breaker operating times.								X														Undervoltage load shedding facilities and systems		TO-1

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
PRC-021-1	01.5	Any other schemes that are part of or impact the UVLS programs such as related generation protection, islanding schemes, automatic load restoration schemes, UFLS and Special Protection Systems.								X								X			Undervoltage load shedding facilities and systems		TO-1
PRC-021-1	02.	Each Transmission Owner and Distribution Provider that owns a UVLS program shall provide its UVLS program data to the Regional Reliability Organization within 30 calendar days of a request.								X								X			Undervoltage load shedding facilities and systems		TO-1
PRC-022-1	0.	Under-Voltage Load Shedding Program Performance							X								X	X			Undervoltage load shedding facilities and systems		Adopted by NERC: 2006-02-07
PRC-022-1	01.	Each Transmission Operator, Load-Serving Entity, and Distribution Provider that operates a UVLS program to mitigate the risk of voltage collapse or voltage instability in the BES shall analyze and document all UVLS operations and Misoperations. The analysis shall include:							X								X	X			Undervoltage load shedding facilities and systems		TO-1
PRC-022-1	01.1	A description of the event including initiating conditions.							X								X	X			Undervoltage load shedding facilities and systems		TO-1
PRC-022-1	01.2	A review of the UVLS set points and tripping times.							X								X	X			Undervoltage load shedding facilities and systems		TO-1
PRC-022-1	01.3	A simulation of the event, if deemed appropriate by the Regional Reliability Organization. For most events, analysis of sequence of events may be sufficient and dynamic simulations may not be needed.							X								X	X			Undervoltage load shedding facilities and systems		TO-1
PRC-022-1	01.4	A summary of the findings.							X								X	X			Undervoltage load shedding facilities and systems		TO-1
PRC-022-1	01.5	For any Misoperation, a Corrective Action Plan to avoid future Misoperations of a similar nature							X								X	X			Undervoltage load shedding facilities and systems		TO-1
PRC-022-1	02.	Each Transmission Operator, Load-Serving Entity, and Distribution Provider that operates a UVLS program shall provide documentation of its analysis of UVLS program performance to its Regional Reliability Organization within 90 calendar days of a request.							X								X	X			Undervoltage load shedding facilities and systems		TO-1
TOP-001-1	0.	Reliability Responsibility and Authorities			X	X							X				X	X			Main Transmission System		Adopted by NERC: 2006-11-01
TOP-001-1	01.	Each Transmission Operator shall have the responsibility and clear decision-making authority to take whatever actions are needed to ensure the reliability of its area and shall exercise specific authority to alleviate operating emergencies.			X																Main Transmission System	NPCC A-03	TOP
TOP-001-1	02.	Each TOP shall take immediate actions to alleviate operating emergencies including curtailing transmission service or energy schedules, operating equipment (e.g., generators, phase shifters, breakers), shedding firm load, etc.			X																Main Transmission System	NPCC A-03	TOP
TOP-001-1	03.	Each TOP, BA and GOP shall comply with reliability directives issued by the RC, and each BA and GOP shall comply with reliability directives issued by the TOP, unless such actions would violate safety, equipment, regulatory or statutory requirements. Under these circumstances the TOP, BA or GOP shall immediately inform the RC or TOP of the inability to perform the directive so that the RC or TOP can implement other remedial actions.			X	X							X								Main Transmission System	NPCC RRP	BA, TOP GOP-1, GOP-2, GOP-3
TOP-001-1	04.	Each Distribution Provider and Load Serving Entity shall comply with all reliability directives issued by the Transmission Operator, including shedding firm load, unless such actions would violate safety, equipment, regulatory or statutory requirements. Under these circumstances, the Distribution Provider or Load Serving Entity shall immediately inform the Transmission Operator of the inability to perform the directive so that the Transmission Operator can implement alternate remedial actions.															X	X			Main Transmission System	NPCC A-03	DP LSE-1, LSE-2
TOP-001-1	05.	Each Transmission Operator shall inform its Reliability Coordinator and any other potentially affected Transmission Operators of real time or anticipated emergency conditions, and take actions to avoid, when possible, or mitigate the emergency.			X																Main Transmission System	NPCC A-03	TOP
TOP-001-1	06.	Each Transmission Operator, Balancing Authority, and Generator Operator shall render all available emergency assistance to others as requested, provided that the requesting entity has implemented its comparable emergency procedures, unless such actions would violate safety, equipment, or regulatory or statutory requirements.			X	X							X								Main Transmission System	NPCC A-03	BA, TOP GOP-1, GOP-2, GOP-3

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
TOP-001-1	07.	Each Transmission Operator and Generator Operator shall not remove Bulk Electric System facilities from service if removing those facilities would burden neighboring systems unless:			X									X								Main Transmission System	NPCC RRP	TOP GOP-1, GOP-2, GOP-3
TOP-001-1	07.1	For a generator outage, the GOP shall notify and coordinate with the Transmission Operator. The TOP shall notify the Reliability Coordinator and other affected TOP, and coordinate the impact of removing the Bulk Electric System facility			X									X								Main Transmission System	NPCC RRP	TOP GOP-1, GOP-2, GOP-3
TOP-001-1	07.2	For a transmission facility, the Transmission Operator shall notify and coordinate with its Reliability Coordinator. The TOP shall notify other affected TOP, and coordinate the impact of removing the Bulk Electric System facility.			X																	Main Transmission System	NPCC RRP	TOP
TOP-001-1	07.3	When time does not permit such notifications and coordination, or when immediate action is required to prevent a hazard to the public, lengthy customer service interruption, or damage to facilities, the Generator Operator shall notify the Transmission Operator, and the Transmission Operator shall notify its Reliability Coordinator and adjacent Transmission Operators, at the earliest possible time.			X									X								Main Transmission System	NPCC RRP	TOP GOP-1, GOP-2, GOP-3
TOP-001-1	08.	During a system emergency, the Balancing Authority and Transmission Operator shall immediately take action to restore the Real and Reactive Power Balance. If the Balancing Authority or Transmission Operator is unable to restore Real and Reactive Power Balance it shall request emergency assistance from the Reliability Coordinator. If corrective action or emergency assistance is not adequate to mitigate the Real and Reactive Power Balance, then the Reliability Coordinator, Balancing Authority, and Transmission Operator shall implement firm load shedding.			X	X																Main Transmission System	NPCC A-03 NPCC RRP	BA, TOP
TOP-002-2	0.	Normal Operations Planning			X	X								X								Main Transmission System		Adopted by NERC: 2006-11-01
TOP-002-2	01.	Each Balancing Authority and Transmission Operator shall maintain a set of current plans that are designed to evaluate options and set procedures for reliable operation through a reasonable future time period. In addition, each Balancing Authority and Transmission Operator shall be responsible for using available personnel and system equipment to implement these plans to ensure that interconnected system reliability will be maintained.			X	X																Main Transmission System	NPCC A-02 NPCC B-04	BA, TOP
TOP-002-2	02.	Each Balancing Authority and Transmission Operator shall ensure its operating personnel participate in the system planning and design study processes, so that these studies contain the operating personnel perspective and system operating personnel are aware of the planning purpose.			X	X																Main Transmission System	NPCC A-02 NPCC B-04	BA, TOP
TOP-002-2	03.	Each Load Serving Entity and Generator Operator shall coordinate (where confidentiality agreements allow) its current-day, next-day, and seasonal operations with its Host Balancing Authority and Transmission Service Provider. Each Balancing Authority and Transmission Service Provider shall coordinate its current-day, next-day, and seasonal operations with its Transmission Operator.				X								X	X							Main Transmission System	NPCC A-02	BA GOP-1, GOP-2, GOP-3 LSE-1 TSP-1, TSP-2, TSP-3
TOP-002-2	04.	Each Balancing Authority and Transmission Operator shall coordinate (where confidentiality agreements allow) its current-day, next-day, and seasonal planning and operations with neighboring Balancing Authorities and Transmission Operators and with its Reliability Coordinator, so that normal Interconnection operation will proceed in an orderly and consistent manner.			X	X																Main Transmission System	NPCC RRP	BA, TOP
TOP-002-2	05.	Each Balancing Authority and Transmission Operator shall plan to meet scheduled system configuration, generation dispatch, interchange scheduling and demand patterns.			X	X																Main Transmission System	NPCC RRP	BA, TOP
TOP-002-2	06.	Each Balancing Authority and Transmission Operator shall plan to meet unscheduled changes in system configuration and generation dispatch (at a minimum N-1 Contingency planning) in accordance with NERC, Regional Reliability Organization, subregional, and local reliability requirements.			X	X																Main Transmission System	NPCC A-02	BA, TOP
TOP-002-2	07.	Each Balancing Authority shall plan to meet capacity and energy reserve requirements, including the deliverability/capability for any single Contingency.				X																Main Transmission System	NPCC A-02	BA
TOP-002-2	08.	Each Balancing Authority shall plan to meet voltage and/or reactive limits, including the deliverability/capability for any single contingency.				X																Main Transmission System	NPCC A-02	BA

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
TOP-002-2	09.	Each Balancing Authority shall plan to meet Interchange Schedules and ramps.				X															Main Transmission System	NPCC B-02	BA
TOP-002-2	10.	Each Balancing Authority and Transmission Operator shall plan to meet all System Operating Limits (SOLs) and Interconnection Reliability Operating Limits (IROLs).			X	X															Main Transmission System	NPCC RRP	BA, TOP
TOP-002-2	11.	The Transmission Operator shall perform seasonal, next-day, and current-day Bulk Electric System studies to determine SOLs. Neighboring Transmission Operators shall utilize identical SOLs for common facilities. The Transmission Operator shall update these Bulk Electric System studies as necessary to reflect current system conditions; and shall make the results of Bulk Electric System studies available to the Transmission Operators, Balancing Authorities (subject confidentiality requirements), and to its Reliability Coordinator.			X																Main Transmission System	NPCC A-02	TOP
TOP-002-2	12.	The Transmission Service Provider shall include known SOLs or IROLs within its area and neighboring areas in the determination of transfer capabilities, in accordance with filed tariffs and/or regional Total Transfer Capability and Available Transfer Capability calculation processes.																		X	Main Transmission System	NPCC CO-13 "Regional Methodology & Guidelines For Forecasting TTC & ATC" (RMGF T&A)	TSP-1, TSP-2, TSP-3
TOP-002-2	13.	At the request of the Balancing Authority or Transmission Operator, a Generator Operator shall perform generating real and reactive capability verification that shall include, among other variables, weather, ambient air and water conditions, and fuel quality and quantity, and provide the results to the Balancing Authority or Transmission Operator operating personnel as requested.																		X	Main Transmission System	CME IQ-P-001 NPCC A-13 NPCC B-09	GOP-1, GOP-2
TOP-002-2	14.	Generator Operators shall, without any intentional time delay, notify their Balancing Authority and Transmission Operator of changes in capabilities and characteristics including but not limited to:																		X	Main Transmission System	NPCC RRP	GOP-1, GOP-2, GOP-3
TOP-002-2	14.1	Changes in real and reactive output capabilities. (Retired August 1, 2007)																		X	Main Transmission System	NPCC RRP	GOP-1, GOP-2, GOP-3
TOP-002-2	14.2	Changes in real output capabilities. (Effective August 1, 2007).																		X	Main Transmission System	NPCC RRP	GOP-1, GOP-2, GOP-3
TOP-002-2	14.3	Automatic Voltage Regulator status and mode setting. (Retired August 1, 2007)																		X	Main Transmission System	NPCC RRP	GOP-1, GOP-2, GOP-3
TOP-002-2	15.	Generation Operators shall, at the request of the Balancing Authority or Transmission Operator, provide a forecast of expected real power output to assist in operations planning (e.g., a seven-day forecast of real output).																		X	Main Transmission System	NPCC C-13	GOP-1, GOP-2
TOP-002-2	16.	Subject to standards of conduct and confidentiality agreements, Transmission Operators shall, without any intentional time delay, notify their Reliability Coordinator and Balancing Authority of changes in capabilities and characteristics including but not limited to:			X																Main Transmission System	NPCC C-13	TOP
TOP-002-2	16.1	Changes in transmission facility status.			X																Main Transmission System	NPCC C-13	TOP
TOP-002-2	16.2	Changes in transmission facility rating.			X																Main Transmission System		TOP
TOP-002-2	17.	Balancing Authorities and Transmission Operators shall, without any intentional time delay, communicate the information described in the requirements R1 to R16 above to their Reliability Coordinator.			X	X															Main Transmission System		BA, TOP
TOP-002-2	18.	Neighboring Balancing Authorities, Transmission Operators, Generator Operators, Transmission Service Providers and Load Serving Entities shall use uniform line identifiers when referring to transmission facilities of an interconnected network.			X	X														X	Main Transmission System		BA, TOP GOP-1, GOP-2, GOP-3 LSE-1, LSE-2 TSP-1, TSP-2, TSP-3
TOP-002-2	19.	Each Balancing Authority and Transmission Operator shall maintain accurate computer models utilized for analyzing and planning system operations.			X	X															Main Transmission System	NPCC A-02	BA, TOP
TOP-003-0	0.	Planned Outage Coordination		X	X	X														X	Main Transmission System		Adopted by NERC: 2005-02-08
TOP-003-0	01.	Generator Operators and Transmission Operators shall provide planned outage information :			X															X	Main Transmission System	NPCC RRP	TOP GOP-1, GOP-2
TOP-003-0	01.1	Each Generator Operator shall provide outage information daily to its TOP for scheduled generator outages planned for the next day (any foreseen outage of a generator greater than 50 MW). The TOP shall establish the outage reporting requirements.																		X	Main Transmission System	NPCC RRP	GOP-1, GOP-2

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
TOP-003-0	01.2	Each TOP shall provide outage information daily to its RC, and to affected BA and TOP for scheduled generator and BES outages planned for the next day (any foreseen outage of a transmission line or transformer greater than 100 kV or generator greater than 50 MW) that may collectively cause or contribute to an SOL or IROL violation or a regional operating area limitation. The RC shall establish the outage reporting requirements.		X	X																Main Transmission System	NPCC RRP	RC, TOP
TOP-003-0	01.3	Such information shall be available by 1200 Central Standard Time for the Eastern Interconnection and 1200 Pacific Standard Time for the Western Interconnection.		X	X																Main Transmission System	NPCC RRP	RC, TOP
TOP-003-0	02.	Each Transmission Operator, Balancing Authority, and Generator Operator shall plan and coordinate scheduled outages of system voltage regulating equipment, such as automatic voltage regulators on generators, supplementary excitation control, synchronous condensers, shunt and series capacitors, reactors, etc., among affected Balancing Authorities and Transmission Operators as required.			X	X							X								Main Transmission System	NPCC RRP	BA, TOP GOP-1, GOP-2
TOP-003-0	03.	Each TOP, BA, and GOP shall plan and coordinate scheduled outages of telemetering and control equipment and associated communication channels between the affected areas.			X	X							X								Main Transmission System		BA, TOP GOP-1, GOP-2
TOP-003-0	04.	Each Reliability Coordinator shall resolve any scheduling of potential reliability conflicts.		X																	Main Transmission System	NPCC RRP	RC
TOP-004-1	0.	Transmission Operations			X																Main Transmission System		Adopted by NERC: 2006-11-01
TOP-004-1	01.	Each Transmission Operator shall operate within the Interconnection Reliability Operating Limits (IROLs) and System Operating Limits (SOLs).			X																Main Transmission System	NPCC RRP	TOP
TOP-004-1	02.	Each Transmission Operator shall operate so that instability, uncontrolled separation, or cascading outages will not occur as a result of the most severe single contingency.			X																Main Transmission System	NPCC A-02	TOP
TOP-004-1	03.	Each Transmission Operator shall, when practical, operate to protect against instability, uncontrolled separation, or cascading outages resulting from multiple outages, as specified by Regional Reliability Organization policy.			X																Main Transmission System	NPCC A-02	TOP
TOP-004-1	04.	If a Transmission Operator enters an unknown operating state (i.e. any state for which valid operating limits have not been determined), it will be considered to be in an emergency and shall restore operations to respect proven reliable power system limits within 30 minutes.			X																Main Transmission System	NPCC RRP	TOP
TOP-004-1	05.	Each Transmission Operator shall make every effort to remain connected to the Interconnection. If the Transmission Operator determines that by remaining interconnected, it is in imminent danger of violating an IROL or SOL, the Transmission Operator may take such actions, as it deems necessary, to protect its area.			X																Main Transmission System	NPCC C-20	TOP
TOP-004-1	06.	TOP, individually and jointly with other TOP, shall develop, maintain, and implement formal policies and procedures to provide for transmission reliability. These policies and procedures shall address the execution and coordination of activities that impact inter- and intra-Regional reliability, including:			X																Main Transmission System	NPCC A-03	TOP
TOP-004-1	06.1	Equipment ratings.			X																Main Transmission System	NPCC A-02 NPCC C-20	TOP
TOP-004-1	06.2	Monitoring and controlling voltage levels and real and reactive power flows.			X																Main Transmission System	NPCC C-20	TOP
TOP-004-1	06.3	Switching transmission elements.			X																Main Transmission System	NPCC RRP	TOP
TOP-004-1	06.4	Planned outages of transmission elements.			X																Main Transmission System	NPCC A-02	TOP
TOP-004-1	06.5	Development of IROLs and SOLs.			X																Main Transmission System	NPCC RRP	TOP
TOP-004-1	06.6	Responding to IROL and SOL violations.			X																Main Transmission System	NPCC C-20	TOP
TOP-005-1	0.	Operational Reliability Information		X	X	X													X		Main Transmission System		Adopted by NERC: 2006-02-07
TOP-005-1	01.	Each Transmission Operator and Balancing Authority shall provide its Reliability Coordinator with the operating data that the Reliability Coordinator requires to perform operational reliability assessments and to coordinate reliable operations within the Reliability Coordinator Area.			X	X															Main Transmission System	NPCC RRP	BA, TOP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
TOP-005-1	01.1	Each Reliability Coordinator shall identify the data requirements from the list in Attachment 1-TOP-005-0 "Electric System Reliability Data" and any additional operating information requirements relating to operation of the bulk power system within the Reliability Coordinator Area.		X																		Main Transmission System		RC
TOP-005-1	02.	As a condition of receiving data from the Interregional Security Network (ISN), each ISN data recipient shall sign the NERC Confidentiality Agreement for "Electric System Reliability Data."		X	X	X																Main Transmission System	NPCC RRP	BA, RC, TOP
TOP-005-1	03.	Upon request, each Balancing Authority and Transmission Operator shall provide to other Balancing Authorities and Transmission Operators with immediate responsibility for operational reliability, the operating data that are necessary to allow these Balancing Authorities and Transmission Operators to perform operational reliability assessments and to coordinate reliable operations. Balancing Authorities and Transmission Operators shall provide the types of data as listed in Attachment 1-TOP-005-0 "Electric System Reliability Data," unless otherwise agreed to by the Balancing Authorities and Transmission Operators with immediate responsibility for operational reliability.			X	X																Main Transmission System	NPCC RRP	BA, TOP
TOP-005-1	04.	Each Purchasing-Selling Entity shall provide information as requested by its Host Balancing Authorities and Transmission Operators to enable them to conduct operational reliability assessments and coordinate reliable operations.																X				Main Transmission System	NPCC C-13	PSE
TOP-005-1	Att. 1	Attachment 1-TOP-005-0 Electric System Reliability Data		X	X	X																Main Transmission System		BA, RC, TOP
TOP-006-1	0.	Monitoring System Conditions		X	X	X							X									Main Transmission System		Adopted by NERC: 2006-11-01
TOP-006-1	01.	Each Transmission Operator and Balancing Authority shall know the status of all generation and transmission resources available for use.			X	X																Main Transmission System	NPCC RRP	BA, TOP
TOP-006-1	01.1	Each Generator Operator shall inform its Host Balancing Authority and the Transmission Operator of all generation resources available for use.											X									Main Transmission System	NPCC A-02	GOP-1, GOP-2
TOP-006-1	01.2	Each Transmission Operator and Balancing Authority shall inform the Reliability Coordinator and other affected Balancing Authorities and Transmission Operators of all generation and transmission resources available for use.			X	X																Main Transmission System	NPCC RRP NPCC A-02	BA, TOP
TOP-006-1	02.	Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall monitor applicable transmission line status, real and reactive power flows, voltage, load-tap-changer settings, and status of rotating and static reactive resources.		X	X	X																Main Transmission System	NPCC B-03	BA, RC, TOP
TOP-006-1	03.	Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall provide appropriate technical information concerning protective relays to their operating personnel.		X	X	X																Main Transmission System		BA, RC, TOP
TOP-006-1	04.	Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall have information, including weather forecasts and past load patterns, available to predict the system's near-term load pattern.		X	X	X																Main Transmission System		BA, RC, TOP
TOP-006-1	05.	Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall use monitoring equipment to bring to the attention of operating personnel important deviations in operating conditions and to indicate, if appropriate, the need for corrective action. Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall use monitoring equipment to bring to the attention of operating personnel important deviations in operating conditions and to indicate, if appropriate, the need for corrective action.		X	X	X																Main Transmission System	NPCC RRP	BA, RC, TOP
TOP-006-1	06.	Each Balancing Authority and Transmission Operator shall use sufficient metering of suitable range, accuracy and sampling rate (if applicable) to ensure accurate and timely monitoring of operating conditions under both normal and emergency situations.		X	X	X																Main Transmission System	NPCC A-03 NPCC RRP	BA, RC, TOP
TOP-006-1	07.	Each Reliability Coordinator, Transmission Operator, and Balancing Authority shall monitor system frequency.		X	X	X																Main Transmission System	NPCC A-03 NPCC RRP	BA, RC, TOP
TOP-007-0	0.	Reporting SOL and IROL Violations		X	X																	Main Transmission System		Adopted by NERC: 2005-02-08
TOP-007-0	01.	A Transmission Operator shall inform its Reliability Coordinator when an IROL or SOL has been exceeded and the actions being taken to return the system to within limits.			X																	Main Transmission System	NPCC C-20	TOP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities	
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC
TOP-007-0	02.	Following a Contingency or other event that results in an IROL violation, the Transmission Operator shall return its transmission system to within IROL as soon as possible, but not longer than 30 minutes.			X																Main Transmission System		TOP
TOP-007-0	03.	A TOP shall take all appropriate actions up to and including shedding firm load, or directing the shedding of firm load, in order to comply with Requirement R2.			X																Main Transmission System	NPCC C-20	TOP
TOP-007-0	04.	The Reliability Coordinator shall evaluate actions taken to address an IROL or SOL violation and, if the actions taken are not appropriate or sufficient, direct actions required to return the system to within limits.		X																	Main Transmission System	NPCC RRP	RC
TOP-008-1	0.	Response to Transmission Limit Violations			X																Main Transmission System		Adopted by NERC: 2006-11-01
TOP-008-1	01.	The Transmission Operator experiencing or contributing to an IROL or SOL violation shall take immediate steps to relieve the condition, which may include shedding firm load.			X																Main Transmission System	NPCC C-20	TOP
TOP-008-1	02.	Each Transmission Operator shall operate to prevent the likelihood that a disturbance, action, or inaction will result in an IROL or SOL violation in its area or another area of the Interconnection. In instances where there is a difference in derived operating limits, the Transmission Operator shall always operate the Bulk Electric System to the most limiting parameter.			X																Main Transmission System	NPCC RRP	TOP
TOP-008-1	03.	The Transmission Operator shall disconnect the affected facility if the overload on a transmission facility or abnormal voltage or reactive condition persists and equipment is endangered. In doing so, the Transmission Operator shall notify its Reliability Coordinator and all neighboring Transmission Operators impacted by the disconnection prior to switching, if time permits, otherwise, immediately thereafter.			X																Main Transmission System	NPCC C-20	TOP
TOP-008-1	04.	The Transmission Operator shall have sufficient information and analysis tools to determine the cause(s) of SOL violations. This analysis shall be conducted in all operating timeframes. The TOP shall use the results of these analyses to immediately mitigate the SOL violation.			X																Main Transmission System	NPCC RRP	TOP
TPL-001-0	0.	System Performance Under Normal (No Contingency) Conditions									X	X									BULK Power System		Adopted by NERC: 2005-02-08
TPL-001-0	01.	The Planning Authority and Transmission Planner shall each demonstrate through a valid assessment that its portion of the interconnected transmission system is planned such that, with all transmission facilities in service and with normal (pre-contingency) operating procedures in effect, the Network can be operated to supply projected customer demands and projected Firm (non-recallable reserved) Transmission Services at all Demand levels over the range of forecast system demands, under the conditions defined in Category A of Table I. To be considered valid, the Planning Authority and Transmission Planner assessments shall:										X	X								BULK Power System	See below	PA TP
TPL-001-0	01.1	Be made annually										X	X								BULK Power System	NPCC B-04	PA TP
TPL-001-0	01.2	Be conducted for near-term (years one through five) and longer-term (years six through ten) planning horizons.										X	X								BULK Power System	NPCC B-04	PA TP
TPL-001-0	01.3	Be supported by a current or past study and/or system simulation testing that addresses each of the following categories (R1.3.1, R1.3.2 etc.), showing system performance following Category A of Table 1 (no contingencies). The specific elements selected (from each of the following categories) shall be acceptable to the associated Regional Reliability Organization(s).										X	X								BULK Power System	NPCC A-02	PA TP
TPL-001-0	01.3.1	Cover critical system conditions and study years as deemed appropriate by the entity performing the study.										X	X								BULK Power System	NPCC B-04	PA TP
TPL-001-0	01.3.2	Be conducted annually unless changes to system conditions do not warrant such analyses.										X	X								BULK Power System	NPCC B-04	PA TP
TPL-001-0	01.3.3	Be conducted beyond the five-year horizon only as needed to address identified marginal conditions that may have longer lead-time solutions.										X	X								BULK Power System	NPCC B-04	PA TP
TPL-001-0	01.3.4	Have established normal (pre-contingency) operating procedures in place.										X	X								BULK Power System	NPCC A-02	PA TP
TPL-001-0	01.3.5	Have all projected firm transfers modeled.										X	X								BULK Power System	NPCC A-02 NPCC B-04	PA TP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
TPL-001-0	01.3.6	Be performed for selected demand levels over the range of forecast system demands.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-001-0	01.3.7	Demonstrate that system performance meets Table 1 for Category A (no contingencies).									X	X										BULK Power System	NPCC A-02	PA TP
TPL-001-0	01.3.8	Include existing and planned facilities.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-001-0	01.3.9	Include Reactive Power resources to ensure that adequate reactive resources are available to meet system performance.									X	X										BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-001-0	01.4	Address any planned upgrades needed to meet the performance requirements of Category A.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-001-0	02.	When system simulations indicate an inability of the systems to respond as prescribed in Reliability Standard TPL-001-0 R1, the Planning Authority and Transmission Planner shall each:									X	X										BULK Power System	NPCC B-04	PA TP
TPL-001-0	02.1	Provide a written summary of its plans to achieve the required system performance as described above throughout the planning horizon:									X	X										BULK Power System	NPCC B-04	PA TP
TPL-001-0	02.1.1	Including a schedule for implementation									X	X										BULK Power System		PA TP
TPL-001-0	02.1.2	Including a discussion of expected required in-service dates of facilities									X	X										BULK Power System		PA TP
TPL-001-0	02.1.3	Consider lead times necessary to implement plans									X	X										BULK Power System		PA TP
TPL-001-0	02.2	Review, in subsequent annual assessments, (where sufficient lead time exists), the continuing need for identified system facilities. Detailed implementation plans are not needed									X	X										BULK Power System	NPCC B-04	PA TP
TPL-001-0	03.	The Planning Authority and Transmission Planner shall each document the results of these reliability assessments and corrective plans and shall annually provide these to its respective NERC Regional Reliability Organization(s), as required by the Regional Reliability Organization									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	0.	System Performance Following Loss of a Single Bulk Electric System Element (Category B)									X	X										BULK Power System		Adopted by NERC: 2005-02-08
TPL-002-0	01.	The Planning Authority and Transmission Planner shall each demonstrate through a valid assessment that its portion of the interconnected transmission system is planned such that, with all transmission facilities in service and with normal (pre-contingency) operating procedures in effect, the Network can be operated to supply projected customer demands and projected Firm (non-recallable reserved) Transmission Services at all Demand levels over the range of forecast system demands, under the conditions defined in Category B of Table I. To be considered valid, the Planning Authority and Transmission Planner assessments shall:									X	X										BULK Power System	See below	PA TP
TPL-002-0	01.1	Be made annually									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.2	Be conducted for near-term (years one through five) and longer-term (years six through ten) planning horizons.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.3	Be supported by a current or past study and/or system simulation testing that addresses each of the following categories (R1.3.1, R1.3.2 etc.), showing system performance following Category B of Table 1 (single contingencies). The specific elements selected (from each of the following categories) shall be acceptable to the associated Regional Reliability Organization(s).									X	X										BULK Power System	NPCC A-02	PA TP
TPL-002-0	01.3.1	Be performed and evaluated only for those Category B contingencies that would produce the more severe System results or impacts. The rationale for the contingencies selected for evaluation shall be available as supporting information. An explanation of why the remaining simulations would produce less severe system results shall be available as supporting information.									X	X										BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-002-0	01.3.10	Include the effects of existing and planned protection systems, including any backup or redundant systems.									X	X										BULK Power System	NPCC A-02	PA TP
TPL-002-0	01.3.11	Include the effects of existing and planned control devices.									X	X										BULK Power System	NPCC B-04	PA TP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
TPL-002-0	01.3.12	Include the planned (including maintenance) outage of any bulk electric equipment (including protection systems or their components) at those demand levels for which planned (including maintenance) outages are performed.									X	X										BULK Power System	NPCC A-02	PA TP
TPL-002-0	01.3.2	Cover critical system conditions and study years as deemed appropriate by the responsible entity									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.3.3	Be conducted annually unless changes to system conditions do not warrant such analyses									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.3.4	Be conducted beyond the five-year horizon only as needed to address identified marginal conditions that may have longer lead-time solutions.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.3.5	Have all projected firm transfers modeled.									X	X										BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-002-0	01.3.6	Be performed and evaluated for selected demand levels over the range of forecast system demands.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.3.7	Demonstrate that system performance meets Category B contingencies.									X	X										BULK Power System	NPCC A-02	PA TP
TPL-002-0	01.3.8	Include existing and planned facilities.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.3.9	Include Reactive Power resources to ensure that adequate reactive resources are available to meet system performance.									X	X										BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-002-0	01.4	Address any planned upgrades needed to meet the performance requirements of Category B Table I.									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	01.5	Consider all contingencies applicable to Category B.									X	X										BULK Power System	NPCC A-02	PA TP
TPL-002-0	02.	When system simulations indicate an inability of the systems to respond as prescribed in Reliability Standard TPL-002-0 R1, the Planning Authority and Transmission Planner shall each (see R2.1 & R2.2 below for details):									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	02.1	Provide a written summary of its plans to achieve the required system performance as described above throughout the planning horizon (see below):									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	02.1.1	Including a schedule for implementation									X	X										BULK Power System		PA TP
TPL-002-0	02.1.2	Including a discussion of expected required in-service dates of facilities									X	X										BULK Power System		PA TP
TPL-002-0	02.1.3	Consider lead times necessary to implement plans									X	X										BULK Power System		PA TP
TPL-002-0	02.2	Review, in subsequent annual assessments, (where sufficient lead time exists), the continuing need for identified system facilities. Detailed implementation plans are not needed									X	X										BULK Power System	NPCC B-04	PA TP
TPL-002-0	03.	The Planning Authority and Transmission Planner shall each document the results of these reliability assessments and corrective plans and shall annually provide these to its respective NERC Regional Reliability Organization(s), as required by the Regional Reliability Organization									X	X										BULK Power System	NPCC B-04	PA TP
TPL-003-0	0.	System Performance Following Loss of a Two or More Bulk Electric System Element (Category C).									X	X										BULK Power System		Adopted by NERC: 2005-02-08
TPL-003-0	01.	The PA and TPI shall each demonstrate through a valid assessment that its portion of the interconnected transmission system is planned such that, with all transmission facilities in service and with normal (pre-contingency) operating procedures in effect, the Network can be operated to supply projected customer demands and projected Firm (non-recallable reserved) Transmission Services at all Demand levels over the range of forecast system demands, under the conditions defined in Category C of Table I. The controlled interruption of customer Demand, the planned removal of generators, or the Curtailment of firm power transfers may be necessary to meet this Standard. To be considered valid, the PA and Transmission Planner assessments shall :									X	X										BULK Power System	See below	PA TP
TPL-003-0	01.1	Be made annually									X	X										BULK Power System	NPCC B-04	PA TP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities				
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP				PSE	NNU / NERC		
TPL-003-0	01.2	Be conducted for near-term (years one through five) and longer-term (years six through ten) planning horizons.									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.3	Be supported by a current or past study and/or system simulation testing that addresses each of the following categories (R1.3.1, R1.3.2 etc.), showing system performance following Category C of Table 1 (multiple contingencies). The specific elements selected (from each of the following categories) shall be acceptable to the associated Regional Reliability Organization(s).									X	X											BULK Power System	NPCC A-02	PA TP
TPL-003-0	01.3.1	Be performed and evaluated only for those Category C contingencies that would produce the more severe System results or impacts. The rationale for the contingencies selected for evaluation shall be available as supporting information. An explanation of why the remaining simulations would produce less severe system results shall be available as supporting information.									X	X											BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-003-0	01.3.10	Include the effects of existing and planned protection systems, including any backup or redundant systems.									X	X											BULK Power System	NPCC A-02	PA TP
TPL-003-0	01.3.11	Include the effects of existing and planned control devices.									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.3.12	Include the planned (including maintenance) outage of any bulk electric equipment (including protection systems or their components) at those demand levels for which planned (including maintenance) outages are performed.									X	X											BULK Power System	NPCC A-02	PA TP
TPL-003-0	01.3.2	Cover critical system conditions and study years as deemed appropriate by the responsible entity									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.3.3	Be conducted annually unless changes to system conditions do not warrant such analyses									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.3.4	Be conducted beyond the five-year horizon only as needed to address identified marginal conditions that may have longer lead-time solutions.									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.3.5	Have all projected firm transfers modeled.									X	X											BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-003-0	01.3.6	Be performed and evaluated for selected demand levels over the range of forecast system demands.									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.3.7	Demonstrate that system performance meets Table 1 for Category C contingencies.									X	X											BULK Power System	NPCC A-02	PA TP
TPL-003-0	01.3.8	Include existing and planned facilities.									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.3.9	Include Reactive Power resources to ensure that adequate reactive resources are available to meet system performance.									X	X											BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-003-0	01.4	Address any planned upgrades needed to meet the performance requirements of Category C.									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	01.5	Consider all contingencies applicable to Category C.									X	X											BULK Power System	NPCC A-02	PA TP
TPL-003-0	02.	When system simulations indicate an inability of the systems to respond as prescribed in Reliability Standard TPL-003-0 R1, the Planning Authority and Transmission Planner shall each (see R2.1 & R2.2 below for details):									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	02.1	Provide a written summary of its plans to achieve the required system performance as described above throughout the planning horizon (see below):									X	X											BULK Power System	NPCC B-04	PA TP
TPL-003-0	02.1.1	Including a schedule for implementation									X	X											BULK Power System		PA TP
TPL-003-0	02.1.2	Including a discussion of expected required in-service dates of facilities									X	X											BULK Power System		PA TP
TPL-003-0	02.1.3	Consider lead times necessary to implement plans									X	X											BULK Power System		PA TP
TPL-003-0	02.2	Review, in subsequent annual assessments, (where sufficient lead time exists), the continuing need for identified system facilities. Detailed implementation plans are not needed									X	X											BULK Power System	NPCC B-04	PA TP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities				
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC			
TPL-003-0	03.	The Planning Authority and Transmission Planner shall each document the results of these reliability assessments and corrective plans and shall annually provide these to its respective NERC Regional Reliability Organization(s), as required by the Regional Reliability Organization									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	0.	System Performance Following Extreme Events Resulting in the Loss of Two or More Bulk Electric System Element (Category D)									X		X											BULK Power System		Adopted by NERC: 2005-02-08
TPL-004-0	01.	The Planning Authority and Transmission Planner shall each demonstrate through a valid assessment that its portion of the interconnected transmission system is evaluated for the risks and consequences of a number of each of the extreme contingencies that are listed under Category D of Table 1. To be valid, the Planning Authority's and Transmission Planner's assessment shall:									X		X											BULK Power System	NPCC A-02	PA TP
TPL-004-0	01.1	Be made annually									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	01.2	Be conducted for near-term (years one through five).									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	01.3	Be supported by a current or past study and/or system simulation testing that addresses each of the following categories (R1.3.1, R1.3.2 etc.), showing system performance following Category D of Table 1 (multiple contingencies). The specific elements selected (from each of the following categories) shall be acceptable to the associated Regional Reliability Organization(s).									X		X											BULK Power System	NPCC A-02	PA TP
TPL-004-0	01.3.1	Be performed and evaluated only for those Category D contingencies that would produce the more severe system results or impacts. The rationale for the contingencies selected for evaluation shall be available as supporting information. An explanation of why the remaining simulations would produce less severe system results shall be available as supporting information.									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	01.3.2	Cover critical system conditions and study years as deemed appropriate by the responsible entity									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	01.3.3	Be conducted annually unless changes to system conditions do not warrant such analyses									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	01.3.4	Have all projected firm transfers modeled.									X		X											BULK Power System	NPCC A-02	PA TP
TPL-004-0	01.3.5	Include existing and planned facilities.									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	01.3.6	Include Reactive Power resources to ensure that adequate reactive resources are available to meet system performance.									X		X											BULK Power System	NPCC A-02 NPCC B-04	PA TP
TPL-004-0	01.3.7	Include the effects of existing and planned protection systems, including any backup or redundant systems.									X		X											BULK Power System	NPCC A-02	PA TP
TPL-004-0	01.3.8	Include the effects of existing and planned control devices.									X		X											BULK Power System	NPCC B-04	PA TP
TPL-004-0	01.3.9	Include the planned (including maintenance) outage of any bulk electric equipment (including protection systems or their components) at those demand levels for which planned (including maintenance) outages are performed.									X		X											BULK Power System	NPCC A-02	PA TP
TPL-004-0	01.4	Consider all contingencies applicable to Category D.									X		X											BULK Power System	NPCC A-02	PA TP
TPL-004-0	02.	The Planning Authority and Transmission Planner shall each document the results of these reliability assessments and corrective plans and shall annually provide these to its respective NERC Regional Reliability Organization(s), as required by the Regional Reliability Organization									X		X											BULK Power System	NPCC B-04	PA TP
VAR-001-1	0.	Voltage and Reactive Control			X															X				Main Transmission System		Adopted by NERC: 2006-08-02
VAR-001-1	01.	Each Transmission Operator, individually and jointly with other Transmission Operators, shall ensure that formal policies and procedures are developed, maintained, and implemented for monitoring and controlling voltage levels and Mvar flows within their individual areas and with the areas of neighboring Transmission Operators.			X																			Main Transmission System		TOP

Reliability Standards Application Matrix based on requirements, according to functions, systems and facilities identified in the Registry of Entities and Facilities subject to Reliability Standards

Standard number	E	Title / Requirements	Function subject to Reliability Standards:																	Applicable System(s) or Facilities in Québec	Reference Documents	Entities subject to Reliability Standards in Québec according to the Registry of Entities and Facilities		
			RRO	RC	TOP	BA	IA	RSG	TO	TP	TSP	PA	GOP	GO	NUC OP	RP	LSE	DP	PSE				NNU / NERC	
VAR-001-1	02.	Each Transmission Operator shall acquire sufficient reactive resources within its area to protect the voltage levels under normal and Contingency conditions. This includes the Transmission Operator's share of the reactive requirements of interconnecting transmission circuits.			X																	Main Transmission System	NPCC A-02	TOP
VAR-001-1	03.	The Transmission Operator shall specify criteria that exempts generators from compliance with the requirements defined in Requirement 4, and Requirement 6.1.			X																	Main Transmission System		TOP
VAR-001-1	03.1	Each Transmission Operator shall maintain a list of generators in its area that are exempt from following a voltage or Reactive Power schedule.			X																	Main Transmission System		TOP
VAR-001-1	03.2	For each generator that is on this exemption list, the Transmission Operator shall notify the associated Generator Owner.			X																	Main Transmission System		TOP
VAR-001-1	04.	Each Transmission Operator shall specify a voltage or Reactive Power schedule ¹ at the interconnection between the generator facility and the Transmission Owner's facilities to be maintained by each generator. The Transmission Operator shall provide the voltage or Reactive Power schedule to the associated Generator Operator and direct the Generator Operator to comply with the schedule in automatic voltage control mode (AVR in service and controlling voltage). 1. The voltage schedule is a target voltage to be maintained within a tolerance band during a specified period			X																	Main Transmission System		TOP
VAR-001-1	05.	Each Purchasing-Selling Entity shall arrange for (self-provide or purchase) reactive resources to satisfy its reactive requirements identified by its Transmission Service Provider.																	X			Main Transmission System	NPCC A-02	PSE
VAR-001-1	06.	The Transmission Operator shall know the status of all transmission Reactive Power resources, including the status of voltage regulators and power system stabilizers.			X																	Main Transmission System	NPCC RRP	TOP
VAR-001-1	06.1	When notified of the loss of an automatic voltage regulator control, the Transmission Operator shall direct the Generator Operator to maintain or change either its voltage schedule or its Reactive Power schedule.			X																	Main Transmission System		TOP
VAR-001-1	07.	The Transmission Operator shall be able to operate or direct the operation of devices necessary to regulate transmission voltage and reactive flow.			X																	Main Transmission System	NPCC B-03	TOP
VAR-001-1	08.	Each Transmission Operator shall operate or direct the operation of capacitive and inductive reactive resources within its area – including reactive generation scheduling; transmission line and reactive resource switching; and, if necessary, load shedding – to maintain system and interconnection voltages within established limits.			X																	Main Transmission System	NPCC B-03	TOP
VAR-001-1	09.	Each Transmission Operator shall maintain reactive resources to support its voltage under first Contingency conditions.			X																	Main Transmission System	NPCC A-02	TOP
VAR-001-1	09.1	Each Transmission Operator shall disperse and locate the reactive resources so that the resources can be applied effectively and quickly when Contingencies occur.			X																	Main Transmission System		TOP
VAR-001-1	10.	Each Transmission Operator shall correct IROL or SOL violations resulting from reactive resource deficiencies (IROL violations must be corrected within 30 minutes) and complete the required IROL or SOL violation reporting.			X																	Main Transmission System	NPCC RRP	TOP
VAR-001-1	11.	After consultation with the Generator Owner regarding necessary step-up transformer tap changes, the Transmission Operator shall provide documentation to the Generator Owner specifying the required tap changes, a timeframe for making the changes, and technical justification for these changes.			X																	Main Transmission System		TOP
VAR-001-1	12.	The Transmission Operator shall direct corrective action, including load reduction, necessary to prevent voltage collapse when reactive resources are insufficient.			X																	Main Transmission System	NPCC B-03	TOP
VAR-002-1a	0.	Generator Operation for Maintaining Network Voltage Schedules												X	X							Main Transmission System		Adopted by NERC: 2006-08-02
VAR-002-1a	01.	The Generator Operator shall operate each generator connected to the interconnected transmission system in the automatic voltage control mode (automatic voltage regulator in service and controlling voltage) unless the Generator Operator has notified the Transmission Operator.												X								Main Transmission System		GOP-1, GOP-2

